

Platform Flash PROMs for Spartan-3A DSP FPGA

Spartan™-3A FPGA	Configuration Bits	ISP PROM Solution	VO20	FS48
XC3SD1800A	8,197,280	XCF08P	—	Y
XC3SD3400A	11,718,304	XCF16P	—	Y

Platform Flash PROMs for Spartan-3A FPGA

Spartan-3A FPGA	Configuration Bits	ISP PROM Solution	VO20	FS48
XC3S50A	437,312	XCF01S	Y	—
XC3S200A	1,196,128	XCF02S	Y	—
XC3S400A	1,886,560	XCF02S	Y	—
XC3S700A	2,732,640	XCF04S	Y	—
XC3S1400A	4,755,296	XCF08P	—	Y

Platform Flash PROMs for Spartan-3E FPGA

Spartan-3E FPGA	Configuration Bits	ISP PROM Solution	VO20	FS48
XC3S100E	581,344	XCF01S	Y	—
XC3S250E	1,353,728	XCF01S	Y	—
XC3S500E	2,270,208	XCF02S	Y	—
XC3S1200E	3,837,184	XCF04S	Y	—
XC3S1600E	5,964,672	XCF08P	—	Y

Platform Flash PROMs for Spartan-3 FPGA

Spartan-3 FPGA	Configuration Bits	ISP PROM Solution	VO20	FS48
XC3S50	439,264	XCF01S	Y	—
XC3S200	1,353,728	XCF01S	Y	—
XC3S400	1,699,136	XCF02S	Y	—
XC3S1000	3,223,488	XCF04S	Y	—
XC3S1500	5,214,784	XCF08P	—	Y
XC3S2000	7,673,024	XCF08P	—	Y
XC3S4000	11,316,864	XCF016P	—	Y
XC3S5000	13,271,936	XCF016P	—	Y

Note: The number of configuration bits represents the typical cases. Certain BitGen options can vary the number of configuration bits.