0.1. ORBIS32/64

l.add Add Signed

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x0
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.add rD,rA,rB
```

Description:

The contents of general-purpose register rA is added to the contents of general-purpose register rB to form the result. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] + rB[31:0]
   SR[CY] <- carry
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] + rB[63:0]
   SR[CY] <- carry
   SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.addc — Add Signed and Carry

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x1
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.addc rD,rA,rB
```

Description:

The contents of general-purpose register rA is added to the contents of general-purpose register rB and carry SR[CY] to form the result. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] + rB[31:0]
   SR[CY] <- carry
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] + rB[63:0]
   SR[CY] <- carry
   SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.addi Add Immediate Signed

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x27	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.addi rD,rA,I
```

Description:

Immediate is signed-extended and added to the contents of general-purposeregister rA to form the result. The result is placed into general-purposeregister rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] + exts(Immediate)
   SR[CY] <- carry
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] + exts(Immediate)
   SR[CY] <- carry
   SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.and And

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x3
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.and rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical AND operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] AND rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] AND rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.andi And with Immediate Half Word

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x29	D	A	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.andi rD,rA,K
```

Description:

Immediate is zero-extended and combined with the contents of general-purpose register rB in a bit-wise logical AND operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rB[31:0] AND extz(Immediate)
```

64-bit Implementation:

```
rD[63:0] <- rB[63:0] AND extz(Immediate)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.bf Branch if Flag

31 26	25 0
opcode 0x4	N
6 bits	26 bits

Format:

```
l.bf N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the branch. If the compare flag is set, then the program branches to EA with a delay of one instruction.

32-bit Implementation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag set
```

64-bit Implementation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag set
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.bnf Branch if No Flag

31 26	25 0
opcode 0x3	N
6 bits	26 bits

Format:

```
l.bnf N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the branch. If the compare flag is cleared, then the program branches to EA with a delay of one instruction.

32-bit Implementation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag cleared
```

64-bit Implementation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag cleared
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.brk Breakpoint

31 16	15 0
opcode 0x2100	K
16 bits	16 bits

Format:

```
l.brk K
```

Description:

Execution of the breakpoint instruction results in the breakpoint exception. Breakpoint exception is a request to the operating system and to the debug facility to execute certain debug services. Immediate is used by the debug to identify which breakpoint it is.

32-bit Implementation:

```
breakpoint-exception(K)
```

64-bit Implementation:

```
breakpoint-exception(K)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.csync Context Syncronization



Format:

```
l.csync
```

Description:

Execution of context synchronization instruction results in completion of all operations inside RISC and flush of the instruction pipelines. When all operations are complete, RISC core resumes with empty instruction pipeline and fresh context in all units (MMU for example).

32-bit Implementation:

```
context-synchronization
```

64-bit Implementation:

```
context-synchronization
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust1 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x1c	reserved
6 bits	26 bits

Format:

```
l.cust1
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust2 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x1d	reserved
6 bits	26 bits

Format:

```
l.cust2
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust3 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x1e	reserved
6 bits	26 bits

Format:

```
l.cust3
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust4 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x1f	reserved
6 bits	26 bits

Format:

```
l.cust4
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust5 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x3c	reserved
6 bits	26 bits

Format:

```
l.cust5
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust6 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x3d	reserved
6 bits	26 bits

Format:

```
l.cust6
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust7 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x3e	reserved
6 bits	26 bits

Format:

```
l.cust7
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.cust8 Reserved for ORBIS32/64 Custom Instructions

31 26	25 0
opcode 0x3f	reserved
6 bits	26 bits

Format:

```
l.cust8
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.div Divide Signed

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x9
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.div rD,rA,rB
```

Description:

The contents of general-purpose register rA are divided by the contents of general-purpose register rB and the result is placed into general-purpose register rD. Both operands are treated as signed integers. A divide by zero flag is set when the divisor is zero.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] / rB[31:0]
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] / rB[63:0]
   SR[OV] <- overflow
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.divu Divide Unsigned

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xa
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.divu rD,rA,rB
```

Description:

The contents of general-purpose register rA are divided by the contents of general-purpose register rA and the result is placed into general-purpose register rD. Both operands are treated as unsigned integers. A divide by zero flag is set when the divisor is zero.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] / rB[31:0]
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] / rB[63:0]
   SR[OV] <- overflow
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.extbs Extend Byte with Sign

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x1	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extbs rD,rA,rB
```

Description:

Bit 7 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order eight bits of general-purpose register rA are copied from low-order eight bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:8] <- rA[7]
   rD[7:0] <- rA[7:0]
```

64-bit Implementation:

```
rD[63:8] <- rA[7]
   rD[7:0] <- rA[7:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.extbz Extend Byte with Zero

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extbz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order eight bits of general-purpose register rA are copied into low-order eight bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:8] <- 0
   rD[7:0] <- rA[7:0]
```

64-bit Implementation:

```
rD[63:8] <- 0
   rD[7:0] <- rA[7:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.exths Extend Half Word with Sign

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.exths rD,rA,rB
```

Description:

Bit 15 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order 16 bits of general-purpose register rA are copied into low-order 16 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:16] <- rA[15]
   rD[15:0] <- rA[15:0]
```

64-bit Implementation:

```
rD[63:16] <- rA[15]
   rD[15:0] <- rA[15:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.exthz Extend Half Word with Zero

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x2	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.exthz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order 16 bits of general-purpose register rA are copied into low-order 16 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:16] <- 0
   rD[15:0] <- rA[15:0]
```

64-bit Implementation:

```
rD[63:16] <- 0
   rD[15:0] <- rA[15:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.extws Extend Word with Sign

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xd
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extws rD,rA,rB
```

Description:

Bit 31 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order 32 bits of general-purpose register rA are copied from low-order 32 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0]
```

64-bit Implementation:

```
rD[63:32] <- rA[31]
   rD[31:0] <- rA[31:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS64 II	Optional

l.extwz Extend Word with Zero

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x2	reserved	opcode 0xd
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extwz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order 32 bits of general-purpose register rA are copied into low-order 32 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0]
```

64-bit Implementation:

```
rD[63:32] <- 0
   rD[31:0] <- rA[31:0]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORBIS64 II	Optional

l.j Jump

31 26	25 0
opcode 0x0	N
6 bits	26 bits

Format:

```
l.j N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction.

32-bit Implementation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

64-bit Implementation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.jal Jump and Link

31 26	25 0
opcode 0x1	N
6 bits	26 bits

Format:

```
l.jal N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction. The address of the instruction after the delay slot is placed in the link register.

32-bit Implementation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

64-bit Implementation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.jalr Jump and Link Register

31 26	25 16	15 . . . 11	10 0
opcode 0x12	reserved	B	reserved
6 bits	10 bits	5 bits	11 bits

Format:

```
l.jalr rB
```

Description:

The contents of general-purpose register rB is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction. The address of the instruction after the delay slot is placed in the link register.

32-bit Implementation:

```
PC <- rB
   LR <- DelayInsnAddr + 4
```

64-bit Implementation:

```
PC <- rB
   LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.jr Jump Register

31 26	25 16	15 . . . 11	10 0
opcode 0x11	reserved	B	reserved
6 bits	10 bits	5 bits	11 bits

Format:

```
l.jr rB
```

Description:

The contents of general-purpose register rB is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction.

32-bit Implementation:

```
PC <- rB
```

64-bit Implementation:

```
PC <- rB
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.lbs Load Byte and Extend with Sign

31 26	25 21	20 16	15 0
opcode 0x24	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lbs rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The byte in memory addressed by EA is loaded into the low-order eight bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 7 of the loaded value.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[7:0] <- (EA)[7:0]
   rD[31:8] <- rA[8]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[7:0] <- (EA)[7:0]
   rD[63:8] <- rA[8]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.lbz Load Byte and Extend with Zero

31 26	25 21	20 16	15 0
opcode 0x23	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lbz rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The byte in memory addressed by EA is loaded into the low-order eight bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[7:0] <- (EA)[7:0]
   rD[31:8] <- 0
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[7:0] <- (EA)[7:0]
   rD[63:8] <- 0
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.ld Load Double Word

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x20	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.ld rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The double word in memory addressed by EA is loaded into general-purpose register rD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[63:0] <- (EA)[63:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS64 I	Required

l.lhs Load Half Word and Extend with Sign

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x26	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lhs rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The half word in memory addressed by EA is loaded into the low-order 16 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 15 of the loaded value.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[15:0] <- (EA)[15:0]
   rD[31:16] <- rA[15]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[15:0] <- (EA)[15:0]
   rD[63:16] <- rA[15]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.lhz Load Half Word and Extend with Zero

31 26	25 21	20 16	15 0
opcode 0x25	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lhz rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The half word in memory addressed by EA is loaded into the low-order 16 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[15:0] <- (EA)[15:0]
   rD[31:16] <- 0
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[15:0] <- (EA)[15:0]
   rD[63:16] <- 0
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.lws Load Single Word and Extend with Sign

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x22	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lws rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The single word in memory addressed by EA is loaded into the low-order 32 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 31 of the loaded value.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[31:0] <- (EA)[31:0]
   rD[63:32] <- rA[31]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.lwz Load Single Word and Extend with Zero

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x21	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lwz rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The single word in memory addressed by EA is loaded into the low-order 32 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[31:0] <- (EA)[31:0]
   rD[63:32] <- 0
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.mac Multiply Signed and Accumulate

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x7
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.mac rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied and the result is truncated to 32 bits and added to the special-purpose registers MACHI and MACLO. All operands are treated as signed integers.

32-bit Implementation:

```
M[31:0] <- rA[31:0] * rB[31:0]
   MACHI[31:0]MACLO[31:0] <- M[31:0] + MACHI[31:0]MACLO[31:0]
   SR[OV] <- overflow
```

64-bit Implementation:

```
M[31:0] <- rA[63:0] * rB[63:0]
   MACHI[31:0]MACLO[31:0] <- M[31:0] + MACHI[31:0]MACLO[31:0]
   SR[OV] <- overflow
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.maci Multiply Immediate Signed and Accumulate

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2d	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.maci rD,rA,I
```

Description:

Immediate and the contents of general-purpose register rA are multiplied and the result is truncated to 32 bits and added to the special-purpose registers MACHI and MACLO. All operands are treated as signed integers.

32-bit Implementation:

```
M[31:0] <- rA[31:0] * Immediate
   MACHI[31:0]MACLO[31:0] <- M[31:0] + MACHI[31:0]MACLO[31:0]
   SR[OV] <- overflow
```

64-bit Implementation:

```
M[31:0] <- rA[63:0] * Immediate
   MACHI[31:0]MACLO[31:0] <- M[31:0] + MACHI[31:0]MACLO[31:0]
   SR[OV] <- overflow
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.mfspr Move From Special-Purpose Register

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x7	D	A	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.mfspr rD,rA,K
```

Description:

The contents of special register identified by the sum of general-purpose rA and zero-extended immediate are moved into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- spr(rA+extz(Immediate))
```

64-bit Implementation:

```
rD[63:0] <- spr(rA+extz(Immediate))
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.movhi Move Immediate High

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x6	D	reserved	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.movhi rD,K
```

Description:

16-bit immediate is zero-extended, shifted left by 16 bits and placed into general-purpose register rD.

32-bit Implementation:

```
rA[31:0] <- extz(Immediate) « 16
```

64-bit Implementation:

```
rA[63:0] <- extz(Immediate) « 16
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.msync Memory Syncronization



Format:

```
l.msync
```

Description:

Execution of memory synchronization instruction results in completion of all load/store operations before the RISC core continues.

32-bit Implementation:

```
memory-synchronization
```

64-bit Implementation:

```
memory-synchronization
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.mtspr Move To Special-Purpose Register

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x10	K	A	B	K
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.mtspr rA,rB,K
```

Description:

The contents of general-purpose register rB are moved into special register identified by the sum of general-purpose register rA and zero-extended immediate.

32-bit Implementation:

```
spr(rA+extz(Immediate)) <- rA[31:0]
```

64-bit Implementation:

```
spr(rA+extz(Immediate)) <- rA[31:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.mul Multiply Signed

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0x6
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.mul rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied and the result is truncated to destination register width and placed into general-purpose register rD. Both operands are treated as unsigned integers.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] * rB[31:0]
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] * rB[63:0]
   SR[OV] <- overflow
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.muli Multiply Immediate Signed

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2c	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.muli rD,rA,I
```

Description:

Immediate and the contents of general-purpose register rA are multiplied and the result is truncated to destination register width and placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] * Immediate
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] * Immediate
   SR[OV] <- overflow
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.mulu Multiply Unsigned

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0xb
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.mulu rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied and the result is truncated to destination register width and placed into general-purpose register rD. Both operands are treated as unsigned integers.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] * rB[31:0]
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] * rB[63:0]
   SR[OV] <- overflow
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.nop — No Operation

31 24	23 0
opcode 0x15	reserved
8 bits	24 bits

Format:

```
l.nop
```

Description:

This instruction does not do anything except it takes at least one clock cycle to complete. It is often used to fill delay slot gaps.

32-bit Implementation:

64-bit Implementation:

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.or Or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x4
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.or rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical OR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] OR rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] OR rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.ori Or with Immediate Half Word

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2a	D	A	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.ori rD,rA,K
```

Description:

Immediate is zero-extended and combined with the contents of general-purpose register rB in a bit-wise logical OR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rB[31:0] OR extz(Immediate)
```

64-bit Implementation:

```
rD[63:0] <- rB[63:0] OR extz(Immediate)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.psync Pipeline Syncronization



Format:

```
l.psync
```

Description:

Execution of pipeline synchronization instruction results in completion of all instructions that were fetched before l.psync instruction. Once all instructions are completed, instructions fetched after l.psync are flushed from the pipeline and fetched again.

32-bit Implementation:

```
pipeline-synchronization
```

64-bit Implementation:

```
pipeline-synchronization
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.rfe Return From Exception

31 26	25 0
opcode 0x9	reserved
6 bits	26 bits

Format:

```
l.rfe
```

Description:

Execution of this instruction restores the state of the processor prior to the exception.

32-bit Implementation:

```
state_restore()
```

64-bit Implementation:

```
state_restore()
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.ror Rotate Right

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x38
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.ror rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are rotated right. Result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-rB:0] <- rA[31:rB]
   rD[31:32-rB] <- rA[rB-1:0]
```

64-bit Implementation:

```
rD[63-rB:0] <- rA[63:rB]
   rD[63:64-rB] <- rA[rB-1:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.rori Rotate Right with Immediate

31 26	25 . . . 21	20 . . . 16	15 9	8 . 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x4	L
6 bits	5 bits	5 bits	7 bits	3 bits	6 bits

Format:

```
l.rori rD,rA,L
```

Description:

6-bit immediate specifies the number of bit positions the contents of general-purpose register rA are rotated right. Result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-L:0] <- rA[31:L]
   rD[31:32-L] <- rA[L-1:0]
```

64-bit Implementation:

```
rD[63-L:0] <- rA[63:L]
   rD[63:64-L] <- rA[L-1:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sb Store Byte

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x36	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sb I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The low-order 8 bits of general-purpose register rB are stored to memory location addressed by EA.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   (EA)[7:0] <- rB[7:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[7:0] <- rB[7:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sd Store Double Word

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x34	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sd I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The double word in general-purpose register rB is stored to memory location addressed by EA.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[63:0] <- rB[63:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS64 I	Required

l.sfeq Set Flag if Equal

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x720	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfeq rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] == rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] == rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfeqi Set Flag if Equal Immediate

31 21	20 . . . 16	15 0
opcode 0x5e0	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfeqi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] == rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] == rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfges Set Flag if Greater or Equal Than Signed

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72b	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfges rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfgesi Set Flag if Greater or Equal Than Immediate Signed

31 21	20 . . . 16	15 0
opcode 0x5eb	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgesi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfgeu Set Flag if Greater or Equal Than Unsigned

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x723	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfgeu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfgeui Set Flag if Greater or Equal Than Immediate Unsigned

31 21	20 . . . 16	15 0
opcode 0x5e3	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgeui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfgts Set Flag if Greater Than Signed

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72a	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfgts rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfgtsi Set Flag if Greater Than Immediate Signed

31 21	20 . . . 16	15 0
opcode 0x5ea	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgtsi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfgtu Set Flag if Greater Than Unsigned

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x722	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfgtu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfgtui Set Flag if Greater Than Immediate Unsigned

31 21	20 . . . 16	15 0
opcode 0x5e2	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgtui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfles Set Flag if Less or Equal Than Signed

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72d	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfles rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sflesi Set Flag if Less or Equal Than Immediate Signed

31 21	20 . . . 16	15 0
opcode 0x5ed	A	I
11 bits	5 bits	16 bits

Format:

```
l.sflesi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfleu Set Flag if Less or Equal Than Unsigned

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x725	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfleu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfleui Set Flag if Less or Equal Than Immediate Unsigned

31 21	20 . . . 16	15 0
opcode 0x5e5	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfleui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sflts Set Flag if Less Than Signed

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72c	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sflts rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfltsi Set Flag if Less Than Immediate Signed

31 21	20 . . . 16	15 0
opcode 0x5ec	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfltsi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfltu Set Flag if Less Than Unsigned

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x724	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfltu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfltui Set Flag if Less Than Immediate Unsigned

31 21	20 . . . 16	15 0
opcode 0x5e4	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfltui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sfne Set Flag if Not Equal

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x721	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfne rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] != rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] != rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sfnei Set Flag if Not Equal Immediate

31 21	20 . . . 16	15 0
opcode 0x5e1	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfnei rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- rA[31:0] != rB[31:0]
```

64-bit Implementation:

```
flag <- rA[63:0] != rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 II	Optional

l.sh Store Half Word

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x37	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sh I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The low-order 16 bits of general-purpose register rB are stored to memory location addressed by EA.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   (EA)[15:0] <- rB[15:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[15:0] <- rB[15:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sll Shift Left Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x8
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.sll rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are shifted left, inserting zeros into the low-order bits. Result is written into general-purpose rD.

32-bit Implementation:

```
rD[31:rB] <- rA[31-rB:0]
   rD[rB-1:0] <- 0
```

64-bit Implementation:

```
rD[63:rB] <- rA[63-rB:0]
   rD[rB-1:0] <- 0
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.slli Shift Left Logical with Immediate

31 26	25 . . . 21	20 . . . 16	15 9	8 . 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x0	L
6 bits	5 bits	5 bits	7 bits	3 bits	6 bits

Format:

```
l.slli rD,rA,L
```

Description:

6-bit immediate specifies the number of bit positions the contents of general-purpose register rA are shifted left, inserting zeros into the low-order bits. Result is written into general-purpose rD.

32-bit Implementation:

```
rD[31:L] <- rA[31-L:0]
   rD[L-1:0] <- 0
```

64-bit Implementation:

```
rD[63:L] <- rA[63-L:0]
   rD[L-1:0] <- 0
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sra Shift Right Arithmetic

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x28
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.sra rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are shifted right, sign-extending the high-order bits. Result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-rB:0] <- rA[31:rB]
   rD[31:32-rB] <- rB[31]
```

64-bit Implementation:

```
rD[63-rB:0] <- rA[63:rB]
   rD[63:64-rB] <- rB[63]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.srai Shift Right Arithmetic with Immediate

31 26	25 . . . 21	20 . . . 16	15 9	8 . 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x2	L
6 bits	5 bits	5 bits	7 bits	3 bits	6 bits

Format:

```
l.srai rD,rA,L
```

Description:

6-bit immediate specifies the number of bit positions the contents of general-purpose register rA are shifted right, sign-extending the high-order bits. Result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-L:0] <- rA[31:L]
   rD[31:32-L] <- rA[31]
```

64-bit Implementation:

```
rD[63-L:0] <- rA[63:L]
   rD[63:64-L] <- rA[63]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.srl Shift Right Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.srl rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are shifted right, inserting zeros into the high-order bits. Result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-rB:0] <- rA[31:rB]
   rD[31:32-rB] <- 0
```

64-bit Implementation:

```
rD[63-rB:0] <- rA[63:rB]
   rD[63:64-rB] <- 0
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.srli Shift Right Logical with Immediate

31 26	25 . . . 21	20 . . . 16	15 9	8 . 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x1	L
6 bits	5 bits	5 bits	7 bits	3 bits	6 bits

Format:

```
l.srli rD,rA,L
```

Description:

6-bit Immediate specifies the number of bit positions the contents of general-purpose register rA are shifted right, inserting zeros into the high-order bits. Result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-L:0] <- rA[31:L]
   rD[31:32-L] <- 0
```

64-bit Implementation:

```
rD[63-L:0] <- rA[63:L]
   rD[63:64-L] <- 0
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sub Subtract Signed

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x2
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.sub rD,rA,rB
```

Description:

The contents of general-purpose register rB is subtracted from the contents of general-purpose register rA to form the result. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] - rB[31:0]
   SR[CY] <- carry
   SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] - rB[63:0]
   SR[CY] <- carry
   SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sw Store Single Word

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x35	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sw I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The low-order 32 bits of general-purpose register rB are stored to memory location addressed by EA.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
   (EA)[31:0] <- rB[31:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[31:0] <- rB[31:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.sys System Call

31 16	15 0
opcode 0x2000	K
16 bits	16 bits

Format:

```
l.sys K
```

Description:

Execution of system call instruction results in the system call exception. System calls exception is a request to the operating system to provide operating system services. Immediate specifies which system service is required.

32-bit Implementation:

```
system-call-exception(K)
```

64-bit Implementation:

```
system-call-exception(K)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.xor Exclusive Or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x5
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.xor rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical XOR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] XOR rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] XOR rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

l.xori Exclusive Or with Immediate Half Word

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2b	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.xori rD,rA,I
```

Description:

Immediate is zero-extended and combined with the contents of general-purpose register rB in a bit-wise logical XOR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rB[31:0] XOR exts(Immediate)
```

64-bit Implementation:

```
rD[63:0] <- rB[63:0] XOR exts(Immediate)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORBIS32 I	Required

lf.add.d Add Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.add.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is added to the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] + vfrB[63:0]
```

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.add.s Add Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.add.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is added to the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] + vfrB[31:0]
```

64-bit Implementation:

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.cust1.d — Reserved for ORFPX64 Custom Instructions

31 26	25 8	7 . . 4	3 . . 0
opcode 0xc	reserved	opcode 0xe	reserved
6 bits	18 bits	4 bits	4 bits

Format:

```
lf.cust1.d
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORFPX64 II	Optional

lf.cust1.s — Reserved for ORFPX32 Custom Instructions

31 26	25 8	7 . . 4	3 . . 0
opcode 0xb	reserved	opcode 0xe	reserved
6 bits	18 bits	4 bits	4 bits

Format:

```
lf.cust1.s
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORFPX32 II	Optional

lf.div.d Divide Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.div.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] / vfrB[63:0]
```

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX64 II	Optional

lf.div.s Divide Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.div.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] / vfrB[31:0]
```

64-bit Implementation:

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX32 II	Optional

lf.ftoi.d Floating-Point Double-Precision To Integer

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.ftoi.d rD,rA
```

Description:

The contents of vector/floating-point register vfrA are converted to integer and stored into general-purpose register rD.

32-bit Implementation:

64-bit Implementation:

```
rD[63:0] <- ftoi(vfrA[63:0])
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.ftoi.s Floating-Point Single-Precision To Integer

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.ftoi.s rD,rA
```

Description:

The contents of vector/floating-point register vfrA are converted to integer and stored into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- ftoi(vfrA[31:0])
```

64-bit Implementation:

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.itof.d Integer To Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x14
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.itof.d rD,rA
```

Description:

The contents of general-purpose register rA are converted to Double-precision floating-point number and stored into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- itof(rA[63:0])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.itof.s Integer To Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x14
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.itof.s rD,rA
```

Description:

The contents of general-purpose register rA are converted to single-precision floating-point number and stored into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- itof(rA[31:0])
```

64-bit Implementation:

Exceptions:

None

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.madd.d Multiply and Add Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.madd.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB and added to special-purpose register FPMADDLO/FPMADDHI.

32-bit Implementation:

64-bit Implementation:

```
FPMADDHI[31:0]FPMADDLO[31:0] <- vfrA[63:0] * vfrB[63:0] +
FPMADDHI[31:0]FPMADDLO[31:0]
```

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX64 II	Optional

lf.madd.s Multiply and Add Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.madd.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB and added to special-purpose register FPMADDLO/FPMADDHI.

32-bit Implementation:

```
FPMADDHI[31:0]FPMADDLO[31:0] <- vfrA[31:0] * vfrB[31:0] +
FPMADDHI[31:0]FPMADDLO[31:0]
```

64-bit Implementation:

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX32 II	Optional

lf.mul.d Multiply Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.mul.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] * vfrB[63:0]
```

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.mul.s Multiply Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.mul.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] * vfrB[31:0]
```

64-bit Implementation:

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.rem.d Remainder Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.rem.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB and remainder is used as the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] % vfrB[63:0]
```

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX64 II	Optional

lf.rem.s Remainder Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.rem.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB and remainder is used as the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] % vfrB[31:0]
```

64-bit Implementation:

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX32 II	Optional

lf.sfeq.d — Set Flag if Equal Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfeq.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[63:0] == vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sfeq.s Set Flag if Equal Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfeq.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- vfrA[31:0] == vfrB[31:0]
```

64-bit Implementation:

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.sfge.d Set Flag if Greater or Equal Than Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfge.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[63:0] >= vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sfge.s Set Flag if Greater or Equal Than Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfge.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- vfrA[31:0] >= vfrB[31:0]
```

64-bit Implementation:

Exceptions:

None

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.sfgt.d Set Flag if Greater Than Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfgt.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[63:0] > vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sfgt.s Set Flag if Greater Than Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfgt.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- vfrA[31:0] > vfrB[31:0]
```

64-bit Implementation:

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.sfle.d Set Flag if Less or Equal Than Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfle.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[363:0] <= vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sfle.s Set Flag if Less or Equal Than Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfle.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- vfrA[31:0] <= vfrB[31:0]
```

64-bit Implementation:

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.sflt.d Set Flag if Less Than Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sflt.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[63:0] < vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sflt.s Set Flag if Less Than Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sflt.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- vfrA[31:0] < vfrB[31:0]
```

64-bit Implementation:

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.sfne.d Set Flag if Not Equal Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfne.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[63:0] != vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sfne.s Set Flag if Not Equal Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfne.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
flag <- vfrA[31:0] != vfrB[31:0]
```

64-bit Implementation:

Exceptions:

None

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lf.sub.d Subtract Floating-Point Double-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sub.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrB is subtracted from the contents of vector/floating-point register vfrA to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] - vfrB[63:0]
```

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lf.sub.s Subtract Floating-Point Single-Precision

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sub.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrB is subtracted from the contents of vector/floating-point register vfrA to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] - vfrB[31:0]
```

64-bit Implementation:

Exceptions:

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lvf.ld Load Vector/Floating-Point Double Word

31 26	25 . . . 21	20 . . . 16	15 8	7 0
opcode 0xd	D	A	reserved	opcode 0x0
6 bits	5 bits	5 bits	8 bits	8 bits

Format:

```
lvf.ld rD,0(rA)
```

Description:

The contents of vector/floating-point register vfrA is used as effective address. The double word in memory addressed by EA is loaded into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- vfrA[63:0]
   rD[63:0] <- (EA)[63:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lvf.lw Load Vector/Floating-Point Single Word

31 26	25 . . . 21	20 . . . 16	15 8	7 0
opcode 0xd	D	A	reserved	opcode 0x1
6 bits	5 bits	5 bits	8 bits	8 bits

Format:

```
lvf.lw rD,0(rA)
```

Description:

The contents of vector/floating-point register vfrA is used as effective address. The double word in memory addressed by EA is loaded into vector/floating-point register vfrD.

32-bit Implementation:

```
EA <- vfrA[31:0]
   rD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- vfrA[31:0]
   rD[31:0] <- (EA)[31:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

lvf.sd Store Vector/Floating-Point Double Word

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xd	reserved	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lvf.sd 0(rA),rB
```

Description:

The contents of vector/floating-point register vfrA is used as effective address. The double word in vector/floating-point register vrfB is stored to memory location addresses by EA.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- vfrA[63:0]
   rD[63:0] <- (EA)[63:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORFPX64 I	Required

lvf.sw Store Vector/Floating-Point Single Word

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xd	reserved	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lvf.sw 0(rA),rB
```

Description:

The contents of vector/floating-point register vfrA is used as effective address. The single word in vector/floating-point register vrfB is stored to memory location addresses by EA.

32-bit Implementation:

```
EA <- vfrA[31:0]
   rD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- vfrA[31:0]
   rD[31:0] <- (EA)[31:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Class	Implementation
ORFPX32 I	Required

0.3. ORVDX64

lv.add.b — Vector Byte Elements Add Signed

31 26	25 21	20 16	15 11	10 . . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x30
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.add.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] + vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] + vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] + vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] + vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] + vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] + vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] + vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] + vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.add.h Vector Half-Word Elements Add Signed

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x31
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.add.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] + vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] + vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] + vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] + vfrB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.adds.b Vector Byte Elements Add Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x32
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.adds.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- sat8s(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8s(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8s(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8s(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8s(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8s(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8s(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8s(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.adds.h Vector Half-Word Elements Add Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x33
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.adds.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] + vfrB[15:0])
   vfrD[31:16] <- sat16s(vfrA[31:16] + vfrB[31:16])
   vfrD[47:32] <- sat16s(vfrA[47:32] + vfrB[47:32])
   vfrD[63:48] <- sat16s(vfrA[63:48] + vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.addu.b — Vector Byte Elements Add Unsigned

31 26	25 21	20 16	15 11	10 . . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x34
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addu.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrA are added to the unsigned byte elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] + vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] + vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] + vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] + vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] + vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] + vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] + vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] + vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.addu.h Vector Half-Word Elements Add Unsigned

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x35
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addu.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrA are added to the unsigned half-word elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] + vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] + vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] + vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] + vfrB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.addus.b — Vector Byte Elements Add Unsigned Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x36
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addus.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrA are added to the unsigned byte elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- sat8u(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8u(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8u(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8u(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8u(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8u(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8u(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8u(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.addus.h Vector Half-Word Elements Add Unsigned Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x37
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addus.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrA are added to the unsigned half-word elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] + vfrB[15:0])
   vfrD[31:16] <- sat16s(vfrA[31:16] + vfrB[31:16])
   vfrD[47:32] <- sat16s(vfrA[47:32] + vfrB[47:32])
   vfrD[63:48] <- sat16s(vfrA[63:48] + vfrB[63:48])
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_eq.b — Vector Byte Elements All Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] == vfrB[7:0]
   vfrA[15:8] == vfrB[15:8]
   vfrA[23:16] == vfrB[23:16]
   vfrA[31:24] == vfrB[31:24]
   vfrA[39:32] == vfrB[39:32]
   vfrA[47:40] == vfrB[47:40]
   vfrA[55:48] == vfrB[55:48]
   vfrA[63:56] == vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_eq.h Vector Half-Word Elements All Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] == vfrB[15:0]
   vfrA[31:16] == vfrB[31:16]
   vfrA[47:32] == vfrB[47:32]
   vfrA[63:48] == vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_ge.b Vector Byte Elements All Greater or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] >= vfrB[7:0]
   vfrA[15:8] >= vfrB[15:8]
   vfrA[23:16] >= vfrB[23:16]
   vfrA[31:24] >= vfrB[31:24]
   vfrA[39:32] >= vfrB[39:32]
   vfrA[47:40] >= vfrB[47:40]
   vfrA[55:48] >= vfrB[55:48]
   vfrA[63:56] >= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_ge.h Vector Half-Word Elements All Greater or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] >= vfrB[15:0]
   vfrA[31:16] >= vfrB[31:16]
   vfrA[47:32] >= vfrB[47:32]
   vfrA[63:48] >= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_gt.b Vector Byte Elements All Greater Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x14
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] > vfrB[7:0]
   vfrA[15:8] > vfrB[15:8]
   vfrA[23:16] > vfrB[23:16]
   vfrA[31:24] > vfrB[31:24]
   vfrA[39:32] > vfrB[39:32]
   vfrA[47:40] > vfrB[47:40]
   vfrA[55:48] > vfrB[55:48]
   vfrA[63:56] > vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_gt.h Vector Half-Word Elements All Greater Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] > vfrB[15:0]
   vfrA[31:16] > vfrB[31:16]
   vfrA[47:32] > vfrB[47:32]
   vfrA[63:48] > vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_le.b Vector Byte Elements All Less or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] <= vfrB[7:0]
   vfrA[15:8] <= vfrB[15:8]
   vfrA[23:16] <= vfrB[23:16]
   vfrA[31:24] <= vfrB[31:24]
   vfrA[39:32] <= vfrB[39:32]
   vfrA[47:40] <= vfrB[47:40]
   vfrA[55:48] <= vfrB[55:48]
   vfrA[63:56] <= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_le.h Vector Half-Word Elements All Less or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] ,= vfrB[15:0]
   vfrA[31:16] <= vfrB[31:16]
   vfrA[47:32] <= vfrB[47:32]
   vfrA[63:48] <= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_lt.b Vector Byte Elements All Less Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] < vfrB[7:0]
   vfrA[15:8] < vfrB[15:8]
   vfrA[23:16] < vfrB[23:16]
   vfrA[31:24] < vfrB[31:24]
   vfrA[39:32] < vfrB[39:32]
   vfrA[47:40] < vfrB[47:40]
   vfrA[55:48] < vfrB[55:48]
   vfrA[63:56] < vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_lt.h Vector Half-Word Elements All Less Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] < vfrB[15:0]
   vfrA[31:16] < vfrB[31:16]
   vfrA[47:32] < vfrB[47:32]
   vfrA[63:48] < vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_ne.b — Vector Byte Elements All Not Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] != vfrB[7:0]
   vfrA[15:8] != vfrB[15:8]
   vfrA[23:16] != vfrB[23:16]
   vfrA[31:24] != vfrB[31:24]
   vfrA[39:32] != vfrB[39:32]
   vfrA[47:40] != vfrB[47:40]
   vfrA[55:48] != vfrB[55:48]
   vfrA[63:56] != vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.all_ne.h Vector Half-Word Elements All Not Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] != vfrB[15:0]
   vfrA[31:16] != vfrB[31:16]
   vfrA[47:32] != vfrB[47:32]
   vfrA[63:48] != vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.and Vector And

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x38
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.and rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical AND operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] AND vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_eq.b — Vector Byte Elements Any Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x20
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] == vfrB[7:0] ||
   vfrA[15:8] == vfrB[15:8] ||
   vfrA[23:16] == vfrB[23:16] ||
   vfrA[31:24] == vfrB[31:24] ||
   vfrA[39:32] == vfrB[39:32] ||
   vfrA[47:40] == vfrB[47:40] ||
   vfrA[55:48] == vfrB[55:48] ||
   vfrA[63:56] == vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_eq.h — Vector Half-Word Elements Any Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x21
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] == vfrB[15:0] ||
   vfrA[31:16] == vfrB[31:16] ||
   vfrA[47:32] == vfrB[47:32] ||
   vfrA[63:48] == vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_ge.b Vector Byte Elements Any Greater or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x22
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] >= vfrB[7:0] ||
   vfrA[15:8] >= vfrB[15:8] ||
   vfrA[23:16] >= vfrB[23:16] ||
   vfrA[31:24] >= vfrB[31:24] ||
   vfrA[39:32] >= vfrB[39:32] ||
   vfrA[47:40] >= vfrB[47:40] ||
   vfrA[55:48] >= vfrB[55:48] ||
   vfrA[63:56] >= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_ge.h Vector Half-Word Elements Any Greater or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x23
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] >= vfrB[15:0] ||
   vfrA[31:16] >= vfrB[31:16] ||
   vfrA[47:32] >= vfrB[47:32] ||
   vfrA[63:48] >= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_gt.b Vector Byte Elements Any Greater Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x24
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] > vfrB[7:0] ||
   vfrA[15:8] > vfrB[15:8] ||
   vfrA[23:16] > vfrB[23:16] ||
   vfrA[31:24] > vfrB[31:24] ||
   vfrA[39:32] > vfrB[39:32] ||
   vfrA[47:40] > vfrB[47:40] ||
   vfrA[55:48] > vfrB[55:48] ||
   vfrA[63:56] > vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_gt.h Vector Half-Word Elements Any Greater Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x25
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] > vfrB[15:0] ||
   vfrA[31:16] > vfrB[31:16] ||
   vfrA[47:32] > vfrB[47:32] ||
   vfrA[63:48] > vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_le.b Vector Byte Elements Any Less or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x26
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] <= vfrB[7:0] ||
   vfrA[15:8] <= vfrB[15:8] ||
   vfrA[23:16] <= vfrB[23:16] ||
   vfrA[31:24] <= vfrB[31:24] ||
   vfrA[39:32] <= vfrB[39:32] ||
   vfrA[47:40] <= vfrB[47:40] ||
   vfrA[55:48] <= vfrB[55:48] ||
   vfrA[63:56] <= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_le.h Vector Half-Word Elements Any Less or Equal Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x27
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] ,= vfrB[15:0] ||
   vfrA[31:16] <= vfrB[31:16] ||
   vfrA[47:32] <= vfrB[47:32] ||
   vfrA[63:48] <= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_lt.b — Vector Byte Elements Any Less Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x28
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] < vfrB[7:0] ||
   vfrA[15:8] < vfrB[15:8] ||
   vfrA[23:16] < vfrB[23:16] ||
   vfrA[31:24] < vfrB[31:24] ||
   vfrA[39:32] < vfrB[39:32] ||
   vfrA[47:40] < vfrB[47:40] ||
   vfrA[55:48] < vfrB[55:48] ||
   vfrA[63:56] < vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_lt.h Vector Half-Word Elements Any Less Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x29
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] < vfrB[15:0] ||
   vfrA[31:16] < vfrB[31:16] ||
   vfrA[47:32] < vfrB[47:32] ||
   vfrA[63:48] < vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_ne.b — Vector Byte Elements Any Not Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x2a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[7:0] != vfrB[7:0] ||
   vfrA[15:8] != vfrB[15:8] ||
   vfrA[23:16] != vfrB[23:16] ||
   vfrA[31:24] != vfrB[31:24] ||
   vfrA[39:32] != vfrB[39:32] ||
   vfrA[47:40] != vfrB[47:40] ||
   vfrA[55:48] != vfrB[55:48] ||
   vfrA[63:56] != vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.any_ne.h — Vector Half-Word Elements Any Not Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x2b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
flag <- vfrA[15:0] != vfrB[15:0] ||
   vfrA[31:16] != vfrB[31:16] ||
   vfrA[47:32] != vfrB[47:32] ||
   vfrA[63:48] != vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.avg.b Vector Byte Elements Average

31 26	25 21	20 16	15 11	10 . . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x39
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.avg.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB and the sum is shifted right by one to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- (vfrA[7:0] + vfrB[7:0]) » 1
   vfrD[15:8] <- (vfrA[15:8] + vfrB[15:8]) » 1
   vfrD[23:16] <- (vfrA[23:16] + vfrB[23:16]) » 1
   vfrD[31:24] <- (vfrA[31:24] + vfrB[31:24]) » 1
   vfrD[39:32] <- (vfrA[39:32] + vfrB[39:32]) » 1
   vfrD[47:40] <- (vfrA[47:40] + vfrB[47:40]) » 1
   vfrD[55:48] <- (vfrA[55:48] + vfrB[55:48]) » 1
   vfrD[63:56] <- (vfrA[63:56] + vfrB[63:56]) » 1
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.avg.h Vector Half-Word Elements Average

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x3a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.avg.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB and the sum is shifted right by one to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- (vfrA[15:0] + vfrB[15:0]) » 1
   vfrD[31:16] <- (vfrA[31:16] + vfrB[31:16]) » 1
   vfrD[47:32] <- (vfrA[47:32] + vfrB[47:32]) » 1
   vfrD[63:48] <- (vfrA[63:48] + vfrB[63:48]) » 1
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_eq.b — Vector Byte Elements Compare Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x40
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are equal; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] == vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] == vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] == vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] == vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] == vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] == vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] == vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] == vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_eq.h — Vector Half-Word Elements Compare Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x41
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are equal; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] == vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] == vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] == vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] == vfrB[55:48]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_ge.b Vector Byte Elements Compare Greater Than or Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x42
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] >= vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] >= vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] >= vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] >= vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] >= vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] >= vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] >= vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] >= vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_ge.h Vector Half-Word Elements Compare Greater Than or Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x43
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] >= vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] >= vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] >= vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] >= vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_gt.b — Vector Byte Elements Compare Greater Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x44
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] > vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] > vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] > vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] > vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] > vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] > vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] > vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] > vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_gt.h Vector Half-Word Elements Compare Greater Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x45
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] > vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] > vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] > vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] > vfrB[55:48]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_le.b Vector Byte Elements Compare Less Than or Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x46
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] <= vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] <= vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] <= vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] <= vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] <= vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_le.h Vector Half-Word Elements Compare Less Than or Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x47
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] <= vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_lt.b — Vector Byte Elements Compare Less Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x48
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] <= vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] <= vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] <= vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] <= vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] <= vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_lt.h — Vector Half-Word Elements Compare Less Than

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x49
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than element in vfrB; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] <= vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_ne.b — Vector Byte Elements Compare Not Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x4a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are not equal; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] != vfrB[7:0])
   vfrD[15:8] <- repl(vfrA[15:8] != vfrB[15:8])
   vfrD[23:16] <- repl(vfrA[23:16] != vfrB[23:16])
   vfrD[31:24] <- repl(vfrA[31:24] != vfrB[31:24])
   vfrD[39:32] <- repl(vfrA[39:32] != vfrB[39:32])
   vfrD[47:40] <- repl(vfrA[47:40] != vfrB[47:40])
   vfrD[55:48] <- repl(vfrA[55:48] != vfrB[55:48])
   vfrD[63:56] <- repl(vfrA[63:56] != vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cmp_ne.h — Vector Half-Word Elements Compare Not Equal

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x4b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are not equal; otherwise element bits are cleared.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] != vfrB[7:0])
   vfrD[31:16] <- repl(vfrA[23:16] != vfrB[23:16])
   vfrD[47:32] <- repl(vfrA[39:32] != vfrB[39:32])
   vfrD[63:48] <- repl(vfrA[55:48] != vfrB[55:48])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.cust1 — Reserved for Custom Vector Instructions

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xc	reserved
6 bits	18 bits	4 bits	4 bits

Format:

```
lv.cust1
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORVDX64 II	Optional

lv.cust2 — Reserved for Custom Vector Instructions

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xd	reserved
6 bits	18 bits	4 bits	4 bits

Format:

```
lv.cust2
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORVDX64 II	Optional

lv.cust3 Reserved for Custom Vector Instructions

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xe	reserved
6 bits	18 bits	4 bits	4 bits

Format:

```
lv.cust3
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORVDX64 II	Optional

lv.cust4 Reserved for Custom Vector Instructions

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xf	reserved
6 bits	18 bits	4 bits	4 bits

Format:

```
lv.cust4
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture, but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

Notes:

Instruction Class	Implementation
ORVDX64 II	Optional

lv.madds.h Vector Half-Word Elements Multiply Add Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x54
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.madds.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form intermediate results. They are added to the signed half-word VMAC elements to form the final results that are placed again in VMAC registers. Intermediate result is placed into vector/floating-point register vfrD. If any of the final results exceeds min/max value, it is saturated.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat32s(vfrA[15:0] * vfrB[15:0] + VMACLO[31:0])
   vfrD[31:16] <- sat32s(vfrA[31:16] * vfrB[31:16] + VMACLO[63:32])
   vfrD[47:32] <- sat32s(vfrA[47:32] * vfrB[47:32] + VMACHI[31:0])
   vfrD[63:48] <- sat32s(vfrA[63:48] * vfrB[63:48] + VMACHI[63:32])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.max.b Vector Byte Elements Maximum

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x55
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.max.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB and larger elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] > vfrB[7:0] ?  vfrA[7:0] :  vrfB[7:0]
   vfrD[15:8] <- vfrA[15:8] > vfrB[15:8] ?  vfrA[15:8] :  vrfB[15:8]
   vfrD[23:16] <- vfrA[23:16] > vfrB[23:16] ?  vfrA[23:16] :
vrfB[23:16]
   vfrD[31:24] <- vfrA[31:24] > vfrB[31:24] ?  vfrA[31:24] :
vrfB[31:24]
   vfrD[39:32] <- vfrA[39:32] > vfrB[39:32] ?  vfrA[39:32] :
vrfB[39:32]
   vfrD[47:40] <- vfrA[47:40] > vfrB[47:40] ?  vfrA[47:40] :
vrfB[47:40]
   vfrD[55:48] <- vfrA[55:48] > vfrB[55:48] ?  vfrA[55:48] :
vrfB[55:48]
   vfrD[63:56] <- vfrA[63:56] > vfrB[63:56] ?  vfrA[63:56] :
vrfB[63:56]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.max.h Vector Half-Word Elements Maximum

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x56
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.max.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB and larger elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] > vfrB[15:0] ?  vfrA[15:0] :  vrfB[15:0]
   vfrD[31:16] <- vfrA[31:16] > vfrB[31:16] ?  vfrA[31:16] :
vrfB[31:16]
   vfrD[47:32] <- vfrA[47:32] > vfrB[47:32] ?  vfrA[47:32] :
vrfB[47:32]
   vfrD[63:48] <- vfrA[63:48] > vfrB[63:48] ?  vfrA[63:48] :
vrfB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.merge.b — Vector Byte Elements Merge

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x57
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.merge.b rD,rA,rB
```

Description:

Byte elements of the lower half of the vector/floating-point register vfrA are combined with the byte elements of the lower half of vector/floating-point register vfrB in such a way that lowest element is from the vfrB, second element from the vfrA, third again from the vfrB etc. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8]
   vfrD[23:16] <- vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24]
   vfrD[39:32] <- vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40]
   vfrD[55:48] <- vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.merge.h — Vector Half-Word Elements Merge

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x58
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.merge.h rD,rA,rB
```

Description:

Half-word elements of the lower half of the vector/floating-point register vfrA are combined with the byte elements of the lower half of vector/floating-point register vfrB in such a way that lowest element is from the vfrB, second element from the vfrA, third again from the vfrB etc. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16]
   vfrD[47:32] <- vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.min.b Vector Byte Elements Minimum

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x59
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.min.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB and smaller elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] < vfrB[7:0] ?  vfrA[7:0] :  vrfB[7:0]
   vfrD[15:8] <- vfrA[15:8] < vfrB[15:8] ?  vfrA[15:8] :  vrfB[15:8]
   vfrD[23:16] <- vfrA[23:16] < vfrB[23:16] ?  vfrA[23:16] :
vrfB[23:16]
   vfrD[31:24] <- vfrA[31:24] < vfrB[31:24] ?  vfrA[31:24] :
vrfB[31:24]
   vfrD[39:32] <- vfrA[39:32] < vfrB[39:32] ?  vfrA[39:32] :
vrfB[39:32]
   vfrD[47:40] <- vfrA[47:40] < vfrB[47:40] ?  vfrA[47:40] :
vrfB[47:40]
   vfrD[55:48] <- vfrA[55:48] < vfrB[55:48] ?  vfrA[55:48] :
vrfB[55:48]
   vfrD[63:56] <- vfrA[63:56] < vfrB[63:56] ?  vfrA[63:56] :
vrfB[63:56]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.min.h Vector Half-Word Elements Minimum

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.min.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB and smaller elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] < vfrB[15:0] ?  vfrA[15:0] :  vrfB[15:0]
   vfrD[31:16] <- vfrA[31:16] < vfrB[31:16] ?  vfrA[31:16] :
vrfB[31:16]
   vfrD[47:32] <- vfrA[47:32] < vfrB[47:32] ?  vfrA[47:32] :
vrfB[47:32]
   vfrD[63:48] <- vfrA[63:48] < vfrB[63:48] ?  vfrA[63:48] :
vrfB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.msubs.h Vector Half-Word Elements Multiply Subtract Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.msubs.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form intermediate results. They are subtracted from the signed half-word VMAC elements to form the final results that are placed again in VMAC registers. Intermediate result is placed into vector/floating-point register vfrD. If any of the final results exceeds min/max value, it is saturated.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat32s(VMACLO[31:0] - vfrA[15:0] * vfrB[15:0])
   vfrD[31:16] <- sat32s(VMACLO[63:32] - vfrA[31:16] * vfrB[31:16])
   vfrD[47:32] <- sat32s(VMACHI[31:0] - vfrA[47:32] * vfrB[47:32])
   vfrD[63:48] <- sat32s(VMACHI[63:32] - vfrA[63:48] * vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.muls.h Vector Half-Word Elements Multiply Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.muls.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form the results. The result is placed into vector/floating-point register vfrD. If any of the final results exceeds min/max value, it is saturated.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat32s(vfrA[15:0] * vfrB[15:0])
   vfrD[31:16] <- sat32s(vfrA[31:16] * vfrB[31:16])
   vfrD[47:32] <- sat32s(vfrA[47:32] * vfrB[47:32])
   vfrD[63:48] <- sat32s(vfrA[63:48] * vfrB[63:48])
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 II	Optional

lv.nand — Vector Not And

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.nand rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical NAND operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] NAND vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.nor — Vector Not Or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5e
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.nor rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical NOR operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] NOR vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.or — Vector Or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5f
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.or rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical OR operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] OR vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.pack.b Vector Byte Elements Pack

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x60
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.pack.b rD,rA,rB
```

Description:

Lower half of the byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the byte truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[3:0] <- vfrB[3:0]
   vfrD[7:4] <- vfrB[11:8]
   vfrD[11:8] <- vfrB[19:16]
   vfrD[15:12] <- vfrB[27:24]
   vfrD[19:16] <- vfrB[35:32]
   vfrD[23:20] <- vfrB[43:40]
   vfrD[27:24] <- vfrB[51:48]
   vfrD[31:28] <- vfrB[59:56]
   vfrD[35:32] <- vfrA[3:0]
   vfrD[39:36] <- vfrA[11:8]
   vfrD[43:40] <- vfrA[19:16]
   vfrD[47:44] <- vfrA[27:24]
   vfrD[51:48] <- vfrA[35:32]
   vfrD[55:52] <- vfrA[43:40]
   vfrD[59:56] <- vfrA[51:48]
   vfrD[63:60] <- vfrA[59:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.pack.h **Vector Half-word Elements Pack**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x61
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.pack.h rD,rA,rB
```

Description:

Lower half of the half-word elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the half-word truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrB[15:0]
   vfrD[15:8] <- vfrB[31:16]
   vfrD[23:16] <- vfrB[47:32]
   vfrD[31:24] <- vfrB[63:48]
   vfrD[39:32] <- vfrA[15:0]
   vfrD[47:40] <- vfrA[31:16]
   vfrD[55:48] <- vfrA[47:32]
   vfrD[63:56] <- vfrA[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.packs.b Vector Byte Elements Pack Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x62
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packs.b rD,rA,rB
```

Description:

Lower half of the signed byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the signed byte truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds signed 4-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[3:0] <- sat4s(vfrB[7:0]
   vfrD[7:4] <- sat4s(vfrB[15:8]
   vfrD[11:8] <- sat4s(vfrB[23:16]
   vfrD[15:12] <- sat4s(vfrB[31:24]
   vfrD[19:16] <- sat4s(vfrB[39:32]
   vfrD[23:20] <- sat4s(vfrB[47:40]
   vfrD[27:24] <- sat4s(vfrB[55:48]
   vfrD[31:28] <- sat4s(vfrB[63:56]
   vfrD[35:32] <- sat4s(vfrA[7:0]
   vfrD[39:36] <- sat4s(vfrA[15:8]
   vfrD[43:40] <- sat4s(vfrA[23:16]
   vfrD[47:44] <- sat4s(vfrA[31:24]
   vfrD[51:48] <- sat4s(vfrA[39:32]
   vfrD[55:52] <- sat4s(vfrA[47:40]
   vfrD[59:56] <- sat4s(vfrA[55:48]
   vfrD[63:60] <- sat4s(vfrA[63:56]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.packs.h Vector Half-word Elements Pack Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x63
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packs.h rD,rA,rB
```

Description:

Lower half of the signed halfpword elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the signed half-word truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds signed 8-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- sat8s(vfrB[15:0])
   vfrD[15:8] <- sat8s(vfrB[31:16])
   vfrD[23:16] <- sat8s(vfrB[47:32])
   vfrD[31:24] <- sat8s(vfrB[63:48])
   vfrD[39:32] <- sat8s(vfrA[15:0])
   vfrD[47:40] <- sat8s(vfrA[31:16])
   vfrD[55:48] <- sat8s(vfrA[47:32])
   vfrD[63:56] <- sat8s(vfrA[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.packus.b Vector Byte Elements Pack Unsigned Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x64
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packus.b rD,rA,rB
```

Description:

Lower half of the unsigned byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the unsigned byte truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds unsigned 4-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[3:0] <- sat4u(vfrB[7:0]
   vfrD[7:4] <- sat4u(vfrB[15:8]
   vfrD[11:8] <- sat4u(vfrB[23:16]
   vfrD[15:12] <- sat4u(vfrB[31:24]
   vfrD[19:16] <- sat4u(vfrB[39:32]
   vfrD[23:20] <- sat4u(vfrB[47:40]
   vfrD[27:24] <- sat4u(vfrB[55:48]
   vfrD[31:28] <- sat4u(vfrB[63:56]
   vfrD[35:32] <- sat4u(vfrA[7:0]
   vfrD[39:36] <- sat4u(vfrA[15:8]
   vfrD[43:40] <- sat4u(vfrA[23:16]
   vfrD[47:44] <- sat4u(vfrA[31:24]
   vfrD[51:48] <- sat4u(vfrA[39:32]
   vfrD[55:52] <- sat4u(vfrA[47:40]
   vfrD[59:56] <- sat4u(vfrA[55:48]
   vfrD[63:60] <- sat4u(vfrA[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.packus.h Vector Half-word Elements Pack Unsigned Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x65
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packus.h rD,rA,rB
```

Description:

Lower half of the unsigned halfpword elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the unsigned half-word truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds unsigned 8-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- sat8u(vfrB[15:0])
   vfrD[15:8] <- sat8u(vfrB[31:16])
   vfrD[23:16] <- sat8u(vfrB[47:32])
   vfrD[31:24] <- sat8u(vfrB[63:48])
   vfrD[39:32] <- sat8u(vfrA[15:0])
   vfrD[47:40] <- sat8u(vfrA[31:16])
   vfrD[55:48] <- sat8u(vfrA[47:32])
   vfrD[63:56] <- sat8u(vfrA[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.perm.n Vector Nibble Elements Permute

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x66
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.perm.n rD,rA,rB
```

Description:

The 4-bit elements of vector/floating-point register vfrA are permuted according to corresponding 4-bit values in vector/floating-point register vfrB. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[3:0] <- vfrA[vfrB[3:0]*4+3:vfrB[3:0]*4]
   vfrD[7:4] <- vfrA[vfrB[7:4]*4+3:vfrB[7:4]*4]
   vfrD[11:8] <- vfrA[vfrB[11:8]*4+3:vfrB[11:8]*4]
   vfrD[15:12] <- vfrA[vfrB[15:12]*4+3:vfrB[15:12]*4]
   vfrD[19:16] <- vfrA[vfrB[19:16]*4+3:vfrB[19:16]*4]
   vfrD[23:20] <- vfrA[vfrB[23:20]*4+3:vfrB[23:20]*4]
   vfrD[27:24] <- vfrA[vfrB[27:24]*4+3:vfrB[27:24]*4]
   vfrD[31:28] <- vfrA[vfrB[31:28]*4+3:vfrB[31:28]*4]
   vfrD[35:32] <- vfrA[vfrB[35:32]*4+3:vfrB[35:32]*4]
   vfrD[39:36] <- vfrA[vfrB[39:36]*4+3:vfrB[39:36]*4]
   vfrD[43:40] <- vfrA[vfrB[43:40]*4+3:vfrB[43:40]*4]
   vfrD[47:44] <- vfrA[vfrB[47:44]*4+3:vfrB[47:44]*4]
   vfrD[51:48] <- vfrA[vfrB[51:48]*4+3:vfrB[51:48]*4]
   vfrD[55:52] <- vfrA[vfrB[55:52]*4+3:vfrB[55:52]*4]
   vfrD[59:56] <- vfrA[vfrB[59:56]*4+3:vfrB[59:56]*4]
   vfrD[63:60] <- vfrA[vfrB[63:60]*4+3:vfrB[63:60]*4]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.rl.b Vector Byte Elements Rotate Left

31 26	25 21	20 16	15 11	10 . . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x67
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.rl.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are rotated left by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] rl vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] rl vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] rl vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] rl vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] rl vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] rl vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] rl vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] rl vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.rl.h Vector Half-Word Elements Rotate Left

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x68
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.rl.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are rotated left by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] rl vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] rl vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] rl vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] rl vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sll Vector Shift Left Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sll rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are shifted left by the number of bits specified in lower 4 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the low-order bits of vfrD. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] « vfrB[2:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sll.b Vector Byte Elements Shift Left Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x69
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sll.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted left by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the low-order bits elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] « vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] « vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] « vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] « vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] « vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] « vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] « vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] « vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sll.h Vector Half-Word Elements Shift Left Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sll.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted left by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting zeros into the low-order bits elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] « vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] « vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] « vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] « vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sra.b — Vector Byte Elements Shift Right Arithmetic

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6e
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sra.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB, inserting most significat bit of each element into the high-order bits. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] sra vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] sra vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] sra vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] sra vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] sra vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] sra vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] sra vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] sra vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sra.h Vector Half-Word Elements Shift Right Arithmetic

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6f
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sra.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting most significant bit of each element into the low-order bits. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] sra vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] sra vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] sra vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] sra vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.srl Vector Shift Right Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x70
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.srl rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 4 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the high-order bits of vfrD. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] » vfrB[2:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.srl.b — Vector Byte Elements Shift Right Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.srl.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the high-order bits elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] » vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] » vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] » vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] » vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] » vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] » vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] » vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] » vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.srl.h Vector Half-Word Elements Shift Right Logical

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.srl.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting zeros into the low-order bits of elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] » vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] » vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] » vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] » vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sub.b Vector Byte Elements Subtract Signed

31 26	25 21	20 16	15 11	10 . . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x71
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sub.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrB are subtracted from the byte elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] - vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] - vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] - vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] - vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] - vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] - vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] - vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] - vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.sub.h — Vector Half-Word Elements Subtract Signed

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x72
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sub.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrB are subtracted from the half-word elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] - vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] - vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] - vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] - vfrB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.subs.b Vector Byte Elements Subtract Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x73
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subs.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrB are subtracted from the byte elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- sat8s(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8s(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8s(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8s(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8s(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8s(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8s(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8s(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.subs.h Vector Half-Word Elements Subtract Signed Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x74
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subs.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrB are subtracted from the half-word elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] - vfrB[15:0])
   vfrD[31:16] <- sat16s(vfrA[31:16] - vfrB[31:16])
   vfrD[47:32] <- sat16s(vfrA[47:32] - vfrB[47:32])
   vfrD[63:48] <- sat16s(vfrA[63:48] - vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.subu.b — Vector Byte Elements Subtract Unsigned

31 26	25 21	20 16	15 11	10 . . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x75
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subu.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrB are subtracted from the unsigned byte elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] - vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] - vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] - vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] - vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] - vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] - vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] - vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] - vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.subu.h — Vector Half-Word Elements Subtract Unsigned

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x76
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subu.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrB are subtracted from the unsigned half-word elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] - vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] - vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] - vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] - vfrB[63:48]
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.subus.b Vector Byte Elements Subtract Unsigned Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x77
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subus.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrB are subtracted from the unsigned byte elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- sat8u(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8u(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8u(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8u(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8u(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8u(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8u(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8u(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.subus.h — Vector Half-Word Elements Subtract Unsigned Saturated

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x78
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subus.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrB are subtracted from the unsigned half-word elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- sat16u(vfrA[15:0] - vfrB[15:0])
   vfrD[31:16] <- sat16u(vfrA[31:16] - vfrB[31:16])
   vfrD[47:32] <- sat16u(vfrA[47:32] - vfrB[47:32])
   vfrD[63:48] <- sat16u(vfrA[63:48] - vfrB[63:48])
```

Exceptions:

None

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.unpack.b — Vector Byte Elements Unpack

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x79
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.unpack.b rD,rA,rB
```

Description:

Lower half of 4-bit elements in vector/floating-point register vfrA are sign-extended and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[7:0] <- exts(vfrA[3:0])
   vfrD[15:8] <- exts(vfrA[7:4])
   vfrD[23:16] <- exts(vfrA[11:8])
   vfrD[31:24] <- exts(vfrA[15:12])
   vfrD[39:32] <- exts(vfrA[19:16])
   vfrD[47:40] <- exts(vfrA[23:20])
   vfrD[55:48] <- exts(vfrA[27:24])
   vfrD[63:56] <- exts(vfrA[31:28])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.unpack.h — Vector Half-Word Elements Unpack

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x7a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.unpack.h rD,rA,rB
```

Description:

Lower half of 8-bit elements in vector/floating-point register vfrA are sign-extended and placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[15:0] <- exts(vfrA[7:0])
   vfrD[31:16] <- exts(vfrA[15:8])
   vfrD[47:32] <- exts(vfrA[23:16])
   vfrD[63:48] <- exts(vfrA[31:24])
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required

lv.xor — Vector Exclusive Or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x7b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.xor rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical XOR operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] XOR vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Class	Implementation
ORVDX64 I	Required