0.1. ORBIS32/64

l.add Add Signed l.add

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x0
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.add rD,rA,rB
```

Description:

The contents of general-purpose register rA are added to the contents of general-purpose register rB to form the result. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] + rB[31:0]
SR[CY] <- carry
SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] + rB[63:0]
SR[CY] <- carry
SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

l.addc Add Signed and Carry l.addc

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x1
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.addc rD,rA,rB
```

Description:

The contents of general-purpose register rA are added to the contents of general-purpose register rB and carry SR[CY] to form the result. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] + rB[31:0] + SR[CY]
SR[CY] <- carry
SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] + rB[63:0] + SR[CY]
SR[CY] <- carry
SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

l.addi Add Immediate Signed l.addi

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x27	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.addi rD,rA,I
```

Description:

The immediate value is signed-extended and added to the contents of general-purposeregister rA to form the result. The result is placed into general-purposeregister rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] + exts(Immediate)
SR[CY] <- carry
SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] + exts(Immediate)
SR[CY] <- carry
SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

l.and And l.and

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x3
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.and rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical AND operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] AND rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] AND rB[63:0]
```

Exceptions:

None

l.andi And with Immediate Half Word l.andi

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x29	D	A	K
6 bits	5 bits	5 bits	16bits

Format:

```
l.andi rD,rA,K
```

Description:

The immediate value is zero-extended and combined with the contents of general-purpose register rA in a bit-wise logical AND operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] AND extz(Immediate)
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] AND extz(Immediate)
```

Exceptions:

None

l.bf Branch if Flag l.bf

31 26	25 0
opcode 0x4	N
6 bits	26bits

Format:

```
l.bf N
```

Description:

The immediate value is shifted left two bits, sign-extended to program counter width, and then added to the address of the delay slot. The result is the effective address of the branch. If the flag is set, the program branches to EA with a delay of one instruction.

32-bit Implementation:

```
EA <- exts(Immediate << 2) + DelayInsnAddr
PC <- EA if SR[F] set
```

64-bit Implementation:

```
EA <- exts(Immediate << 2) + DelayInsnAddr
PC <- EA if SR[F] set
```

Exceptions:

None

l.bnf Branch if No Flag l.bnf

31 26	25 0
opcode 0x3	N
6 bits	26bits

Format:

```
l.bnf N
```

Description:

The immediate value is shifted left two bits, sign-extended to program counter width, and then added to the address of the delay slot. The result is the effective address of the branch. If the flag is cleared, the program branches to EA with a delay of one instruction.

32-bit Implementation:

```
EA <- exts(Immediate << 2) + DelayInsnAddr
PC <- EA if SR[F] cleared
```

64-bit Implementation:

```
EA <- exts(Immediate << 2) + DelayInsnAddr
PC <- EA if SR[F] cleared
```

Exceptions:

None

l.cmov **Conditional Move** **l.cmov**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xe
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.cmov rD,rA,rB
```

Description:

If SR[F] is set, general-purpose register rA is placed in general-purpose register rD. If SR[F] is cleared, general-purpose register rB is placed in general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- SR[F] ? rA[31:0] :  rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- SR[F] ? rA[63:0] :  rB[63:0]
```

Exceptions:

None

l.csync **Context Syncronization** **l.csync**



Format:

```
l.csync
```

Description:

Execution of context synchronization instruction results in completion of all operations inside the processor and a flush of the instruction pipelines. When all operations are complete, the RISC core resumes with an empty instruction pipeline and fresh context in all units (MMU for example).

32-bit Implementation:

```
context-synchronization
```

64-bit Implementation:

```
context-synchronization
```

Exceptions:

```
None
```

l.cust1 Reserved for ORBIS32/64 Custom Instructions l.cust1

31 26	25 0
opcode 0x1c	reserved
6 bits	26bits

Format:

```
l.cust1
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust2 Reserved for ORBIS32/64 Custom Instructions l.cust2

31 26	25 0
opcode 0x1d	reserved
6 bits	26bits

Format:

```
l.cust2
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust3 Reserved for ORBIS32/64 Custom Instructions l.cust3

31 26	25 0
opcode 0x1e	reserved
6 bits	26bits

Format:

```
l.cust3
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust4 Reserved for ORBIS32/64 Custom Instructions l.cust4

31 26	25 0
opcode 0x1f	reserved
6 bits	26bits

Format:

```
l.cust4
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust5 Reserved for ORBIS32/64 Custom Instructions l.cust5

31 26	25 0
opcode 0x3c	reserved
6 bits	26bits

Format:

```
l.cust5
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust6 Reserved for ORBIS32/64 Custom Instructions l.cust6

31 26	25 0
opcode 0x3d	reserved
6 bits	26bits

Format:

```
l.cust6
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust7 Reserved for ORBIS32/64 Custom Instructions l.cust7

31 26	25 0
opcode 0x3e	reserved
6 bits	26bits

Format:

```
l.cust7
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.cust8 Reserved for ORBIS32/64 Custom Instructions l.cust8

31 26	25 0
opcode 0x3f	reserved
6 bits	26bits

Format:

```
l.cust8
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but rather by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

l.div Divide Signed l.div

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0x9
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.div rD,rA,rB
```

Description:

The content of general-purpose register rA are divided by the content of general-purpose register rB, and the result is placed into general-purpose register rD. Both operands are treated as signed integers. A carry flag is set when the divisor is zero.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] / rB[31:0]
SR[OV] <- overflow
SR[CY] <- carry
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] / rB[63:0]
SR[OV] <- overflow
SR[CY] <- carry
```

Exceptions:

```
Range Exception
```

l.divu **Divide Unsigned** **l.divu**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0xa
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.divu rD,rA,rB
```

Description:

The content of general-purpose register rA are divided by the content of general-purpose register rA, and the result is placed into general-purpose register rD. Both operands are treated as unsigned integers. A carry flag is set when the divisor is zero.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] / rB[31:0]
SR[OV] <- overflow
SR[CY] <- carry
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] / rB[63:0]
SR[OV] <- overflow
SR[CY] <- carry
```

Exceptions:

```
Range Exception
```

l.extbs Extend Byte with Sign l.extbs

31 26	25 . . . 21	20 . . . 16	15 10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	reserved	opcode 0x1	reserved	opcode 0xc
6 bits	5 bits	5 bits	6 bits	4 bits	2 bits	4bits

Format:

```
l.extbs rD,rA,rB
```

Description:

Bit 7 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order eight bits of general-purpose register rA are copied into the low-order eight bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:8] <- rA[7]
rD[7:0] <- rA[7:0]
```

64-bit Implementation:

```
rD[63:8] <- rA[7]
rD[7:0] <- rA[7:0]
```

Exceptions:

None

l.extbz Extend Byte with Zero l.extbz

31 26	25 . . . 21	20 . . . 16	15 10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	reserved	opcode 0x3	reserved	opcode 0xc
6 bits	5 bits	5 bits	6 bits	4 bits	2 bits	4bits

Format:

```
l.extbz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order eight bits of general-purpose register rA are copied into the low-order eight bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:8] <- 0
rD[7:0] <- rA[7:0]
```

64-bit Implementation:

```
rD[63:8] <- 0
rD[7:0] <- rA[7:0]
```

Exceptions:

None

l.exths Extend Half Word with Sign l.exths

31 26	25 . . . 21	20 . . . 16	15 10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	reserved	opcode 0x0	reserved	opcode 0xc
6 bits	5 bits	5 bits	6 bits	4 bits	2 bits	4bits

Format:

```
l.exths rD,rA,rB
```

Description:

Bit 15 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order 16 bits of general-purpose register rA are copied into the low-order 16 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:16] <- rA[15]
rD[15:0] <- rA[15:0]
```

64-bit Implementation:

```
rD[63:16] <- rA[15]
rD[15:0] <- rA[15:0]
```

Exceptions:

None

l.exthz Extend Half Word with Zero l.exthz

31 26	25 . . . 21	20 . . . 16	15 10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	reserved	opcode 0x2	reserved	opcode 0xc
6 bits	5 bits	5 bits	6 bits	4 bits	2 bits	4bits

Format:

```
l.exthz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order 16 bits of general-purpose register rA are copied into the low-order 16 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:16] <- 0
rD[15:0] <- rA[15:0]
```

64-bit Implementation:

```
rD[63:16] <- 0
rD[15:0] <- rA[15:0]
```

Exceptions:

None

l.extws Extend Word with Sign l.extws

31 26	25 . . . 21	20 . . . 16	15 10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	reserved	opcode 0x0	reserved	opcode 0xd
6 bits	5 bits	5 bits	6 bits	4 bits	2 bits	4bits

Format:

```
l.extws rD,rA,rB
```

Description:

Bit 31 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order 32 bits of general-purpose register rA are copied from low-order 32 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0]
```

64-bit Implementation:

```
rD[63:32] <- rA[31]
rD[31:0] <- rA[31:0]
```

Exceptions:

None

l.extwz **Extend Word with Zero** **l.extwz**

31 26	25 . . . 21	20 . . . 16	15 10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	reserved	opcode 0x1	reserved	opcode 0xd
6 bits	5 bits	5 bits	6 bits	4 bits	2 bits	4bits

Format:

```
l.extwz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order 32 bits of general-purpose register rA are copied into the low-order 32 bits of general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0]
```

64-bit Implementation:

```
rD[63:32] <- 0
rD[31:0] <- rA[31:0]
```

Exceptions:

None

l.ff1 Find First 1 l.ff1

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xf
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.ff1 rD,rA,rB
```

Description:

Position of the first '1' bit is written into general-purpose register rD. Checking for bit '1' starts with MSB, and counting is decremented for every zero bit. If first '1' bit is discovered in LSB, one is written into rD. If there is no '1' bit, zero is written in rD.

32-bit Implementation:

```
rD[31:0] <- rA[31] ?  32 :  rA[30] ?  31 ...  rA[0] ?  1 :  0
```

64-bit Implementation:

```
rD[63:0] <- rA[63] ?  64 :  rA[62] ?  63 ...  rA[0] ?  1 :  0
```

Exceptions:

None

l.j Jump l.j

31 26	25 0
opcode 0x0	N
6 bits	26bits

Format:

```
l.j N
```

Description:

The immediate value is shifted left two bits, sign-extended to program counter width, and then added to the address of the delay slot. The result is the effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction.

32-bit Implementation:

```
PC <- exts(Immediate << 2) + DelayInsnAddr
LR <- DelayInsnAddr + 4
```

64-bit Implementation:

```
PC <- exts(Immediate << 2) + DelayInsnAddr
LR <- DelayInsnAddr + 4
```

Exceptions:

None

l.jal Jump and Link l.jal

31 26	25 0
opcode 0x1	N
6 bits	26bits

Format:

```
l.jal N
```

Description:

The immediate value is shifted left two bits, sign-extended to program counter width, and then added to the address of the delay slot. The result is the effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction. The address of the instruction after the delay slot is placed in the link register.

32-bit Implementation:

```
PC <- exts(Immediate << 2) + DelayInsnAddr
LR <- DelayInsnAddr + 4
```

64-bit Implementation:

```
PC <- exts(Immediate << 2) + DelayInsnAddr
LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

l.jalr Jump and Link Register l.jalr

31 26	25 16	15 . . . 11	10 0
opcode 0x12	reserved	B	reserved
6 bits	10 bits	5 bits	11bits

Format:

```
l.jalr rB
```

Description:

The contents of general-purpose register rB is the effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction. The address of the instruction after the delay slot is placed in the link register.

32-bit Implementation:

```
PC <- rB
LR <- DelayInsnAddr + 4
```

64-bit Implementation:

```
PC <- rB
LR <- DelayInsnAddr + 4
```

Exceptions:

None

l.jr Jump Register l.jr

31 26	25 16	15 . . . 11	10 0
opcode 0x11	reserved	B	reserved
6 bits	10 bits	5 bits	11bits

Format:

```
l.jr rB
```

Description:

The contents of general-purpose register rB is the effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction.

32-bit Implementation:

```
PC <- rB
```

64-bit Implementation:

```
PC <- rB
```

Exceptions:

```
None
```

l.lbs Load Byte and Extend with Sign l.lbs

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x24	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.lbs rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The byte in memory addressed by EA is loaded into the low-order eight bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 7 of the loaded value.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
rD[7:0] <- (EA)[7:0]
rD[31:8] <- rD[7]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[7:0] <- (EA)[7:0]
rD[63:8] <- rD[7]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.lbz Load Byte and Extend with Zero l.lbz

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x23	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.lbz rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The byte in memory addressed by EA is loaded into the low-order eight bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
rD[7:0] <- (EA)[7:0]
rD[31:8] <- 0
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[7:0] <- (EA)[7:0]
rD[63:8] <- 0
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.ld Load Double Word l.ld

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x20	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.ld rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The double word in memory addressed by EA is loaded into general-purpose register rD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[63:0] <- (EA)[63:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.lhs Load Half Word and Extend with Sign l.lhs

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x26	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.lhs rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The half word in memory addressed by EA is loaded into the low-order 16 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 15 of the loaded value.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
rD[15:0] <- (EA)[15:0]
rD[31:16] <- rD[15]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[15:0] <- (EA)[15:0]
rD[63:16] <- rD[15]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.lhz Load Half Word and Extend with Zero l.lhz

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x25	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.lhz rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The half word in memory addressed by EA is loaded into the low-order 16 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
rD[15:0] <- (EA)[15:0]
rD[31:16] <- 0
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[15:0] <- (EA)[15:0]
rD[63:16] <- 0
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.lws Load Single Word and Extend with Sign l.lws

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x22	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.lws rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The single word in memory addressed by EA is loaded into the low-order 32 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 31 of the loaded value.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
rD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[31:0] <- (EA)[31:0]
rD[63:32] <- rD[31]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.lwz Load Single Word and Extend with Zero l.lwz

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x21	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.lwz rD,I(rA)
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The single word in memory addressed by EA is loaded into the low-order 32 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
rD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
rD[31:0] <- (EA)[31:0]
rD[63:32] <- 0
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.mac Multiply Signed and Accumulate l.mac

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 4	3 . . 0
opcode 0x31	reserved	A	B	reserved	opcode 0x1
6 bits	5 bits	5 bits	5 bits	7 bits	4bits

Format:

```
l.mac rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied, and the result is truncated to 32 bits and added to the special-purpose registers MACHI and MACLO. All operands are treated as signed integers.

32-bit Implementation:

```
temp[31:0] <- rA[31:0] * rB[31:0]
MACHI[31:0]MACLO[31:0] <- temp[31:0] + MACHI[31:0]MACLO[31:0]
```

64-bit Implementation:

```
temp[31:0] <- rA[63:0] * rB[63:0]
MACHI[31:0]MACLO[31:0] <- temp[31:0] + MACHI[31:0]MACLO[31:0]
```

Exceptions:

None

l.maci Multiply Immediate Signed and Accumulate l.maci

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x13	I	reserved	B	I
6 bits	5 bits	5 bits	5 bits	11bits

Format:

```
l.maci rB,I
```

Description:

The immediate value and the contents of general-purpose register rA are multiplied, and the result is truncated to 32 bits and added to the special-purpose registers MACHI and MACLO. All operands are treated as signed integers.

32-bit Implementation:

```
temp[31:0] <- rA[31:0] * Immediate
MACHI[31:0]MACLO[31:0] <- temp[31:0] + MACHI[31:0]MACLO[31:0]
```

64-bit Implementation:

```
temp[31:0] <- rA[63:0] * Immediate
MACHI[31:0]MACLO[31:0] <- temp[31:0] + MACHI[31:0]MACLO[31:0]
```

Exceptions:

None

l.mfspr Move From Special-Purpose Register l.mfspr

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2d	D	A	K
6 bits	5 bits	5 bits	16bits

Format:

```
l.mfspr rD,rA,K
```

Description:

The contents of the special register are identified by the sum of general-purpose rA, and the immediate value are moved into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- spr(rA+Immediate)
```

64-bit Implementation:

```
rD[63:0] <- spr(rA+Immediate)
```

Exceptions:

None

l.movhi Move Immediate High l.movhi

31 26	25 . . . 21	20 . . 17	16	15 0
opcode 0x6	D	reserved	opcode 0x0	K
6 bits	5 bits	4 bits	1 bits	16bits

Format:

```
l.movhi rD,K
```

Description:

The 16-bit immediate value is zero-extended, shifted left by 16 bits, and placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- extz(Immediate) << 16
```

64-bit Implementation:

```
rD[63:0] <- extz(Immediate) << 16
```

Exceptions:

None

l.msync Memory Syncronization l.msync



Format:

```
l.msync
```

Description:

Execution of the memory synchronization instruction results in completion of all load/store operations before the RISC core continues.

32-bit Implementation:

```
memory-synchronization
```

64-bit Implementation:

```
memory-synchronization
```

Exceptions:

```
None
```

l.mtspr Move To Special-Purpose Register l.mtspr

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x30	K	A	B	K
6 bits	5 bits	5 bits	5 bits	11bits

Format:

```
l.mtspr rA,rB,K
```

Description:

The contents of general-purpose register rB are moved into the special register identified by the sum of general-purpose register rA and the immediate value.

32-bit Implementation:

```
spr(rA+Immediate) <- rB[31:0]
```

64-bit Implementation:

```
spr(rA+Immediate) <- rB[31:0]
```

Exceptions:

None

l.mul Multiply Signed l.mul

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0x6
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.mul rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied, and the result is truncated to destination register width and placed into general-purpose register rD. Both operands are treated as signed integers.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] * rB[31:0]
SR[OV] <- overflow
SR[CY] <- carry
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] * rB[63:0]
SR[OV] <- overflow
SR[CY] <- carry
```

Exceptions:

```
Range Exception
```

l.muli Multiply Immediate Signed l.muli

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2c	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.muli rD,rA,I
```

Description:

The immediate value and the contents of general-purpose register rA are multiplied, and the result is truncated to destination register width and placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] * Immediate
SR[OV] <- overflow
SR[CY] <- carry
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] * Immediate
SR[OV] <- overflow
SR[CY] <- carry
```

Exceptions:

```
Range Exception
```

l.mulu Multiply Unsigned l.mulu

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0xb
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.mulu rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied, and the result is truncated to destination register width and placed into general-purpose register rD. Both operands are treated as unsigned integers.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] * rB[31:0]
SR[OV] <- overflow
SR[CY] <- carry
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] * rB[63:0]
SR[OV] <- overflow
SR[CY] <- carry
```

Exceptions:

```
Range Exception
```

l.nop **No Operation** **l.nop**

31 24	23 16	15 0
opcode 0x15	reserved	K
8 bits	8 bits	16bits

Format:

```
l.nop K
```

Description:

This instruction does not do anything except that it takes at least one clock cycle to complete. It is often used to fill delay slot gaps.Immediate value can be used for simulation purposes.

32-bit Implementation:

64-bit Implementation:

Exceptions:

```
None
```

l.or Or l.or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x4
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.or rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical OR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] OR rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] OR rB[63:0]
```

Exceptions:

None

l.ori Or with Immediate Half Word l.ori

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2a	D	A	K
6 bits	5 bits	5 bits	16bits

Format:

```
l.ori rD,rA,K
```

Description:

The immediate value is zero-extended and combined with the contents of general-purpose register rA in a bit-wise logical OR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] OR extz(Immediate)
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] OR extz(Immediate)
```

Exceptions:

None

l.psync Pipeline Syncronization l.psync



Format:

```
l.psync
```

Description:

Execution of pipeline synchronization instruction results in completion of all instructions that were fetched before l.psync instruction. Once all instructions are completed, instructions fetched after l.psync are flushed from the pipeline and fetched again.

32-bit Implementation:

```
pipeline-synchronization
```

64-bit Implementation:

```
pipeline-synchronization
```

Exceptions:

```
None
```

l.rfe Return From Exception l.rfe

31 26	25 0
opcode 0x9	reserved
6 bits	26bits

Format:

```
l.rfe
```

Description:

Execution of this instruction partially restores the state of the processor prior to the exception. This instruction does not have a delay slot.

32-bit Implementation:

```
PC <- EPCR
SR <- ESR
```

64-bit Implementation:

```
PC <- EPCR
SR <- ESR
```

Exceptions:

None

l.ror **Rotate Right** **l.ror**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0x8
6 bits	5 bits	5 bits	5 bits	1 bits	4 bits	2 bits	4bits

Format:

```
l.ror rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions; the contents of general-purpose register rA are rotated right. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-rB[5:0]:0] <- rA[31:rB]
rD[31:32-rB[5:0]] <- rA[rB[5:0]-1:0]
```

64-bit Implementation:

```
rD[63-rB[5:0]:0] <- rA[63:rB]
rD[63:64-rB[5:0]] <- rA[rB[5:0]-1:0]
```

Exceptions:

None

l.rori Rotate Right with Immediate l.rori

31 26	25 . . . 21	20 . . . 16	15 8	7 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x3	L
6 bits	5 bits	5 bits	8 bits	2 bits	6bits

Format:

```
l.rori rD,rA,L
```

Description:

The 6-bit immediate value specifies the number of bit positions; the contents of general-purpose register rA are rotated right. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-L:0] <- rA[31:L]
rD[31:32-L] <- rA[L-1:0]
```

64-bit Implementation:

```
rD[63-L:0] <- rA[63:L]
rD[63:64-L] <- rA[L-1:0]
```

Exceptions:

None

l.sb Store Byte l.sb

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x36	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11bits

Format:

```
l.sb I(rA),rB
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The low-order 8 bits of general-purpose register rB are stored to memory location addressed by EA.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
(EA)[7:0] <- rB[7:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
(EA)[7:0] <- rB[7:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.sd Store Double Word l.sd

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x34	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11bits

Format:

```
l.sd I(rA),rB
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The double word in general-purpose register rB is stored to memory location addressed by EA.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
(EA)[63:0] <- rB[63:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.sfeq Set Flag if Equal l.sfeq

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x720	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfeq rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared. If the contents are equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] == rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] == rB[63:0]
```

Exceptions:

None

l.sfeqi Set Flag if Equal Immediate l.sfeqi

31 21	20 . . . 16	15 0
opcode 0x5e0	A	I
11 bits	5 bits	16bits

Format:

```
l.sfeqi rA,I
```

Description:

The contents of general-purpose register rA and the sign-extended immediate value are compared. If the two values are equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] == exts(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] == exts(Immediate)
```

Exceptions:

```
None
```

l.sfges Set Flag if Greater or Equal Than Signed l.sfges

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72b	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfges rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as signed integers. If the contents of the first register are greater than or equal to the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] >= rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] >= rB[63:0]
```

Exceptions:

None

l.sfgesi Set Flag if Greater or Equal Than Immediate Signed l.sfgesi

31 21	20 . . . 16	15 0
opcode 0x5eb	A	I
11 bits	5 bits	16bits

Format:

```
l.sfgesi rA,I
```

Description:

The contents of general-purpose register rA and the sign-extended immediate value are compared as signed integers. If the contents of the first register are greater than or equal to the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] >= exts(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] >= exts(Immediate)
```

Exceptions:

None

l.sfgeu Set Flag if Greater or Equal Than Unsigned l.sfgeu

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x723	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfgeu rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as unsigned integers. If the contents of the first register are greater than or equal to the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] >= rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] >= rB[63:0]
```

Exceptions:

None

l.sfgeui Set Flag if Greater or Equal Than Immediate Unsigned l.sfgeui

31 21	20 . . . 16	15 0
opcode 0x5e3	A	I
11 bits	5 bits	16bits

Format:

```
l.sfgeui rA,I
```

Description:

The contents of general-purpose register rA and the zero-extended immediate value are compared as unsigned integers. If the contents of the first register are greater than or equal to the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] >= extz(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] >= extz(Immediate)
```

Exceptions:

None

l.sfgts Set Flag if Greater Than Signed l.sfgts

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72a	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfgts rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as signed integers. If the contents of the first register are greater than the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] > rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] > rB[63:0]
```

Exceptions:

None

l.sfgtsi Set Flag if Greater Than Immediate Signed l.sfgtsi

31 21	20 . . . 16	15 0
opcode 0x5ea	A	I
11 bits	5 bits	16bits

Format:

```
l.sfgtsi rA,I
```

Description:

The contents of general-purpose register rA and the sign-extended immediate value are compared as signed integers. If the contents of the first register are greater than the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] > exts(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] > exts(Immediate)
```

Exceptions:

None

l.sfgtu Set Flag if Greater Than Unsigned l.sfgtu

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x722	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfgtu rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as unsigned integers. If the contents of the first register are greater than the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] > rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] > rB[63:0]
```

Exceptions:

None

l.sfgtui Set Flag if Greater Than Immediate Unsigned l.sfgtui

31 21	20 . . . 16	15 0
opcode 0x5e2	A	I
11 bits	5 bits	16bits

Format:

```
l.sfgtui rA,I
```

Description:

The contents of general-purpose register rA and the zero-extended immediate value are compared as unsigned integers. If the contents of the first register are greater than the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] > extz(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] > extz(Immediate)
```

Exceptions:

None

l.sfles Set Flag if Less or Equal Than Signed l.sfles

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72d	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfles rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as signed integers. If the contents of the first register are less than or equal to the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] <= rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] <= rB[63:0]
```

Exceptions:

None

l.sflesi Set Flag if Less or Equal Than Immediate Signed l.sflesi

31 21	20 . . . 16	15 0
opcode 0x5ed	A	I
11 bits	5 bits	16bits

Format:

```
l.sflesi rA,I
```

Description:

The contents of general-purpose register rA and the sign-extended immediate value are compared as signed integers. If the contents of the first register are less than or equal to the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] <= exts(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] <= exts(Immediate)
```

Exceptions:

None

l.sfleu Set Flag if Less or Equal Than Unsigned l.sfleu

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x725	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfleu rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as unsigned integers. If the contents of the first register are less than or equal to the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] <= rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] <= rB[63:0]
```

Exceptions:

None

l.sfleui Set Flag if Less or Equal Than Immediate Unsigned l.sfleui

31 21	20 . . . 16	15 0
opcode 0x5e5	A	I
11 bits	5 bits	16bits

Format:

```
l.sfleui rA,I
```

Description:

The contents of general-purpose register rA and the zero-extended immediate value are compared as unsigned integers. If the contents of the first register are less than or equal to the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] <= extz(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] <= extz(Immediate)
```

Exceptions:

None

l.sflts Set Flag if Less Than Signed l.sflts

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72c	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sflts rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as signed integers. If the contents of the first register are less than the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] < rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] < rB[63:0]
```

Exceptions:

None

l.sfltsi Set Flag if Less Than Immediate Signed l.sfltsi

31 21	20 . . . 16	15 0
opcode 0x5ec	A	I
11 bits	5 bits	16bits

Format:

```
l.sfltsi rA,I
```

Description:

The contents of general-purpose register rA and the sign-extended immediate value are compared as signed integers. If the contents of the first register are less than the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] < exts(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] < exts(Immediate)
```

Exceptions:

None

l.sfltu Set Flag if Less Than Unsigned l.sfltu

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x724	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfltu rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared as unsigned integers. If the contents of the first register are less than the contents of the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] < rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] < rB[63:0]
```

Exceptions:

None

l.sfltui Set Flag if Less Than Immediate Unsigned l.sfltui

31 21	20 . . . 16	15 0
opcode 0x5e4	A	I
11 bits	5 bits	16bits

Format:

```
l.sfltui rA,I
```

Description:

The contents of general-purpose register rA and the zero-extended immediate value are compared as unsigned integers. If the contents of the first register are less than the immediate value the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] < extz(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] < extz(Immediate)
```

Exceptions:

None

l.sfne Set Flag if Not Equal l.sfne

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x721	A	B	reserved
11 bits	5 bits	5 bits	11bits

Format:

```
l.sfne rA,rB
```

Description:

The contents of general-purpose registers rA and rB are compared. If the contents are not equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] != rB[31:0]
```

64-bit Implementation:

```
SR[F] <- rA[63:0] != rB[63:0]
```

Exceptions:

None

l.sfnei Set Flag if Not Equal Immediate l.sfnei

31 21	20 . . . 16	15 0
opcode 0x5e1	A	I
11 bits	5 bits	16bits

Format:

```
l.sfnei rA,I
```

Description:

The contents of general-purpose register rA and the sign-extended immediate value are compared. If the two values are not equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- rA[31:0] != exts(Immediate)
```

64-bit Implementation:

```
SR[F] <- rA[63:0] != exts(Immediate)
```

Exceptions:

None

l.sh Store Half Word l.sh

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x37	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11bits

Format:

```
l.sh I(rA),rB
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The low-order 16 bits of general-purpose register rB are stored to memory location addressed by EA.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
(EA)[15:0] <- rB[15:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
(EA)[15:0] <- rB[15:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.sll Shift Left Logical l.sll

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x8
6 bits	5 bits	5 bits	5 bits	1 bits	4 bits	2 bits	4bits

Format:

```
l.sll rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions; the contents of general-purpose register rA are shifted left, inserting zeros into the low-order bits. The result is written into general-purpose rD.

32-bit Implementation:

```
rD[31:rB[5:0]] <- rA[31-rB[5:0]:0]
rD[rB[5:0]-1:0] <- 0
```

64-bit Implementation:

```
rD[63:rB[5:0]] <- rA[63-rB[5:0]:0]
rD[rB[5:0]-1:0] <- 0
```

Exceptions:

None

l.slli Shift Left Logical with Immediate l.slli

31 26	25 . . . 21	20 . . . 16	15 8	7 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x0	L
6 bits	5 bits	5 bits	8 bits	2 bits	6bits

Format:

```
l.slli rD,rA,L
```

Description:

The 6-bit immediate value specifies the number of bit positions; the contents of general-purpose register rA are shifted left, inserting zeros into the low-order bits. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31:L] <- rA[31-L:0]
rD[L-1:0] <- 0
```

64-bit Implementation:

```
rD[63:L] <- rA[63-L:0]
rD[L-1:0] <- 0
```

Exceptions:

None

l.sra Shift Right Arithmetic l.sra

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x2	reserved	opcode 0x8
6 bits	5 bits	5 bits	5 bits	1 bits	4 bits	2 bits	4bits

Format:

```
l.sra rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions; the contents of general-purpose register rA are shifted right, sign-extending the high-order bits. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-rB[5:0]:0] <- rA[31:rB[5:0]]
rD[31:32-rB[5:0]] <- rA[31]
```

64-bit Implementation:

```
rD[63-rB[5:0]:0] <- rA[63:rB[5:0]]
rD[63:64-rB[5:0]] <- rA[63]
```

Exceptions:

None

l.srai Shift Right Arithmetic with Immediate l.srai

31 26	25 . . . 21	20 . . . 16	15 8	7 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x2	L
6 bits	5 bits	5 bits	8 bits	2 bits	6bits

Format:

```
l.srai rD,rA,L
```

Description:

The 6-bit immediate value specifies the number of bit positions; the contents of general-purpose register rA are shifted right, sign-extending the high-order bits. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-L:0] <- rA[31:L]
rD[31:32-L] <- rA[31]
```

64-bit Implementation:

```
rD[63-L:0] <- rA[63:L]
rD[63:64-L] <- rA[63]
```

Exceptions:

None

l.srl Shift Right Logical l.srl

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 . . 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x1	reserved	opcode 0x8
6 bits	5 bits	5 bits	5 bits	1 bits	4 bits	2 bits	4bits

Format:

```
l.srl rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions; the contents of general-purpose register rA are shifted right, inserting zeros into the high-order bits. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-rB[5:0]:0] <- rA[31:rB[5:0]]
rD[31:32-rB[5:0]] <- 0
```

64-bit Implementation:

```
rD[63-rB[5:0]:0] <- rA[63:rB[5:0]]
rD[63:64-rB[5:0]] <- 0
```

Exceptions:

None

l.srli Shift Right Logical with Immediate l.srli

31 26	25 . . . 21	20 . . . 16	15 8	7 6	5 0
opcode 0x2e	D	A	reserved	opcode 0x1	L
6 bits	5 bits	5 bits	8 bits	2 bits	6bits

Format:

```
l.srli rD,rA,L
```

Description:

The 6-bit immediate value specifies the number of bit positions; the contents of general-purpose register rA are shifted right, inserting zeros into the high-order bits. The result is written into general-purpose register rD.

32-bit Implementation:

```
rD[31-L:0] <- rA[31:L]
rD[31:32-L] <- 0
```

64-bit Implementation:

```
rD[63-L:0] <- rA[63:L]
rD[63:64-L] <- 0
```

Exceptions:

None

l.sub Subtract Signed l.sub

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x2
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.sub rD,rA,rB
```

Description:

The contents of general-purpose register rB are subtracted from the contents of general-purpose register rA to form the result. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] - rB[31:0]
SR[CY] <- carry
SR[OV] <- overflow
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] - rB[63:0]
SR[CY] <- carry
SR[OV] <- overflow
```

Exceptions:

```
Range Exception
```

l.sw Store Single Word l.sw

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x35	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11bits

Format:

```
l.sw I(rA),rB
```

Description:

The offset is sign-extended and added to the contents of general-purpose register rA. The sum represents an effective address. The low-order 32 bits of general-purpose register rB are stored to memory location addressed by EA.

32-bit Implementation:

```
EA <- exts(Immediate) + rA[31:0]
(EA)[31:0] <- rB[31:0]
```

64-bit Implementation:

```
EA <- exts(Immediate) + rA[63:0]
(EA)[31:0] <- rB[31:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
Alignment
```

l.sys System Call l.sys

31 16	15 0
opcode 0x2000	K
16 bits	16bits

Format:

```
l.sys K
```

Description:

Execution of the system call instruction results in the system call exception. The system calls exception is a request to the operating system to provide operating system services. The immediate value specifies which system service is required.

32-bit Implementation:

```
system-call-exception()
```

64-bit Implementation:

```
system-call-exception()
```

Exceptions:

```
System Call
```

l.trap **Trap** **l.trap**

31 16	15 0
opcode 0x2100	K
16 bits	16bits

Format:

```
l.trap K
```

Description:

Execution of trap instruction results in the trap exception if specified bit in SR is set. Trap exception is a request to the operating system or to the debug facility to execute certain debug services. Immediate value is used to select which SR bit is tested by trap instruction.

32-bit Implementation:

```
if SR[K] = 1 then trap-exception()
```

64-bit Implementation:

```
if SR[K] = 1 then trap-exception()
```

Exceptions:

```
Trap exception
```

l.xor **Exclusive Or** **l.xor**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10	9 8	7 . . 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x5
6 bits	5 bits	5 bits	5 bits	1 bits	2 bits	4 bits	4bits

Format:

```
l.xor rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical XOR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] XOR rB[31:0]
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] XOR rB[63:0]
```

Exceptions:

None

l.xori Exclusive Or with Immediate Half Word l.xori

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2b	D	A	I
6 bits	5 bits	5 bits	16bits

Format:

```
l.xori rD,rA,I
```

Description:

The immediate value is zero-extended and combined with the contents of general-purpose register rA in a bit-wise logical XOR operation. The result is placed into general-purpose register rD.

32-bit Implementation:

```
rD[31:0] <- rA[31:0] XOR extz(Immediate)
```

64-bit Implementation:

```
rD[63:0] <- rA[63:0] XOR extz(Immediate)
```

Exceptions:

None

lf.add.d Add Floating-Point Double-Precision lf.add.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.add.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are added to the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] + vfrB[63:0]
```

Exceptions:

```
None
```

lf.add.s Add Floating-Point Single-Precision lf.add.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.add.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are added to the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] + vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.cust1.d Reserved for ORFPX64 Custom Instructions lf.cust1.d

31 26	25 8	7 . . 4	3 . . 0
opcode 0xc	reserved	opcode 0xe	reserved
6 bits	18 bits	4 bits	4bits

Format:

```
lf.cust1.d
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

lf.cust1.s Reserved for ORFPX32 Custom Instructions lf.cust1.s

31 26	25 8	7 . . 4	3 . . 0
opcode 0xb	reserved	opcode 0xe	reserved
6 bits	18 bits	4 bits	4bits

Format:

```
lf.cust1.s
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

lf.div.d Divide Floating-Point Double-Precision lf.div.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.div.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are divided by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] / vfrB[63:0]
```

Exceptions:

```
None
```

lf.div.s Divide Floating-Point Single-Precision lf.div.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.div.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are divided by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] / vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.madd.d Multiply and Add Floating-Point Double-Precision lf.madd.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.madd.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are multiplied by the contents of vector/floating-point register vfrB, and added to special-purpose register FPMADDLO/FPMADDHI.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
FPMADDHI[31:0]FPMADDLO[31:0] <- vfrA[63:0] * vfrB[63:0] + FPMADDHI[31:0]FPMADDLO[31:0]
```

Exceptions:

```
None
```

lf.madd.s Multiply and Add Floating-Point Single-Precision lf.madd.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.madd.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are multiplied by the contents of vector/floating-point register vfrB, and added to special-purpose register FPMADDLO/FPMADDHI.

32-bit Implementation:

```
FPMADDHI[31:0]FPMADDLO[31:0] <- vfrA[31:0] * vfrB[31:0] + FPMADDHI[31:0]FPMADDLO[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.mul.d Multiply Floating-Point Double-Precision lf.mul.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.mul.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are multiplied by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] * vfrB[63:0]
```

Exceptions:

```
None
```

lf.mul.s Multiply Floating-Point Single-Precision lf.mul.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.mul.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are multiplied by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] * vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.rem.d Remainder Floating-Point Double-Precision lf.rem.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.rem.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are divided by the contents of vector/floating-point register vfrB, and remainder is used as the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] % vfrB[63:0]
```

Exceptions:

```
None
```

lf.rem.s Remainder Floating-Point Single-Precision lf.rem.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.rem.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are divided by the contents of vector/floating-point register vfrB, and remainder is used as the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] % vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sfeq.d Set Flag if Equal Floating-Point Double-Precision lf.sfeq.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfeq.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
SR[F] <- vfrA[63:0] == vfrB[63:0]
```

Exceptions:

```
None
```

lf.sfeq.s Set Flag if Equal Floating-Point Single-Precision lf.sfeq.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfeq.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- vfrA[31:0] == vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sfge.d Set Flag if Greater or Equal Than Floating-Point Double-Precision lf.sfge.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfge.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is greater than or equal to the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
SR[F] <- vfrA[63:0] >= vfrB[63:0]
```

Exceptions:

```
None
```

lf.sfge.s Set Flag if Greater or Equal Than Floating-Point Single-Precision lf.sfge.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfge.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is greater than or equal to the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- vfrA[31:0] >= vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sfgt.d Set Flag if Greater Than Floating-Point Double-Precision lf.sfgt.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfgt.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is greater than the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
SR[F] <- vfrA[63:0] > vfrB[63:0]
```

Exceptions:

```
None
```

lf.sfgt.s Set Flag if Greater Than Floating-Point Single-Precision lf.sfgt.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfgt.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is greater than the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- vfrA[31:0] > vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sfle.d Set Flag if Less or Equal Than Floating-Point Double-Precision lf.sfle.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1d
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfle.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is less than or equal to the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
SR[F] <- vfrA[363:0] <= vfrB[63:0]
```

Exceptions:

```
None
```

lf.sfle.s Set Flag if Less or Equal Than Floating-Point Single-Precision lf.sfle.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1d
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfle.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is less than or equal to the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- vfrA[31:0] <= vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sflt.d Set Flag if Less Than Floating-Point Double-Precision lf.sflt.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1c
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sflt.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is less than the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
SR[F] <- vfrA[63:0] < vfrB[63:0]
```

Exceptions:

```
None
```

lf.sflt.s Set Flag if Less Than Floating-Point Single-Precision lf.sflt.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1c
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sflt.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the first register is less than the second register, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- vfrA[31:0] < vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sfne.d Set Flag if Not Equal Floating-Point Double-Precision lf.sfne.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfne.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are not equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
SR[F] <- vfrA[63:0] != vfrB[63:0]
```

Exceptions:

```
None
```

lf.sfne.s Set Flag if Not Equal Floating-Point Single-Precision lf.sfne.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sfne.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are not equal, the compare flag is set; otherwise the compare flag is cleared.

32-bit Implementation:

```
SR[F] <- vfrA[31:0] != vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lf.sub.d Subtract Floating-Point Double-Precision lf.sub.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sub.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrB are subtracted from the contents of vector/floating-point register vfrA to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] - vfrB[63:0]
```

Exceptions:

```
None
```

lf.sub.s Subtract Floating-Point Single-Precision lf.sub.s

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lf.sub.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrB are subtracted from the contents of vector/floating-point register vfrA to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
vfrD[31:0] <- vfrA[31:0] - vfrB[31:0]
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
None
```

lvf.ld Load Vector/Floating-Point Double Word lvf.ld

31 26	25 . . . 21	20 . . . 16	15 8	7 0
opcode 0xd	D	A	reserved	opcode 0x0
6 bits	5 bits	5 bits	8 bits	8bits

Format:

```
lvf.ld rD,0(rA)
```

Description:

The contents of vector/floating-point register vfrA are used as an effective address. The double word in memory addressed by EA is loaded into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- vfrA[63:0]
vfrD[63:0] <- (EA)[63:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
```

lvf.lw Load Vector/Floating-Point Single Word lvf.lw

31 26	25 . . . 21	20 . . . 16	15 8	7 0
opcode 0xd	D	A	reserved	opcode 0x1
6 bits	5 bits	5 bits	8 bits	8bits

Format:

```
lvf.lw rD,0(rA)
```

Description:

The contents of vector/floating-point register vfrA are used as an effective address. The double word in memory addressed by EA is loaded into vector/floating-point register vfrD.

32-bit Implementation:

```
EA <- vfrA[31:0]
vfrD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- vfrA[31:0]
vfrD[31:0] <- (EA)[31:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
```

lvf.sd Store Vector/Floating-Point Double Word lvf.sd

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xd	reserved	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lvf.sd 0(rA),rB
```

Description:

The contents of vector/floating-point register vfrA are used as an effective address. The double word in vector/floating-point register vrfB is stored to the memory location addressed by EA.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
EA <- vfrA[63:0]
vfrD[63:0] <- (EA)[63:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
```

lvf.sw Store Vector/Floating-Point Single Word lvf.sw

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xd	reserved	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lvf.sw 0(rA),rB
```

Description:

The contents of vector/floating-point register vfrA are used as an effective address. The single word in vector/floating-point register vrfB is stored to the memory location addressed by EA.

32-bit Implementation:

```
EA <- vfrA[31:0]
vfrD[31:0] <- (EA)[31:0]
```

64-bit Implementation:

```
EA <- vfrA[31:0]
vfrD[31:0] <- (EA)[31:0]
```

Exceptions:

```
TLB miss
Page fault
Bus error
```

lv.add.b Vector Byte Elements Add Signed lv.add.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x30
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.add.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] + vfrB[7:0]
vfrD[15:8] <- vfrA[15:8] + vfrB[15:8]
vfrD[23:16] <- vfrA[23:16] + vfrB[23:16]
vfrD[31:24] <- vfrA[31:24] + vfrB[31:24]
vfrD[39:32] <- vfrA[39:32] + vfrB[39:32]
vfrD[47:40] <- vfrA[47:40] + vfrB[47:40]
vfrD[55:48] <- vfrA[55:48] + vfrB[55:48]
vfrD[63:56] <- vfrA[63:56] + vfrB[63:56]
```

Exceptions:

```
None
```

lv.add.h Vector Half-Word Elements Add Signed lv.add.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x31
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.add.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] + vfrB[15:0]
vfrD[31:16] <- vfrA[31:16] + vfrB[31:16]
vfrD[47:32] <- vfrA[47:32] + vfrB[47:32]
vfrD[63:48] <- vfrA[63:48] + vfrB[63:48]
```

Exceptions:

```
None
```

lv.adds.b Vector Byte Elements Add Signed Saturated lv.adds.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x32
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.adds.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- sat8s(vfrA[7:0] + vfrB[7:0])
vfrD[15:8] <- sat8s(vfrA[15:8] + vfrB[15:8])
vfrD[23:16] <- sat8s(vfrA[23:16] + vfrB[23:16])
vfrD[31:24] <- sat8s(vfrA[31:24] + vfrB[31:24])
vfrD[39:32] <- sat8s(vfrA[39:32] + vfrB[39:32])
vfrD[47:40] <- sat8s(vfrA[47:40] + vfrB[47:40])
vfrD[55:48] <- sat8s(vfrA[55:48] + vfrB[55:48])
vfrD[63:56] <- sat8s(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

lv.adds.h Vector Half-Word Elements Add Signed Saturated lv.adds.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x33
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.adds.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] + vfrB[15:0])
vfrD[31:16] <- sat16s(vfrA[31:16] + vfrB[31:16])
vfrD[47:32] <- sat16s(vfrA[47:32] + vfrB[47:32])
vfrD[63:48] <- sat16s(vfrA[63:48] + vfrB[63:48])
```

Exceptions:

```
None
```

lv.addu.b Vector Byte Elements Add Unsigned lv.addu.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x34
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.addu.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrA are added to the unsigned byte elements of vector/floating-point register vfrB to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] + vfrB[7:0]
vfrD[15:8] <- vfrA[15:8] + vfrB[15:8]
vfrD[23:16] <- vfrA[23:16] + vfrB[23:16]
vfrD[31:24] <- vfrA[31:24] + vfrB[31:24]
vfrD[39:32] <- vfrA[39:32] + vfrB[39:32]
vfrD[47:40] <- vfrA[47:40] + vfrB[47:40]
vfrD[55:48] <- vfrA[55:48] + vfrB[55:48]
vfrD[63:56] <- vfrA[63:56] + vfrB[63:56]
```

Exceptions:

```
None
```

lv.addu.h Vector Half-Word Elements Add Unsigned lv.addu.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x35
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.addu.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrA are added to the unsigned half-word elements of vector/floating-point register vfrB to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] + vfrB[15:0]
vfrD[31:16] <- vfrA[31:16] + vfrB[31:16]
vfrD[47:32] <- vfrA[47:32] + vfrB[47:32]
vfrD[63:48] <- vfrA[63:48] + vfrB[63:48]
```

Exceptions:

```
None
```

lv.addus.b Vector Byte Elements Add Unsigned Saturated lv.addus.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x36
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.addus.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrA are added to the unsigned byte elements of vector/floating-point register vfrB to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- sat8u(vfrA[7:0] + vfrB[7:0])
vfrD[15:8] <- sat8u(vfrA[15:8] + vfrB[15:8])
vfrD[23:16] <- sat8u(vfrA[23:16] + vfrB[23:16])
vfrD[31:24] <- sat8u(vfrA[31:24] + vfrB[31:24])
vfrD[39:32] <- sat8u(vfrA[39:32] + vfrB[39:32])
vfrD[47:40] <- sat8u(vfrA[47:40] + vfrB[47:40])
vfrD[55:48] <- sat8u(vfrA[55:48] + vfrB[55:48])
vfrD[63:56] <- sat8u(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

lv.addus.h Vector Half-Word Elements Add Unsigned Saturated lv.addus.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x37
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.addus.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrA are added to the unsigned half-word elements of vector/floating-point register vfrB to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] + vfrB[15:0])
vfrD[31:16] <- sat16s(vfrA[31:16] + vfrB[31:16])
vfrD[47:32] <- sat16s(vfrA[47:32] + vfrB[47:32])
vfrD[63:48] <- sat16s(vfrA[63:48] + vfrB[63:48])
```

Exceptions:

```
None
```

lv.all_eq.b Vector Byte Elements All Equal lv.all_eq.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if all corresponding elements are equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] == vfrB[7:0]
   vfrA[15:8] == vfrB[15:8] &&
   vfrA[23:16] == vfrB[23:16] &&
   vfrA[31:24] == vfrB[31:24] &&
   vfrA[39:32] == vfrB[39:32] &&
   vfrA[47:40] == vfrB[47:40] &&
   vfrA[55:48] == vfrB[55:48] &&
   vfrA[63:56] == vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_eq.h Vector Half-Word Elements All Equal lv.all_eq.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if all corresponding elements are equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] == vfrB[15:0] &&
   vfrA[31:16] == vfrB[31:16] &&
   vfrA[47:32] == vfrB[47:32] &&
   vfrA[63:48] == vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_ge.b Vector Byte Elements All Greater Than or Equal To lv.all_ge.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are greater than or equal to the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] >= vfrB[7:0] &&
   vfrA[15:8] >= vfrB[15:8] &&
   vfrA[23:16] >= vfrB[23:16] &&
   vfrA[31:24] >= vfrB[31:24] &&
   vfrA[39:32] >= vfrB[39:32] &&
   vfrA[47:40] >= vfrB[47:40] &&
   vfrA[55:48] >= vfrB[55:48] &&
   vfrA[63:56] >= vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_ge.h Vector Half-Word Elements All Greater Than or Equal To lv.all_ge.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are greater than or equal to the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] >= vfrB[15:0] &&
   vfrA[31:16] >= vfrB[31:16] &&
   vfrA[47:32] >= vfrB[47:32] &&
   vfrA[63:48] >= vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_gt.b Vector Byte Elements All Greater Than lv.all_gt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x14
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are greater than the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] > vfrB[7:0] &&
   vfrA[15:8] > vfrB[15:8] &&
   vfrA[23:16] > vfrB[23:16] &&
   vfrA[31:24] > vfrB[31:24] &&
   vfrA[39:32] > vfrB[39:32] &&
   vfrA[47:40] > vfrB[47:40] &&
   vfrA[55:48] > vfrB[55:48] &&
   vfrA[63:56] > vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_gt.h Vector Half-Word Elements All Greater Than lv.all_gt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are greater than the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] > vfrB[15:0] &&
   vfrA[31:16] > vfrB[31:16] &&
   vfrA[47:32] > vfrB[47:32] &&
   vfrA[63:48] > vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_le.b Vector Byte Elements All Less Than or Equal To lv.all_le.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are less than or equal to the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] <= vfrB[7:0] &&
   vfrA[15:8] <= vfrB[15:8] &&
   vfrA[23:16] <= vfrB[23:16] &&
   vfrA[31:24] <= vfrB[31:24] &&
   vfrA[39:32] <= vfrB[39:32] &&
   vfrA[47:40] <= vfrB[47:40] &&
   vfrA[55:48] <= vfrB[55:48] &&
   vfrA[63:56] <= vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_le.h Vector Half-Word Elements All Less Than or Equal To lv.all_le.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are less than or equal to the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] <= vfrB[15:0] &&
   vfrA[31:16] <= vfrB[31:16] &&
   vfrA[47:32] <= vfrB[47:32] &&
   vfrA[63:48] <= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_lt.b **Vector Byte Elements All Less Than** **lv.all_lt.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are less than the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] < vfrB[7:0] &&
   vfrA[15:8] < vfrB[15:8] &&
   vfrA[23:16] < vfrB[23:16] &&
   vfrA[31:24] < vfrB[31:24] &&
   vfrA[39:32] < vfrB[39:32] &&
   vfrA[47:40] < vfrB[47:40] &&
   vfrA[55:48] < vfrB[55:48] &&
   vfrA[63:56] < vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_lt.h Vector Half-Word Elements All Less Than lv.all_lt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if all elements of vfrA are less than the elements of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] < vfrB[15:0] &&
   vfrA[31:16] < vfrB[31:16] &&
   vfrA[47:32] < vfrB[47:32] &&
   vfrA[63:48] < vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_ne.b Vector Byte Elements All Not Equal lv.all_ne.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if all corresponding elements are not equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] != vfrB[7:0] &&
   vfrA[15:8] != vfrB[15:8] &&
   vfrA[23:16] != vfrB[23:16] &&
   vfrA[31:24] != vfrB[31:24] &&
   vfrA[39:32] != vfrB[39:32] &&
   vfrA[47:40] != vfrB[47:40] &&
   vfrA[55:48] != vfrB[55:48] &&
   vfrA[63:56] != vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.all_ne.h Vector Half-Word Elements All Not Equal lv.all_ne.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.all_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if all corresponding elements are not equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] != vfrB[15:0] &&
   vfrA[31:16] != vfrB[31:16] &&
   vfrA[47:32] != vfrB[47:32] &&
   vfrA[63:48] != vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.and Vector And lv.and

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x38
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.and rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical AND operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] AND vfrB[63:0]
```

Exceptions:

```
None
```

lv.any_eq.b Vector Byte Elements Any Equal lv.any_eq.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x20
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if any two corresponding elements are equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] == vfrB[7:0] ||
   vfrA[15:8] == vfrB[15:8] ||
   vfrA[23:16] == vfrB[23:16] ||
   vfrA[31:24] == vfrB[31:24] ||
   vfrA[39:32] == vfrB[39:32] ||
   vfrA[47:40] == vfrB[47:40] ||
   vfrA[55:48] == vfrB[55:48] ||
   vfrA[63:56] == vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_eq.h Vector Half-Word Elements Any Equal lv.any_eq.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x21
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if any two corresponding elements are equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] == vfrB[15:0] ||
   vfrA[31:16] == vfrB[31:16] ||
   vfrA[47:32] == vfrB[47:32] ||
   vfrA[63:48] == vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_ge.b Vector Byte Elements Any Greater Than or Equal To lv.any_ge.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x22
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is greater than or equal to the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] >= vfrB[7:0] ||
   vfrA[15:8] >= vfrB[15:8] ||
   vfrA[23:16] >= vfrB[23:16] ||
   vfrA[31:24] >= vfrB[31:24] ||
   vfrA[39:32] >= vfrB[39:32] ||
   vfrA[47:40] >= vfrB[47:40] ||
   vfrA[55:48] >= vfrB[55:48] ||
   vfrA[63:56] >= vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_ge.h Vector Half-Word Elements Any Greater Than or Equal To lv.any_ge.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x23
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is greater than or equal to the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] >= vfrB[15:0] ||
   vfrA[31:16] >= vfrB[31:16] ||
   vfrA[47:32] >= vfrB[47:32] ||
   vfrA[63:48] >= vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_gt.b Vector Byte Elements Any Greater Than lv.any_gt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x24
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is greater than the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] > vfrB[7:0] ||
   vfrA[15:8] > vfrB[15:8] ||
   vfrA[23:16] > vfrB[23:16] ||
   vfrA[31:24] > vfrB[31:24] ||
   vfrA[39:32] > vfrB[39:32] ||
   vfrA[47:40] > vfrB[47:40] ||
   vfrA[55:48] > vfrB[55:48] ||
   vfrA[63:56] > vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_gt.h Vector Half-Word Elements Any Greater Than lv.any_gt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x25
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is greater than the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] > vfrB[15:0] ||
   vfrA[31:16] > vfrB[31:16] ||
   vfrA[47:32] > vfrB[47:32] ||
   vfrA[63:48] > vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_le.b Vector Byte Elements Any Less Than or Equal To lv.any_le.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x26
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is less than or equal to the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] <= vfrB[7:0] ||
   vfrA[15:8] <= vfrB[15:8] ||
   vfrA[23:16] <= vfrB[23:16] ||
   vfrA[31:24] <= vfrB[31:24] ||
   vfrA[39:32] <= vfrB[39:32] ||
   vfrA[47:40] <= vfrB[47:40] ||
   vfrA[55:48] <= vfrB[55:48] ||
   vfrA[63:56] <= vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_le.h Vector Half-Word Elements Any Less Than or Equal To lv.any_le.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x27
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is less than or equal to the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] ,= vfrB[15:0] ||
   vfrA[31:16] <= vfrB[31:16] ||
   vfrA[47:32] <= vfrB[47:32] ||
   vfrA[63:48] <= vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_lt.b **Vector Byte Elements Any Less Than** **lv.any_lt.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x28
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is less than the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] < vfrB[7:0] ||
   vfrA[15:8] < vfrB[15:8] ||
   vfrA[23:16] < vfrB[23:16] ||
   vfrA[31:24] < vfrB[31:24] ||
   vfrA[39:32] < vfrB[39:32] ||
   vfrA[47:40] < vfrB[47:40] ||
   vfrA[55:48] < vfrB[55:48] ||
   vfrA[63:56] < vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_lt.h Vector Half-Word Elements Any Less Than lv.any_lt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x29
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if any element of vfrA is less than the corresponding element of vfrB; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] < vfrB[15:0] ||
   vfrA[31:16] < vfrB[31:16] ||
   vfrA[47:32] < vfrB[47:32] ||
   vfrA[63:48] < vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_ne.b **Vector Byte Elements Any Not Equal** **lv.any_ne.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x2a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. The compare flag is set if any two corresponding elements are not equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[7:0] != vfrB[7:0] ||
   vfrA[15:8] != vfrB[15:8] ||
   vfrA[23:16] != vfrB[23:16] ||
   vfrA[31:24] != vfrB[31:24] ||
   vfrA[39:32] != vfrB[39:32] ||
   vfrA[47:40] != vfrB[47:40] ||
   vfrA[55:48] != vfrB[55:48] ||
   vfrA[63:56] != vfrB[63:56]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.any_ne.h Vector Half-Word Elements Any Not Equal lv.any_ne.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x2b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.any_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. The compare flag is set if any two corresponding elements are not equal; otherwise the compare flag is cleared.
The compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
flag <- vfrA[15:0] != vfrB[15:0] ||
   vfrA[31:16] != vfrB[31:16] ||
   vfrA[47:32] != vfrB[47:32] ||
   vfrA[63:48] != vfrB[63:48]
vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

lv.avg.b Vector Byte Elements Average lv.avg.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x39
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.avg.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB, and the sum is shifted right by one to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- (vfrA[7:0] + vfrB[7:0]) » 1
vfrD[15:8] <- (vfrA[15:8] + vfrB[15:8]) » 1
vfrD[23:16] <- (vfrA[23:16] + vfrB[23:16]) » 1
vfrD[31:24] <- (vfrA[31:24] + vfrB[31:24]) » 1
vfrD[39:32] <- (vfrA[39:32] + vfrB[39:32]) » 1
vfrD[47:40] <- (vfrA[47:40] + vfrB[47:40]) » 1
vfrD[55:48] <- (vfrA[55:48] + vfrB[55:48]) » 1
vfrD[63:56] <- (vfrA[63:56] + vfrB[63:56]) » 1
```

Exceptions:

```
None
```

lv.avg.h Vector Half-Word Elements Average lv.avg.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x3a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.avg.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB, and the sum is shifted right by one to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- (vfrA[15:0] + vfrB[15:0]) » 1
vfrD[31:16] <- (vfrA[31:16] + vfrB[31:16]) » 1
vfrD[47:32] <- (vfrA[47:32] + vfrB[47:32]) » 1
vfrD[63:48] <- (vfrA[63:48] + vfrB[63:48]) » 1
```

Exceptions:

```
None
```

lv.cmp_eq.b Vector Byte Elements Compare Equal lv.cmp_eq.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x40
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the two corresponding compared elements are equal; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] == vfrB[7:0]
vfrD[15:8] <- repl(vfrA[15:8] == vfrB[15:8]
vfrD[23:16] <- repl(vfrA[23:16] == vfrB[23:16]
vfrD[31:24] <- repl(vfrA[31:24] == vfrB[31:24]
vfrD[39:32] <- repl(vfrA[39:32] == vfrB[39:32]
vfrD[47:40] <- repl(vfrA[47:40] == vfrB[47:40]
vfrD[55:48] <- repl(vfrA[55:48] == vfrB[55:48]
vfrD[63:56] <- repl(vfrA[63:56] == vfrB[63:56]
```

Exceptions:

```
None
```

lv.cmp_eq.h Vector Half-Word Elements Compare Equal lv.cmp_eq.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x41
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the two corresponding compared elements are equal; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] == vfrB[7:0]
vfrD[31:16] <- repl(vfrA[23:16] == vfrB[23:16]
vfrD[47:32] <- repl(vfrA[39:32] == vfrB[39:32]
vfrD[63:48] <- repl(vfrA[55:48] == vfrB[55:48]
```

Exceptions:

```
None
```

lv.cmp_ge.b Vector Byte Elements Compare Greater Than or Equal To lv.cmp_ge.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x42
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is greater than or equal to the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] >= vfrB[7:0]
vfrD[15:8] <- repl(vfrA[15:8] >= vfrB[15:8]
vfrD[23:16] <- repl(vfrA[23:16] >= vfrB[23:16]
vfrD[31:24] <- repl(vfrA[31:24] >= vfrB[31:24]
vfrD[39:32] <- repl(vfrA[39:32] >= vfrB[39:32]
vfrD[47:40] <- repl(vfrA[47:40] >= vfrB[47:40]
vfrD[55:48] <- repl(vfrA[55:48] >= vfrB[55:48]
vfrD[63:56] <- repl(vfrA[63:56] >= vfrB[63:56]
```

Exceptions:

```
None
```

lv.cmp_ge.h Vector Half-Word Elements Compare Greater Than or Equal To lv.cmp_ge.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x43
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is greater than or equal to the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] >= vfrB[7:0]
vfrD[31:16] <- repl(vfrA[23:16] >= vfrB[23:16]
vfrD[47:32] <- repl(vfrA[39:32] >= vfrB[39:32]
vfrD[63:48] <- repl(vfrA[55:48] >= vfrB[55:48]
```

Exceptions:

```
None
```

lv.cmp_gt.b Vector Byte Elements Compare Greater Than lv.cmp_gt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x44
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is greater than the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] > vfrB[7:0]
vfrD[15:8] <- repl(vfrA[15:8] > vfrB[15:8]
vfrD[23:16] <- repl(vfrA[23:16] > vfrB[23:16]
vfrD[31:24] <- repl(vfrA[31:24] > vfrB[31:24]
vfrD[39:32] <- repl(vfrA[39:32] > vfrB[39:32]
vfrD[47:40] <- repl(vfrA[47:40] > vfrB[47:40]
vfrD[55:48] <- repl(vfrA[55:48] > vfrB[55:48]
vfrD[63:56] <- repl(vfrA[63:56] > vfrB[63:56]
```

Exceptions:

```
None
```

lv.cmp_gt.h Vector Half-Word Elements Compare Greater Than lv.cmp_gt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x45
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is greater than the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] > vfrB[7:0]
vfrD[31:16] <- repl(vfrA[23:16] > vfrB[23:16]
vfrD[47:32] <- repl(vfrA[39:32] > vfrB[39:32]
vfrD[63:48] <- repl(vfrA[55:48] > vfrB[55:48]
```

Exceptions:

```
None
```

lv.cmp_le.b Vector Byte Elements Compare Less Than or Equal To lv.cmp_le.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x46
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is less than or equal to the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] <= vfrB[7:0]
vfrD[15:8] <- repl(vfrA[15:8] <= vfrB[15:8]
vfrD[23:16] <- repl(vfrA[23:16] <= vfrB[23:16]
vfrD[31:24] <- repl(vfrA[31:24] <= vfrB[31:24]
vfrD[39:32] <- repl(vfrA[39:32] <= vfrB[39:32]
vfrD[47:40] <- repl(vfrA[47:40] <= vfrB[47:40]
vfrD[55:48] <- repl(vfrA[55:48] <= vfrB[55:48]
vfrD[63:56] <- repl(vfrA[63:56] <= vfrB[63:56]
```

Exceptions:

```
None
```

lv.cmp_le.h Vector Half-Word Elements Compare Less Than or Equal To lv.cmp_le.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x47
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is less than or equal to the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] <= vfrB[7:0]
vfrD[31:16] <- repl(vfrA[23:16] <= vfrB[23:16]
vfrD[47:32] <- repl(vfrA[39:32] <= vfrB[39:32]
vfrD[63:48] <- repl(vfrA[55:48] <= vfrB[55:48]
```

Exceptions:

```
None
```

lv.cmp_lt.b Vector Byte Elements Compare Less Than lv.cmp_lt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x48
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is less than the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] <= vfrB[7:0]
vfrD[15:8] <- repl(vfrA[15:8] <= vfrB[15:8]
vfrD[23:16] <- repl(vfrA[23:16] <= vfrB[23:16]
vfrD[31:24] <- repl(vfrA[31:24] <= vfrB[31:24]
vfrD[39:32] <- repl(vfrA[39:32] <= vfrB[39:32]
vfrD[47:40] <- repl(vfrA[47:40] <= vfrB[47:40]
vfrD[55:48] <- repl(vfrA[55:48] <= vfrB[55:48]
vfrD[63:56] <- repl(vfrA[63:56] <= vfrB[63:56]
```

Exceptions:

```
None
```

lv.cmp_lt.h Vector Half-Word Elements Compare Less Than lv.cmp_lt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x49
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the element in vfrA is less than the element in vfrB; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] <= vfrB[7:0]
vfrD[31:16] <- repl(vfrA[23:16] <= vfrB[23:16]
vfrD[47:32] <- repl(vfrA[39:32] <= vfrB[39:32]
vfrD[63:48] <- repl(vfrA[55:48] <= vfrB[55:48]
```

Exceptions:

```
None
```

lv.cmp_ne.b Vector Byte Elements Compare Not Equal lv.cmp_ne.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x4a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the two corresponding compared elements are not equal; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- repl(vfrA[7:0] != vfrB[7:0])
vfrD[15:8] <- repl(vfrA[15:8] != vfrB[15:8])
vfrD[23:16] <- repl(vfrA[23:16] != vfrB[23:16])
vfrD[31:24] <- repl(vfrA[31:24] != vfrB[31:24])
vfrD[39:32] <- repl(vfrA[39:32] != vfrB[39:32])
vfrD[47:40] <- repl(vfrA[47:40] != vfrB[47:40])
vfrD[55:48] <- repl(vfrA[55:48] != vfrB[55:48])
vfrD[63:56] <- repl(vfrA[63:56] != vfrB[63:56])
```

Exceptions:

```
None
```

lv.cmp_ne.h Vector Half-Word Elements Compare Not Equal lv.cmp_ne.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x4b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.cmp_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if the two corresponding compared elements are not equal; otherwise the element bits are cleared.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- repl(vfrA[7:0] != vfrB[7:0])
vfrD[31:16] <- repl(vfrA[23:16] != vfrB[23:16])
vfrD[47:32] <- repl(vfrA[39:32] != vfrB[39:32])
vfrD[63:48] <- repl(vfrA[55:48] != vfrB[55:48])
```

Exceptions:

```
None
```

lv.cust1 Reserved for Custom Vector Instructions lv.cust1

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xc	reserved
6 bits	18 bits	4 bits	4bits

Format:

```
lv.cust1
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

lv.cust2 Reserved for Custom Vector Instructions lv.cust2

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xd	reserved
6 bits	18 bits	4 bits	4bits

Format:

```
lv.cust2
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

lv.cust3 Reserved for Custom Vector Instructions lv.cust3

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xe	reserved
6 bits	18 bits	4 bits	4bits

Format:

```
lv.cust3
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

lv.cust4 Reserved for Custom Vector Instructions lv.cust4

31 26	25 8	7 . . 4	3 . . 0
opcode 0xa	reserved	opcode 0xf	reserved
6 bits	18 bits	4 bits	4bits

Format:

```
lv.cust4
```

Description:

This fake instruction only allocates instruction set space for custom instructions. Custom instructions are those that are not defined by the architecture but instead by the implementation itself.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
N/A
```

Exceptions:

```
N/A
```

lv.madds.h Vector Half-Word Elements Multiply Add Signed Saturated lv.madds.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x54
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.madds.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form intermediate results. They are then added to the signed half-word VMAC elements to form the final results that are placed again in the VMAC registers. The intermediate result is placed into vector/floating-point register vfrD. If any of the final results exceeds the min/max value, it is saturated.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat32s(vfrA[15:0] * vfrB[15:0] + VMACLO[31:0])
vfrD[31:16] <- sat32s(vfrA[31:16] * vfrB[31:16] + VMACLO[63:32])
vfrD[47:32] <- sat32s(vfrA[47:32] * vfrB[47:32] + VMACHI[31:0])
vfrD[63:48] <- sat32s(vfrA[63:48] * vfrB[63:48] + VMACHI[63:32])
```

Exceptions:

```
None
```

lv.max.b Vector Byte Elements Maximum lv.max.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x55
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.max.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB, and the larger elements are selected to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] > vfrB[7:0] ?  vfrA[7:0] :  vrfB[7:0]
vfrD[15:8] <- vfrA[15:8] > vfrB[15:8] ?  vfrA[15:8] :  vrfB[15:8]
vfrD[23:16] <- vfrA[23:16] > vfrB[23:16] ?  vfrA[23:16] :  vrfB[23:16]
vfrD[31:24] <- vfrA[31:24] > vfrB[31:24] ?  vfrA[31:24] :  vrfB[31:24]
vfrD[39:32] <- vfrA[39:32] > vfrB[39:32] ?  vfrA[39:32] :  vrfB[39:32]
vfrD[47:40] <- vfrA[47:40] > vfrB[47:40] ?  vfrA[47:40] :  vrfB[47:40]
vfrD[55:48] <- vfrA[55:48] > vfrB[55:48] ?  vfrA[55:48] :  vrfB[55:48]
vfrD[63:56] <- vfrA[63:56] > vfrB[63:56] ?  vfrA[63:56] :  vrfB[63:56]
```

Exceptions:

```
None
```

lv.max.h Vector Half-Word Elements Maximum lv.max.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x56
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.max.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB, and the larger elements are selected to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] > vfrB[15:0] ?  vfrA[15:0] :  vrfB[15:0]
vfrD[31:16] <- vfrA[31:16] > vfrB[31:16] ?  vfrA[31:16] :  vrfB[31:16]
vfrD[47:32] <- vfrA[47:32] > vfrB[47:32] ?  vfrA[47:32] :  vrfB[47:32]
vfrD[63:48] <- vfrA[63:48] > vfrB[63:48] ?  vfrA[63:48] :  vrfB[63:48]
```

Exceptions:

```
None
```

lv.merge.b Vector Byte Elements Merge lv.merge.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x57
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.merge.b rD,rA,rB
```

Description:

The byte elements of the lower half of the vector/floating-point register vfrA are combined with the byte elements of the lower half of vector/floating-point register vfrB in such a way that the lowest element is from vfrB, the second element from vfrA, the third again from vfrB etc. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrB[7:0]
vfrD[15:8] <- vfrA[15:8]
vfrD[23:16] <- vfrB[23:16]
vfrD[31:24] <- vfrA[31:24]
vfrD[39:32] <- vfrB[39:32]
vfrD[47:40] <- vfrA[47:40]
vfrD[55:48] <- vfrB[55:48]
vfrD[63:56] <- vfrA[63:56]
```

Exceptions:

```
None
```

lv.merge.h Vector Half-Word Elements Merge lv.merge.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x58
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.merge.h rD,rA,rB
```

Description:

The half-word elements of the lower half of the vector/floating-point register vfrA are combined with the half-word elements of the lower half of vector/floating-point register vfrB in such a way that the lowest element is from vfrB, the second element from vfrA, the third again from vfrB etc. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrB[15:0]
vfrD[31:16] <- vfrA[31:16]
vfrD[47:32] <- vfrB[47:32]
vfrD[63:48] <- vfrA[63:48]
```

Exceptions:

```
None
```

lv.min.b Vector Byte Elements Minimum lv.min.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x59
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.min.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB, and the smaller elements are selected to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] < vfrB[7:0] ?  vfrA[7:0] :  vrfB[7:0]
vfrD[15:8] <- vfrA[15:8] < vfrB[15:8] ?  vfrA[15:8] :  vrfB[15:8]
vfrD[23:16] <- vfrA[23:16] < vfrB[23:16] ?  vfrA[23:16] :  vrfB[23:16]
vfrD[31:24] <- vfrA[31:24] < vfrB[31:24] ?  vfrA[31:24] :  vrfB[31:24]
vfrD[39:32] <- vfrA[39:32] < vfrB[39:32] ?  vfrA[39:32] :  vrfB[39:32]
vfrD[47:40] <- vfrA[47:40] < vfrB[47:40] ?  vfrA[47:40] :  vrfB[47:40]
vfrD[55:48] <- vfrA[55:48] < vfrB[55:48] ?  vfrA[55:48] :  vrfB[55:48]
vfrD[63:56] <- vfrA[63:56] < vfrB[63:56] ?  vfrA[63:56] :  vrfB[63:56]
```

Exceptions:

```
None
```

lv.min.h Vector Half-Word Elements Minimum lv.min.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.min.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB, and the smaller elements are selected to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] < vfrB[15:0] ?  vfrA[15:0] :  vrfB[15:0]
vfrD[31:16] <- vfrA[31:16] < vfrB[31:16] ?  vfrA[31:16] :  vrfB[31:16]
vfrD[47:32] <- vfrA[47:32] < vfrB[47:32] ?  vfrA[47:32] :  vrfB[47:32]
vfrD[63:48] <- vfrA[63:48] < vfrB[63:48] ?  vfrA[63:48] :  vrfB[63:48]
```

Exceptions:

```
None
```

lv.msubs.h Vector Half-Word Elements Multiply Subtract Signed Saturated lv.msubs.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.msubs.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form intermediate results. They are then subtracted from the signed half-word VMAC elements to form the final results that are placed again in the VMAC registers. The intermediate result is placed into vector/floating-point register vfrD. If any of the final results exceeds the min/max value, it is saturated.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat32s(VMACLO[31:0] - vfrA[15:0] * vfrB[15:0])
vfrD[31:16] <- sat32s(VMACLO[63:32] - vfrA[31:16] * vfrB[31:16])
vfrD[47:32] <- sat32s(VMACHI[31:0] - vfrA[47:32] * vfrB[47:32])
vfrD[63:48] <- sat32s(VMACHI[63:32] - vfrA[63:48] * vfrB[63:48])
```

Exceptions:

```
None
```

lv.muls.h Vector Half-Word Elements Multiply Signed Saturated lv.muls.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5c
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.muls.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form the results. The result is placed into vector/floating-point register vfrD. If any of the final results exceeds the min/max value, it is saturated.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat32s(vfrA[15:0] * vfrB[15:0])
vfrD[31:16] <- sat32s(vfrA[31:16] * vfrB[31:16])
vfrD[47:32] <- sat32s(vfrA[47:32] * vfrB[47:32])
vfrD[63:48] <- sat32s(vfrA[63:48] * vfrB[63:48])
```

Exceptions:

```
None
```

lv.nand Vector Not And lv.nand

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5d
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.nand rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical NAND operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] NAND vfrB[63:0]
```

Exceptions:

```
None
```

lv.nor Vector Not Or lv.nor

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5e
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.nor rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical NOR operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] NOR vfrB[63:0]
```

Exceptions:

```
None
```

lv.or Vector Or lv.or

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5f
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.or rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical OR operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] OR vfrB[63:0]
```

Exceptions:

```
None
```

lv.pack.b **Vector Byte Elements Pack** **lv.pack.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x60
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.pack.b rD,rA,rB
```

Description:

The lower half of the byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the byte truncated elements of the vector/floating-point register vfrB in such a way that the lowest elements are from vfrB, and the highest elements from vfrA. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[3:0] <- vfrB[3:0]
vfrD[7:4] <- vfrB[11:8]
vfrD[11:8] <- vfrB[19:16]
vfrD[15:12] <- vfrB[27:24]
vfrD[19:16] <- vfrB[35:32]
vfrD[23:20] <- vfrB[43:40]
vfrD[27:24] <- vfrB[51:48]
vfrD[31:28] <- vfrB[59:56]
vfrD[35:32] <- vfrA[3:0]
vfrD[39:36] <- vfrA[11:8]
vfrD[43:40] <- vfrA[19:16]
vfrD[47:44] <- vfrA[27:24]
vfrD[51:48] <- vfrA[35:32]
vfrD[55:52] <- vfrA[43:40]
vfrD[59:56] <- vfrA[51:48]
vfrD[63:60] <- vfrA[59:56]
```

Exceptions:

None

lv.pack.h **Vector Half-word Elements Pack** **lv.pack.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x61
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.pack.h rD,rA,rB
```

Description:

The lower half of the half-word elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the half-word truncated elements of the vector/floating-point register vfrB in such a way that the lowest elements are from vfrB, and the highest elements from vfrA. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrB[15:0]
vfrD[15:8] <- vfrB[31:16]
vfrD[23:16] <- vfrB[47:32]
vfrD[31:24] <- vfrB[63:48]
vfrD[39:32] <- vfrA[15:0]
vfrD[47:40] <- vfrA[31:16]
vfrD[55:48] <- vfrA[47:32]
vfrD[63:56] <- vfrA[63:48]
```

Exceptions:

```
None
```

lv.packs.b Vector Byte Elements Pack Signed Saturated lv.packs.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x62
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.packs.b rD,rA,rB
```

Description:

The lower half of the signed byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the signed byte truncated elements of the vector/floating-point register vfrB in such a way that the lowest elements are from vfrB, and the highest elements from vfrA. If any truncated element exceeds a signed 4-bit value, it is saturated. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[3:0] <- sat4s(vfrB[7:0]
vfrD[7:4] <- sat4s(vfrB[15:8]
vfrD[11:8] <- sat4s(vfrB[23:16]
vfrD[15:12] <- sat4s(vfrB[31:24]
vfrD[19:16] <- sat4s(vfrB[39:32]
vfrD[23:20] <- sat4s(vfrB[47:40]
vfrD[27:24] <- sat4s(vfrB[55:48]
vfrD[31:28] <- sat4s(vfrB[63:56]
vfrD[35:32] <- sat4s(vfrA[7:0]
vfrD[39:36] <- sat4s(vfrA[15:8]
vfrD[43:40] <- sat4s(vfrA[23:16]
vfrD[47:44] <- sat4s(vfrA[31:24]
vfrD[51:48] <- sat4s(vfrA[39:32]
vfrD[55:52] <- sat4s(vfrA[47:40]
vfrD[59:56] <- sat4s(vfrA[55:48]
vfrD[63:60] <- sat4s(vfrA[63:56]
```

Exceptions:

None

lv.packs.h Vector Half-word Elements Pack Signed Saturated lv.packs.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x63
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.packs.h rD,rA,rB
```

Description:

The lower half of the signed halfword elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the signed half-word truncated elements of the vector/floating-point register vfrB in such a way that the lowest elements are from vfrB, and the highest elements from vfrA. If any truncated element exceeds a signed 8-bit value, it is saturated. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- sat8s(vfrB[15:0])
vfrD[15:8] <- sat8s(vfrB[31:16])
vfrD[23:16] <- sat8s(vfrB[47:32])
vfrD[31:24] <- sat8s(vfrB[63:48])
vfrD[39:32] <- sat8s(vfrA[15:0])
vfrD[47:40] <- sat8s(vfrA[31:16])
vfrD[55:48] <- sat8s(vfrA[47:32])
vfrD[63:56] <- sat8s(vfrA[63:48])
```

Exceptions:

```
None
```

lv.packus.b Vector Byte Elements Pack Unsigned Saturated lv.packus.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x64
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.packus.b rD,rA,rB
```

Description:

The lower half of the unsigned byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the unsigned byte truncated elements of the vector/floating-point register vfrB in such a way that the lowest elements are from vfrB, and the highest elements from vfrA. If any truncated element exceeds an unsigned 4-bit value, it is saturated. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[3:0] <- sat4u(vfrB[7:0]
vfrD[7:4] <- sat4u(vfrB[15:8]
vfrD[11:8] <- sat4u(vfrB[23:16]
vfrD[15:12] <- sat4u(vfrB[31:24]
vfrD[19:16] <- sat4u(vfrB[39:32]
vfrD[23:20] <- sat4u(vfrB[47:40]
vfrD[27:24] <- sat4u(vfrB[55:48]
vfrD[31:28] <- sat4u(vfrB[63:56]
vfrD[35:32] <- sat4u(vfrA[7:0]
vfrD[39:36] <- sat4u(vfrA[15:8]
vfrD[43:40] <- sat4u(vfrA[23:16]
vfrD[47:44] <- sat4u(vfrA[31:24]
vfrD[51:48] <- sat4u(vfrA[39:32]
vfrD[55:52] <- sat4u(vfrA[47:40]
vfrD[59:56] <- sat4u(vfrA[55:48]
vfrD[63:60] <- sat4u(vfrA[63:56]
```

Exceptions:

None

lv.packus.h Vector Half-word Elements Pack Unsigned Saturated lv.packus.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x65
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.packus.h rD,rA,rB
```

Description:

The lower half of the unsigned halfword elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the unsigned half-word truncated elements of the vector/floating-point register vfrB in such a way that the lowest elements are from vfrB, and the highest elements from vfrA. If any truncated element exceeds an unsigned 8-bit value, it is saturated. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- sat8u(vfrB[15:0])
vfrD[15:8] <- sat8u(vfrB[31:16])
vfrD[23:16] <- sat8u(vfrB[47:32])
vfrD[31:24] <- sat8u(vfrB[63:48])
vfrD[39:32] <- sat8u(vfrA[15:0])
vfrD[47:40] <- sat8u(vfrA[31:16])
vfrD[55:48] <- sat8u(vfrA[47:32])
vfrD[63:56] <- sat8u(vfrA[63:48])
```

Exceptions:

```
None
```

lv.perm.n **Vector Nibble Elements Permute** **lv.perm.n**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x66
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.perm.n rD,rA,rB
```

Description:

The 4-bit elements of vector/floating-point register vfrA are permuted according to the corresponding 4-bit values in vector/floating-point register vfrB. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[3:0] <- vfrA[vfrB[3:0]*4+3:vfrB[3:0]*4]
vfrD[7:4] <- vfrA[vfrB[7:4]*4+3:vfrB[7:4]*4]
vfrD[11:8] <- vfrA[vfrB[11:8]*4+3:vfrB[11:8]*4]
vfrD[15:12] <- vfrA[vfrB[15:12]*4+3:vfrB[15:12]*4]
vfrD[19:16] <- vfrA[vfrB[19:16]*4+3:vfrB[19:16]*4]
vfrD[23:20] <- vfrA[vfrB[23:20]*4+3:vfrB[23:20]*4]
vfrD[27:24] <- vfrA[vfrB[27:24]*4+3:vfrB[27:24]*4]
vfrD[31:28] <- vfrA[vfrB[31:28]*4+3:vfrB[31:28]*4]
vfrD[35:32] <- vfrA[vfrB[35:32]*4+3:vfrB[35:32]*4]
vfrD[39:36] <- vfrA[vfrB[39:36]*4+3:vfrB[39:36]*4]
vfrD[43:40] <- vfrA[vfrB[43:40]*4+3:vfrB[43:40]*4]
vfrD[47:44] <- vfrA[vfrB[47:44]*4+3:vfrB[47:44]*4]
vfrD[51:48] <- vfrA[vfrB[51:48]*4+3:vfrB[51:48]*4]
vfrD[55:52] <- vfrA[vfrB[55:52]*4+3:vfrB[55:52]*4]
vfrD[59:56] <- vfrA[vfrB[59:56]*4+3:vfrB[59:56]*4]
vfrD[63:60] <- vfrA[vfrB[63:60]*4+3:vfrB[63:60]*4]
```

Exceptions:

None

lv.rl.b Vector Byte Elements Rotate Left lv.rl.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x67
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.rl.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are rotated left by the number of bits specified in the lower 3 bits in each byte element of vector/floating-point register vfrB. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] rl vfrB[2:0]
vfrD[15:8] <- vfrA[15:8] rl vfrB[10:8]
vfrD[23:16] <- vfrA[23:16] rl vfrB[18:16]
vfrD[31:24] <- vfrA[31:24] rl vfrB[26:24]
vfrD[39:32] <- vfrA[39:32] rl vfrB[34:32]
vfrD[47:40] <- vfrA[47:40] rl vfrB[42:40]
vfrD[55:48] <- vfrA[55:48] rl vfrB[50:48]
vfrD[63:56] <- vfrA[63:56] rl vfrB[58:56]
```

Exceptions:

```
None
```

lv.rl.h Vector Half-Word Elements Rotate Left lv.rl.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x68
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.rl.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are rotated left by the number of bits specified in the lower 4 bits in each half-word element of vector/floating-point register vfrB. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] rl vfrB[3:0]
vfrD[31:16] <- vfrA[31:16] rl vfrB[19:16]
vfrD[47:32] <- vfrA[47:32] rl vfrB[35:32]
vfrD[63:48] <- vfrA[63:48] rl vfrB[51:48]
```

Exceptions:

```
None
```

lv.sll Vector Shift Left Logical lv.sll

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sll rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are shifted left by the number of bits specified in the lower 4 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the low-order bits of vfrD. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] << vfrB[2:0]
```

Exceptions:

```
None
```

lv.sll.b Vector Byte Elements Shift Left Logical lv.sll.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x69
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sll.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted left by the number of bits specified in the lower 3 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the low-order bits. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] << vfrB[2:0]
vfrD[15:8] <- vfrA[15:8] << vfrB[10:8]
vfrD[23:16] <- vfrA[23:16] << vfrB[18:16]
vfrD[31:24] <- vfrA[31:24] << vfrB[26:24]
vfrD[39:32] <- vfrA[39:32] << vfrB[34:32]
vfrD[47:40] <- vfrA[47:40] << vfrB[42:40]
vfrD[55:48] <- vfrA[55:48] << vfrB[50:48]
vfrD[63:56] <- vfrA[63:56] << vfrB[58:56]
```

Exceptions:

```
None
```

lv.sll.h Vector Half-Word Elements Shift Left Logical lv.sll.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sll.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted left by the number of bits specified in the lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting zeros into the low-order bits. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] << vfrB[3:0]
vfrD[31:16] <- vfrA[31:16] << vfrB[19:16]
vfrD[47:32] <- vfrA[47:32] << vfrB[35:32]
vfrD[63:48] <- vfrA[63:48] << vfrB[51:48]
```

Exceptions:

```
None
```

lv.sra.b Vector Byte Elements Shift Right Arithmetic lv.sra.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6e
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sra.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted right by the number of bits specified in the lower 3 bits in each byte element of vector/floating-point register vfrB, inserting the most significant bit of each element into the high-order bits. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] sra vfrB[2:0]
vfrD[15:8] <- vfrA[15:8] sra vfrB[10:8]
vfrD[23:16] <- vfrA[23:16] sra vfrB[18:16]
vfrD[31:24] <- vfrA[31:24] sra vfrB[26:24]
vfrD[39:32] <- vfrA[39:32] sra vfrB[34:32]
vfrD[47:40] <- vfrA[47:40] sra vfrB[42:40]
vfrD[55:48] <- vfrA[55:48] sra vfrB[50:48]
vfrD[63:56] <- vfrA[63:56] sra vfrB[58:56]
```

Exceptions:

```
None
```

lv.sra.h Vector Half-Word Elements Shift Right Arithmetic lv.sra.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6f
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sra.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted right by the number of bits specified in the lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting the most significant bit of each element into the high-order bits. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] sra vfrB[3:0]
vfrD[31:16] <- vfrA[31:16] sra vfrB[19:16]
vfrD[47:32] <- vfrA[47:32] sra vfrB[35:32]
vfrD[63:48] <- vfrA[63:48] sra vfrB[51:48]
```

Exceptions:

```
None
```

lv.srl Vector Shift Right Logical lv.srl

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x70
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.srl rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are shifted right by the number of bits specified in the lower 4 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the high-order bits of vfrD. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] » vfrB[2:0]
```

Exceptions:

```
None
```

lv.srl.b Vector Byte Elements Shift Right Logical lv.srl.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6c
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.srl.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted right by the number of bits specified in the lower 3 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the high-order bits. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] » vfrB[2:0]
vfrD[15:8] <- vfrA[15:8] » vfrB[10:8]
vfrD[23:16] <- vfrA[23:16] » vfrB[18:16]
vfrD[31:24] <- vfrA[31:24] » vfrB[26:24]
vfrD[39:32] <- vfrA[39:32] » vfrB[34:32]
vfrD[47:40] <- vfrA[47:40] » vfrB[42:40]
vfrD[55:48] <- vfrA[55:48] » vfrB[50:48]
vfrD[63:56] <- vfrA[63:56] » vfrB[58:56]
```

Exceptions:

```
None
```

lv.srl.h Vector Half-Word Elements Shift Right Logical lv.srl.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6d
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.srl.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted right by the number of bits specified in the lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting zeros into the high-order bits. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] » vfrB[3:0]
vfrD[31:16] <- vfrA[31:16] » vfrB[19:16]
vfrD[47:32] <- vfrA[47:32] » vfrB[35:32]
vfrD[63:48] <- vfrA[63:48] » vfrB[51:48]
```

Exceptions:

```
None
```

lv.sub.b Vector Byte Elements Subtract Signed lv.sub.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x71
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sub.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrB are subtracted from the byte elements of vector/floating-point register vfrA to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] - vfrB[7:0]
vfrD[15:8] <- vfrA[15:8] - vfrB[15:8]
vfrD[23:16] <- vfrA[23:16] - vfrB[23:16]
vfrD[31:24] <- vfrA[31:24] - vfrB[31:24]
vfrD[39:32] <- vfrA[39:32] - vfrB[39:32]
vfrD[47:40] <- vfrA[47:40] - vfrB[47:40]
vfrD[55:48] <- vfrA[55:48] - vfrB[55:48]
vfrD[63:56] <- vfrA[63:56] - vfrB[63:56]
```

Exceptions:

```
None
```

lv.sub.h Vector Half-Word Elements Subtract Signed lv.sub.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x72
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.sub.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrB are subtracted from the half-word elements of vector/floating-point register vfrA to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] - vfrB[15:0]
vfrD[31:16] <- vfrA[31:16] - vfrB[31:16]
vfrD[47:32] <- vfrA[47:32] - vfrB[47:32]
vfrD[63:48] <- vfrA[63:48] - vfrB[63:48]
```

Exceptions:

```
None
```

lv.subs.b Vector Byte Elements Subtract Signed Saturated lv.subs.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x73
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.subs.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrB are subtracted from the byte elements of vector/floating-point register vfrA to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- sat8s(vfrA[7:0] + vfrB[7:0])
vfrD[15:8] <- sat8s(vfrA[15:8] + vfrB[15:8])
vfrD[23:16] <- sat8s(vfrA[23:16] + vfrB[23:16])
vfrD[31:24] <- sat8s(vfrA[31:24] + vfrB[31:24])
vfrD[39:32] <- sat8s(vfrA[39:32] + vfrB[39:32])
vfrD[47:40] <- sat8s(vfrA[47:40] + vfrB[47:40])
vfrD[55:48] <- sat8s(vfrA[55:48] + vfrB[55:48])
vfrD[63:56] <- sat8s(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

lv.subs.h Vector Half-Word Elements Subtract Signed Saturated lv.subs.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x74
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.subs.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrB are subtracted from the half-word elements of vector/floating-point register vfrA to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] - vfrB[15:0])
vfrD[31:16] <- sat16s(vfrA[31:16] - vfrB[31:16])
vfrD[47:32] <- sat16s(vfrA[47:32] - vfrB[47:32])
vfrD[63:48] <- sat16s(vfrA[63:48] - vfrB[63:48])
```

Exceptions:

```
None
```

lv.subu.b Vector Byte Elements Subtract Unsigned lv.subu.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x75
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.subu.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrB are subtracted from the unsigned byte elements of vector/floating-point register vfrA to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- vfrA[7:0] - vfrB[7:0]
vfrD[15:8] <- vfrA[15:8] - vfrB[15:8]
vfrD[23:16] <- vfrA[23:16] - vfrB[23:16]
vfrD[31:24] <- vfrA[31:24] - vfrB[31:24]
vfrD[39:32] <- vfrA[39:32] - vfrB[39:32]
vfrD[47:40] <- vfrA[47:40] - vfrB[47:40]
vfrD[55:48] <- vfrA[55:48] - vfrB[55:48]
vfrD[63:56] <- vfrA[63:56] - vfrB[63:56]
```

Exceptions:

```
None
```

lv.subu.h Vector Half-Word Elements Subtract Unsigned lv.subu.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x76
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.subu.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrB are subtracted from the unsigned half-word elements of vector/floating-point register vfrA to form the result elements. The result elements are placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- vfrA[15:0] - vfrB[15:0]
vfrD[31:16] <- vfrA[31:16] - vfrB[31:16]
vfrD[47:32] <- vfrA[47:32] - vfrB[47:32]
vfrD[63:48] <- vfrA[63:48] - vfrB[63:48]
```

Exceptions:

```
None
```

lv.subus.b Vector Byte Elements Subtract Unsigned Saturated lv.subus.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x77
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.subus.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrB are subtracted from the unsigned byte elements of vector/floating-point register vfrA to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- sat8u(vfrA[7:0] + vfrB[7:0])
vfrD[15:8] <- sat8u(vfrA[15:8] + vfrB[15:8])
vfrD[23:16] <- sat8u(vfrA[23:16] + vfrB[23:16])
vfrD[31:24] <- sat8u(vfrA[31:24] + vfrB[31:24])
vfrD[39:32] <- sat8u(vfrA[39:32] + vfrB[39:32])
vfrD[47:40] <- sat8u(vfrA[47:40] + vfrB[47:40])
vfrD[55:48] <- sat8u(vfrA[55:48] + vfrB[55:48])
vfrD[63:56] <- sat8u(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

lv.subus.h Vector Half-Word Elements Subtract Unsigned Saturated lv.subus.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x78
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.subus.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrB are subtracted from the unsigned half-word elements of vector/floating-point register vfrA to form the result elements. If the result exceeds the min/max value for the destination data type, it is saturated to the min/max value and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- sat16u(vfrA[15:0] - vfrB[15:0])
vfrD[31:16] <- sat16u(vfrA[31:16] - vfrB[31:16])
vfrD[47:32] <- sat16u(vfrA[47:32] - vfrB[47:32])
vfrD[63:48] <- sat16u(vfrA[63:48] - vfrB[63:48])
```

Exceptions:

```
None
```

lv.unpack.b **Vector Byte Elements Unpack** **lv.unpack.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x79
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.unpack.b rD,rA,rB
```

Description:

The lower half of the 4-bit elements in vector/floating-point register vfrA are sign-extended and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[7:0] <- exts(vfrA[3:0])
vfrD[15:8] <- exts(vfrA[7:4])
vfrD[23:16] <- exts(vfrA[11:8])
vfrD[31:24] <- exts(vfrA[15:12])
vfrD[39:32] <- exts(vfrA[19:16])
vfrD[47:40] <- exts(vfrA[23:20])
vfrD[55:48] <- exts(vfrA[27:24])
vfrD[63:56] <- exts(vfrA[31:28])
```

Exceptions:

```
None
```

lv.unpack.h Vector Half-Word Elements Unpack lv.unpack.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x7a
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.unpack.h rD,rA,rB
```

Description:

The lower half of the 8-bit elements in vector/floating-point register vfrA are sign-extended and placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[15:0] <- exts(vfrA[7:0])
vfrD[31:16] <- exts(vfrA[15:8])
vfrD[47:32] <- exts(vfrA[23:16])
vfrD[63:48] <- exts(vfrA[31:24])
```

Exceptions:

```
None
```

lv.xor **Vector Exclusive Or** **lv.xor**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x7b
6 bits	5 bits	5 bits	5 bits	3 bits	8bits

Format:

```
lv.xor rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical XOR operation. The result is placed into vector/floating-point register vfrD.

32-bit Implementation:

```
N/A
```

64-bit Implementation:

```
vfrD[63:0] <- vfrA[63:0] XOR vfrB[63:0]
```

Exceptions:

```
None
```