0.1. ORBIS32/64

l.add **Add Signed** **l.add**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x0
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.add rD,rA,rB
```

Description:

The contents of general-purpose register rA is added to the contents of general-purpose register rB to form the result. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] + rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] + rB[63:0]
```

Exceptions:

```
Integer Overflow
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.addc **Add Signed and Carry** **l.addc**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x1
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.addc rD,rA,rB
```

Description:

The contents of general-purpose register rA is added to the contents of general-purpose register rB and carry SR[CY] to form the result. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] + rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] + rB[63:0]
```

Exceptions:

```
Integer Overflow
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.addi **Add Immediate Signed** **l.addi**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x25	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.addi rD,rA,I
```

Description:

Immediate is signed-extended and added to the contents of general-purposeregister rA to form the result. The result is placed into general-purposeregister rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] + exts(Immediate)
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] + exts(Immediate)
```

Exceptions:

```
Integer Overflow
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.addic **Add Immediate Signed and Carry** **l.addic**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x26	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.addic rD,rA,I
```

Description:

Immediate is signed-extended and added to the contents of general-purposeregister rA and carry SR[CY] to form the result. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] + exts(Immediate) + SR[CY]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] + exts(Immediate) + SR[CY]
```

Exceptions:

```
Integer Overflow
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.and **And** **l.and**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x3
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.and rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical AND operation. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] AND rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] AND rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.andi And with Immediate Half Word l.andi

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x28	D	A	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.andi rD,rA,K
```

Description:

Immediate is zero-extended and combined with the contents of general-purpose register rB in a bit-wise logical AND operation. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rB[31:0] AND extz(Immediate)
```

64-bit Operation:

```
rD[63:0] <- rB[63:0] AND extz(Immediate)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.bf **Branch if Flag** **l.bf**

31 26	25 0
opcode 0x4	N
6 bits	26 bits

Format:

```
l.bf N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the branch. If the compare flag is set, then the program branches to EA with a delay of one instruction.

32-bit Operation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag set
```

64-bit Operation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag set
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.bnf **Branch if No Flag** **l.bnf**

31 26	25 0
opcode 0x3	N
6 bits	26 bits

Format:

```
l.bnf N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the branch. If the compare flag is cleared, then the program branches to EA with a delay of one instruction.

32-bit Operation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag cleared
```

64-bit Operation:

```
EA <- (Immediate || 00) + DelayInsnAddr
   PC <- EA if flag cleared
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.div **Divide Signed** **l.div**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x9
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.div rD,rA,rB
```

Description:

The contents of general-purpose register rA are divided by the contents of general-purpose register rB and the result is placed into general-purpose register rD. Both operands are treated as signed integers. A divide by zero flag is set when the divisor is zero.

32-bit Operation:

```
rD[31:0] <- rA[31:0] / rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] / rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.divu **Divide Unsigned** **l.divu**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xa
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.divu rD,rA,rB
```

Description:

The contents of general-purpose register rA are divided by the contents of general-purpose register rA and the result is placed into general-purpose register rD. Both operands are treated as unsigned integers. A divide by zero flag is set when the divisor is zero.

32-bit Operation:

```
rD[31:0] <- rA[31:0] / rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] / rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.extbs **Extend Byte with Sign** **l.extbs**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x1	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extbs rD,rA,rB
```

Description:

Bit 7 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order eight bits of general-purpose register rA are copied from low-order eight bits of general-purpose register rD.

32-bit Operation:

```
rD[31:8] <- rA[7]
   rD[7:0] <- rA[7:0]
```

64-bit Operation:

```
rD[63:8] <- rA[7]
   rD[7:0] <- rA[7:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.extbz **Extend Byte with Zero** **l.extbz**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extbz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order eight bits of general-purpose register rA are copied into low-order eight bits of general-purpose register rD.

32-bit Operation:

```
rD[31:8] <- 0
   rD[7:0] <- rA[7:0]
```

64-bit Operation:

```
rD[63:8] <- 0
   rD[7:0] <- rA[7:0]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.exths **Extend Half Word with Sign** **l.exths**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.exths rD,rA,rB
```

Description:

Bit 15 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order 16 bits of general-purpose register rA are copied into low-order 16 bits of general-purpose register rD.

32-bit Operation:

```
rD[31:16] <- rA[15]
   rD[15:0] <- rA[15:0]
```

64-bit Operation:

```
rD[63:16] <- rA[15]
   rD[15:0] <- rA[15:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.exthz **Extend Half Word with Zero** **l.exthz**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x2	reserved	opcode 0xc
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.exthz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order 16 bits of general-purpose register rA are copied into low-order 16 bits of general-purpose register rD.

32-bit Operation:

```
rD[31:16] <- 0
   rD[15:0] <- rA[15:0]
```

64-bit Operation:

```
rD[63:16] <- 0
   rD[15:0] <- rA[15:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.extws **Extend Word with Sign** **l.extws**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0xd
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extws rD,rA,rB
```

Description:

Bit 31 of general-purpose register rA is placed in high-order bits of general-purpose register rD. The low-order 32 bits of general-purpose register rA are copied from low-order 32 bits of general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0]
```

64-bit Operation:

```
rD[63:32] <- rA[31]
   rD[31:0] <- rA[31:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS64 II	Optional

l.extwz **Extend Word with Zero** **l.extwz**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x2	reserved	opcode 0xd
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.extwz rD,rA,rB
```

Description:

Zero is placed in high-order bits of general-purpose register rD. The low-order 32 bits of general-purpose register rA are copied into low-order 32 bits of general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0]
```

64-bit Operation:

```
rD[63:32] <- 0
   rD[31:0] <- rA[31:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS64 II	Optional

l.j **Jump** **l.j**

31 26	25 0
opcode 0x0	N
6 bits	26 bits

Format:

```
l.j N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction.

32-bit Operation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

64-bit Operation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.jal **Jump and Link** **l.jal**

31 26	25 0
opcode 0x1	N
6 bits	26 bits

Format:

```
l.jal N
```

Description:

The immediate is shifted left two bits, sign-extended to program counter width and then added to the address of the delay slot. The result is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction. The address of the instruction after the delay slot is placed in the link register.

32-bit Operation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

64-bit Operation:

```
PC <- (Immediate || 00) + DelayInsnAddr
   LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.jalr **Jump and Link Register** **l.jalr**

31 26	25 16	15 . . . 11	10 0
opcode 0x12	reserved	B	reserved
6 bits	10 bits	5 bits	11 bits

Format:

```
l.jalr rB
```

Description:

The contents of general-purpose register rB is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction. The address of the instruction after the delay slot is placed in the link register.

32-bit Operation:

```
PC <- rB
   LR <- DelayInsnAddr + 4
```

64-bit Operation:

```
PC <- rB
   LR <- DelayInsnAddr + 4
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.jr **Jump Register** **l.jr**

31 26	25 16	15 . . . 11	10 0
opcode 0x11	reserved	B	reserved
6 bits	10 bits	5 bits	11 bits

Format:

```
l.jr rB
```

Description:

The contents of general-purpose register rB is effective address of the jump. The program unconditionally jumps to EA with a delay of one instruction.

32-bit Operation:

```
PC <- rB
```

64-bit Operation:

```
PC <- rB
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.lbs **Load Byte and Extend with Sign** **l.lbs**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x22	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lbs rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The byte in memory addressed by EA is loaded into the low-order eight bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 7 of the loaded value.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[7:0] <- (EA)[7:0]
   rD[31:8] <- rA[8]
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[7:0] <- (EA)[7:0]
   rD[63:8] <- rA[8]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.lbz **Load Byte and Extend with Zero** **l.lbz**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x21	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lbz rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The byte in memory addressed by EA is loaded into the low-order eight bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[7:0] <- (EA)[7:0]
   rD[31:8] <- 0
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[7:0] <- (EA)[7:0]
   rD[63:8] <- 0
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.lhs **Load Half Word and Extend with Sign** **l.lhs**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x24	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lhs rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The half word in memory addressed by EA is loaded into the low-order 16 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with bit 15 of the loaded value.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[15:0] <- (EA)[15:0]
   rD[31:16] <- rA[15]
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[15:0] <- (EA)[15:0]
   rD[63:16] <- rA[15]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.lhz **Load Half Word and Extend with Zero** **l.lhz**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x23	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.lhz rD,I(rA)
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The half word in memory addressed by EA is loaded into the low-order 16 bits of general-purpose register rD. High-order bits of general-purpose register rD are replaced with zero.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   rD[15:0] <- (EA)[15:0]
   rD[31:16] <- 0
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   rD[15:0] <- (EA)[15:0]
   rD[63:16] <- 0
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.mac Multiply Signed and Accumulate l.mac

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x7
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.mac rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied and the result is truncated to 32 bits and added to the special-purpose registers MACHI and MACLO. All operands are treated as signed integers.

32-bit Operation:

```
M[31:0] <- rA[31:0] * rB[31:0]
   MACHI[31:0]MACLO[31:0] <- M[31:0] + MACHI[31:0]MACLO[31:0]
```

64-bit Operation:

```
M[31:0] <- rA[63:0] * rB[63:0]
   MACHI[31:0]MACLO[31:0] <- M[31:0] + MACHI[31:0]MACLO[31:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.mfsr	**Move From Special-Purpose Register**	**l.mfsr**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x7	D	A	reserved
6 bits	5 bits	5 bits	16 bits

Format:

```
l.mfsr rD,rA
```

Description:

The contents of special register identified by the sum of general-purpose rA and zero-extended immediate are moved into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- spr(rA+extz(Immediate))
```

64-bit Operation:

```
rD[63:0] <- spr(rA+extz(Immediate))
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.movhi **Move Immediate High** **l.movhi**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x6	D	reserved	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.movhi rD,K
```

Description:

16-bit immediate is zero-extended, shifted left by 16 bits and placed into general-purpose register rD.

32-bit Operation:

```
rA[31:0] <- extz(Immediate) « 16
```

64-bit Operation:

```
rA[63:0] <- extz(Immediate) « 16
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.mtsr **Move To Special-Purpose Register** **l.mtsr**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x10	reserved	A	B	reserved
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.mtsr rA,rB
```

Description:

The contents of general-purpose register rB are moved into special register identified by the sum of general-purpose register rA and zero-extended immediate.

32-bit Operation:

```
spr(rA+extz(Immediate)) <- rA[31:0]
```

64-bit Operation:

```
spr(rA+extz(Immediate)) <- rA[31:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.mul **Multiply Signed** **l.mul**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0x6
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.mul rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied and the result is truncated to destination register width and placed into general-purpose register rD. Both operands are treated as unsigned integers.

32-bit Operation:

```
rD[31:0] <- rA[31:0] * rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] * rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.muli **Multiply Immediate Signed** **l.muli**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2b	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.muli rD,rA,I
```

Description:

Immediate and the contents of general-purpose register rA are multiplied and the result is truncated to destination register width and placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] * Immediate
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] * Immediate
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.mulu **Multiply Unsigned** **l.mulu**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x3	reserved	opcode 0xb
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.mulu rD,rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are multiplied and the result is truncated to destination register width and placed into general-purpose register rD. Both operands are treated as unsigned integers.

32-bit Operation:

```
rD[31:0] <- rA[31:0] * rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] * rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.nop **No Operation** **l.nop**

31 24	23 0
opcode 0x15	reserved
8 bits	24 bits

Format:

```
l.nop
```

Description:

This instruction does not do anything except it takes at least one clock cycle to complete. It is often used to fill delay slot gaps.

32-bit Operation:

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.or **Or** **l.or**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x4
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.or rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical OR operation. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] OR rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] OR rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.ori **Or with Immediate Half Word** **l.ori**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x29	D	A	K
6 bits	5 bits	5 bits	16 bits

Format:

```
l.ori rD,rA,K
```

Description:

Immediate is zero-extended and combined with the contents of general-purpose register rB in a bit-wise logical OR operation. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rB[31:0] OR extz(Immediate)
```

64-bit Operation:

```
rD[63:0] <- rB[63:0] OR extz(Immediate)
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.rfe **Return From Exception** **l.rfe**

31 26	25 0
opcode 0x9	reserved
6 bits	26 bits

Format:

```
l.rfe
```

Description:

Execution of this instruction restores the state of the processor prior to the exception.

32-bit Operation:

```
state_restore()
```

64-bit Operation:

```
state_restore()
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.ror **Rotate Right** **l.ror**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x38
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.ror rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are rotated right. Result is written into general-purpose register rD.

32-bit Operation:

```
rD[31-rB:0] <- rA[31:rB]
   rD[31:32-rB] <- rA[rB-1:0]
```

64-bit Operation:

```
rD[63-rB:0] <- rA[63:rB]
   rD[63:64-rB] <- rA[rB-1:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.rori **Rotate Right with Immediate** **l.rori**

31 26	25 . . . 21	20 . . . 16	15 8	7 . 5	4 . . . 0
opcode 0x2d	D	A	reserved	opcode 0x4	L
6 bits	5 bits	5 bits	8 bits	3 bits	5 bits

Format:

```
l.rori rD,rA,L
```

Description:

6-bit immediate specifies the number of bit positions the contents of general-purpose register rA are rotated right. Result is written into general-purpose register rD.

32-bit Operation:

```
rD[31-L:0] <- rA[31:L]
   rD[31:32-L] <- rA[L-1:0]
```

64-bit Operation:

```
rD[63-L:0] <- rA[63:L]
   rD[63:64-L] <- rA[L-1:0]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sb **Store Byte** **l.sb**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x36	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sb I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The low-order 8 bits of general-purpose register rB are stored to memory addressed by EA.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   (EA)[7:0] <- rB[7:0]
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[7:0] <- rB[7:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfeq **Set Flag if Equal** **l.sfeq**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x720	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfeq rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] == rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] == rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfeqi	Set Flag if Equal Immediate	l.sfeqi

31 21	20 . . . 16	15 0
opcode 0x5c0	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfeqi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] == rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] == rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfges Set Flag if Greater or Equal Than Signed l.sfges

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72b	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfges rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfgesi **Set Flag if Greater or Equal Than Immediate Signed** **l.sfgesi**

31 21	20 . . . 16	15 0
opcode 0x5cb	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgesi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfgeu **Set Flag if Greater or Equal Than Unsigned** **l.sfgeu**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x723	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfgeu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfgeui **Set Flag if Greater or Equal Than Immediate Unsigned** **l.sfgeui**

31 21	20 . . . 16	15 0
opcode 0x5c3	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgeui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are greater or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] >= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] >= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfgts **Set Flag if Greater Than Signed** **l.sfgts**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72a	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfgts rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfgtsi **Set Flag if Greater Than Immediate Signed** **l.sfgtsi**

31 21	20 . . . 16	15 0
opcode 0x5ca	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgtsi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfgtu **Set Flag if Greater Than Unsigned** **l.sfgtu**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x722	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfgtu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfgtui **Set Flag if Greater Than Immediate Unsigned** **l.sfgtui**

31 21	20 . . . 16	15 0
opcode 0x5c2	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfgtui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are greater than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] > rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] > rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfles **Set Flag if Less or Equal Than Signed** **l.sfles**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72d	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfles rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sflesi **Set Flag if Less or Equal Than Immediate Signed** **l.sflesi**

31 21	20 . . . 16	15 0
opcode 0x5cd	A	I
11 bits	5 bits	16 bits

Format:

```
l.sflesi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfleu Set Flag if Less or Equal Than Unsigned l.sfleu

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x725	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfleu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfleui **Set Flag if Less or Equal Than Immediate Unsigned** **l.sfleui**

31 21	20 . . . 16	15 0
opcode 0x5c5	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfleui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are less or equal than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] <= rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] <= rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sflts **Set Flag if Less Than Signed** **l.sflts**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x72c	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sflts rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as signed integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfltsi **Set Flag if Less Than Immediate Signed** **l.sfltsi**

31 21	20 . . . 16	15 0
opcode 0x5cc	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfltsi rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared as signed integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfltu **Set Flag if Less Than Unsigned** **l.sfltu**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x724	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfltu rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared as unsigned integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfltui **Set Flag if Less Than Immediate Unsigned** **l.sfltui**

31 21	20 . . . 16	15 0
opcode 0x5c4	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfltui rA,I
```

Description:

The contents of general-purpose register rA and zero-extended immediate are compared as unsigned integers. If the contents of the first register are less than the contents of the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] < rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] < rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sfne **Set Flag if Not Equal** **l.sfne**

31 21	20 . . . 16	15 . . . 11	10 0
opcode 0x721	A	B	reserved
11 bits	5 bits	5 bits	11 bits

Format:

```
l.sfne rA,rB
```

Description:

The contents of general-purpose register rA and the contents of general-purpose register rB are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] != rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] != rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sfnei **Set Flag if Not Equal Immediate** **l.sfnei**

31 21	20 . . . 16	15 0
opcode 0x5c1	A	I
11 bits	5 bits	16 bits

Format:

```
l.sfnei rA,I
```

Description:

The contents of general-purpose register rA and sign-extended immediate are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- rA[31:0] != rB[31:0]
```

64-bit Operation:

```
flag <- rA[63:0] != rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 II	Optional

l.sh **Store Half Word** l.sh

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x37	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sh I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The low-order 16 bits of general-purpose register rB are stored to memory addressed by EA.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   (EA)[15:0] <- rB[15:0]
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[15:0] <- rB[15:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sll **Shift Left Logical** **l.sll**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x8
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.sll rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are shifted left, inserting zeros into the low-order bits. Result is written into general-purpose rD.

32-bit Operation:

```
rD[31:rB] <- rA[31-rB:0]
   rD[rB-1:0] <- 0
```

64-bit Operation:

```
rD[63:rB] <- rA[63-rB:0]
   rD[rB-1:0] <- 0
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.slli **Shift Left Logical with Immediate** **l.slli**

31 26	25 . . . 21	20 . . . 16	15 8	7 . 5	4 . . . 0
opcode 0x2d	D	A	reserved	opcode 0x0	L
6 bits	5 bits	5 bits	8 bits	3 bits	5 bits

Format:

```
l.slli rD,rA,L
```

Description:

6-bit immediate specifies the number of bit positions the contents of general-purpose register rA are shifted left, inserting zeros into the low-order bits. Result is written into general-purpose rD.

32-bit Operation:

```
rD[31:L] <- rA[31-L:0]
   rD[L-1:0] <- 0
```

64-bit Operation:

```
rD[63:L] <- rA[63-L:0]
   rD[L-1:0] <- 0
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sra **Shift Right Arithmetic** **l.sra**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x28
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.sra rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are shifted right, sign-extending the high-order bits. Result is written into general-purpose register rD.

32-bit Operation:

```
rD[31-rB:0] <- rA[31:rB]
   rD[31:32-rB] <- rB[31]
```

64-bit Operation:

```
rD[63-rB:0] <- rA[63:rB]
   rD[63:64-rB] <- rB[63]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.srai Shift Right Arithmetic with Immediate l.srai

31 26	25 . . . 21	20 . . . 16	15 8	7 . 5	4 . . . 0
opcode 0x2d	D	A	reserved	opcode 0x2	L
6 bits	5 bits	5 bits	8 bits	3 bits	5 bits

Format:

```
l.srai rD,rA,L
```

Description:

6-bit immediate specifies the number of bit positions the contents of general-purpose register rA are shifted right, sign-extending the high-order bits. Result is written into general-purpose register rD.

32-bit Operation:

```
rD[31-L:0] <- rA[31:L]
   rD[31:32-L] <- rA[31]
```

64-bit Operation:

```
rD[63-L:0] <- rA[63:L]
   rD[63:64-L] <- rA[63]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.srl **Shift Right Logical** **l.srl**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0x38	D	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
l.srl rD,rA,rB
```

Description:

General-purpose register rB specifies the number of bit positions the contents of general-purpose register rA are shifted right, inserting zeros into the high-order bits. Result is written into general-purpose register rD.

32-bit Operation:

```
rD[31-rB:0] <- rA[31:rB]
   rD[31:32-rB] <- 0
```

64-bit Operation:

```
rD[63-rB:0] <- rA[63:rB]
   rD[63:64-rB] <- 0
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.srli **Shift Right Logical with Immediate** **l.srli**

31 26	25 . . . 21	20 . . . 16	15 8	7 . 5	4 . . . 0
opcode 0x2d	D	A	reserved	opcode 0x1	L
6 bits	5 bits	5 bits	8 bits	3 bits	5 bits

Format:

```
l.srli rD,rA,L
```

Description:

6-bit Immediate specifies the number of bit positions the contents of general-purpose register rA are shifted right, inserting zeros into the high-order bits. Result is written into general-purpose register rD.

32-bit Operation:

```
rD[31-L:0] <- rA[31:L]
   rD[31:32-L] <- 0
```

64-bit Operation:

```
rD[63-L:0] <- rA[63:L]
   rD[63:64-L] <- 0
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sub **Subtract Signed** **l.sub**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x2
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.sub rD,rA,rB
```

Description:

The contents of general-purpose register rB is subtracted from the contents of general-purpose register rA to form the result. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] - rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] - rB[63:0]
```

Exceptions:

```
Integer Overflow
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.subi **Subtract Immediate Signed** **l.subi**

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x27	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.subi rD,rA,I
```

Description:

Immediate is signed-extended and subtracted from the contents of general-purposeregister rA to form the result. The result is placed into general-purposeregister rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] - exts(Immediate)
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] - exts(Immediate)
```

Exceptions:

```
Integer Overflow
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sw **Store Single Word** **l.sw**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 0
opcode 0x35	I	A	B	I
6 bits	5 bits	5 bits	5 bits	11 bits

Format:

```
l.sw I(rA),rB
```

Description:

Offset is sign-extended and added to the contents of general-purpose register rA. Sum represents effective address. The low-order 32 bits of general-purpose register rB are stored to memory addressed by EA.

32-bit Operation:

```
EA <- exts(Immediate) + rA[31:0]
   (EA)[31:0] <- rB[31:0]
```

64-bit Operation:

```
EA <- exts(Immediate) + rA[63:0]
   (EA)[31:0] <- rB[31:0]
```

Exceptions:

```
TLB miss
   Page fault
   Bus error
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.sys **System Call** **l.sys**

31 12	11 0
opcode 0x20000	K
20 bits	12 bits

Format:

```
l.sys K
```

Description:

Execution of system call instruction results in the system call exception. System calls exception is a request to the operating system to provide certain services. Immediate specifies which system service is required.

32-bit Operation:

```
system-call-exception(K)
```

64-bit Operation:

```
system-call-exception(K)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.xor **Exclusive Or** **l.xor**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 6	5 4	3 . . 0
opcode 0x38	D	A	B	reserved	opcode 0x0	reserved	opcode 0x5
6 bits	5 bits	5 bits	5 bits	3 bits	2 bits	2 bits	4 bits

Format:

```
l.xor rD,rA,rB
```

Description:

The contents of general-purpose register rA are combined with the contents of general-purpose register rB in a bit-wise logical XOR operation. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rA[31:0] XOR rB[31:0]
```

64-bit Operation:

```
rD[63:0] <- rA[63:0] XOR rB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

l.xori Exclusive Or with Immediate Half Word l.xori

31 26	25 . . . 21	20 . . . 16	15 0
opcode 0x2a	D	A	I
6 bits	5 bits	5 bits	16 bits

Format:

```
l.xori rD,rA,I
```

Description:

Immediate is zero-extended and combined with the contents of general-purpose register rB in a bit-wise logical XOR operation. The result is placed into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- rB[31:0] XOR exts(Immediate)
```

64-bit Operation:

```
rD[63:0] <- rB[63:0] XOR exts(Immediate)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORBIS32 I	Required

lf.add.d **Add Floating-Point Double-Precision** **lf.add.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.add.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is added to the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] + vfrB[63:0]
```

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.add.s **Add Floating-Point Single-Precision** **lf.add.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.add.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is added to the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

```
vfrD[31:0] <- vfrA[31:0] + vfrB[31:0]
```

64-bit Operation:

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.div.d **Divide Floating-Point Double-Precision** **lf.div.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.div.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] / vfrB[63:0]
```

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX64 II	Optional

lf.div.s **Divide Floating-Point Single-Precision** **lf.div.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.div.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

```
vfrD[31:0] <- vfrA[31:0] / vfrB[31:0]
```

64-bit Operation:

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX32 II	Optional

lf.ftoi.d Floating-Point Double-Precision To Integer lf.ftoi.d

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.ftoi.d rD,rA
```

Description:

The contents of vector/floating-point register vfrA are converted to integer and stored into general-purpose register rD.

32-bit Operation:

64-bit Operation:

```
rD[63:0] <- ftoi(vfrA[63:0])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.ftoi.s **Floating-Point Single-Precision To Integer** **lf.ftoi.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.ftoi.s rD,rA
```

Description:

The contents of vector/floating-point register vfrA are converted to integer and stored into general-purpose register rD.

32-bit Operation:

```
rD[31:0] <- ftoi(vfrA[31:0])
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.itof.d **Integer To Floating-Point Double-Precision** **lf.itof.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 4	3 . . 0
opcode 0x14	D	reserved	B	reserved	opcode 0x5
6 bits	5 bits	5 bits	5 bits	7 bits	4 bits

Format:

```
lf.itof.d rD,rA
```

Description:

The contents of general-purpose register rA are converted to Double-precision floating-point number and stored into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- itof(rA[63:0])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.itof.s **Integer To Floating-Point Single-Precision** **lf.itof.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 4	3 . . 0
opcode 0x14	D	reserved	B	reserved	opcode 0x4
6 bits	5 bits	5 bits	5 bits	7 bits	4 bits

Format:

```
lf.itof.s rD,rA
```

Description:

The contents of general-purpose register rA are converted to single-precision floating-point number and stored into vector/floating-point register vfrD.

32-bit Operation:

```
vfrD[31:0] <- itof(rA[31:0])
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.madd.d **Multiply and Add Floating-Point Double-Precision** **lf.madd.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.madd.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB and added to special-purpose register FPMADDLO/FPMADDHI.

32-bit Operation:

64-bit Operation:

```
FPMADDHI[31:0]FPMADDLO[31:0] <- vfrA[63:0] * vfrB[63:0] +
FPMADDHI[31:0]FPMADDLO[31:0]
```

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX64 II	Optional

lf.madd.s **Multiply and Add Floating-Point Single-Precision** **lf.madd.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.madd.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB and added to special-purpose register FPMADDLO/FPMADDHI.

32-bit Operation:

```
FPMADDHI[31:0]FPMADDLO[31:0] <- vfrA[31:0] * vfrB[31:0] +
FPMADDHI[31:0]FPMADDLO[31:0]
```

64-bit Operation:

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX32 II	Optional

lf.mul.d **Multiply Floating-Point Double-Precision** **lf.mul.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.mul.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] * vfrB[63:0]
```

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.mul.s **Multiply Floating-Point Single-Precision** **lf.mul.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.mul.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is multiplied by the contents of vector/floating-point register vfrB to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

```
vfrD[31:0] <- vfrA[31:0] * vfrB[31:0]
```

64-bit Operation:

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.rem.d **Remainder Floating-Point Double-Precision** **lf.rem.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.rem.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB and remainder is used as the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] % vfrB[63:0]
```

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX64 II	Optional

lf.rem.s **Remainder Floating-Point Single-Precision** **lf.rem.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.rem.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA is divided by the contents of vector/floating-point register vfrB and remainder is used as the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

```
vfrD[31:0] <- vfrA[31:0] % vfrB[31:0]
```

64-bit Operation:

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX32 II	Optional

lf.sfeq.d **Set Flag if Equal Floating-Point Double-Precision** **lf.sfeq.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfeq.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[63:0] == vfrB[63:0]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sfeq.s **Set Flag if Equal Floating-Point Single-Precision** **lf.sfeq.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfeq.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- vfrA[31:0] == vfrB[31:0]
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.sfge.d **Set Flag if Greater or Equal Than Floating-Point Double-Precision** **lf.sfge.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfge.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[63:0] >= vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sfge.s **Set Flag if Greater or Equal Than Floating-Point Single-Precision** **lf.sfge.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfge.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- vfrA[31:0] >= vfrB[31:0]
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.sfgt.d **Set Flag if Greater Than Floating-Point Double-Precision** **lf.sfgt.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfgt.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[63:0] > vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sfgt.s **Set Flag if Greater Than Floating-Point Single-Precision** **lf.sfgt.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfgt.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is greater than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- vfrA[31:0] > vfrB[31:0]
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.sfle.d **Set Flag if Less or Equal Than Floating-Point Double-Precision** **lf.sfle.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfle.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[363:0] <= vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sfle.s **Set Flag if Less or Equal Than Floating-Point Single-Precision** **lf.sfle.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfle.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less or equal than the second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- vfrA[31:0] <= vfrB[31:0]
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.sflt.d **Set Flag if Less Than Floating-Point Double-Precision** **lf.sflt.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x1c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sflt.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[63:0] < vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sflt.s **Set Flag if Less Than Floating-Point Single-Precision** **lf.sflt.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x1c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sflt.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If first register is less than second register, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- vfrA[31:0] < vfrB[31:0]
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.sfne.d **Set Flag if Not Equal Floating-Point Double-Precision** **lf.sfne.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	reserved	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfne.d rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[63:0] != vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sfne.s **Set Flag if Not Equal Floating-Point Single-Precision** **lf.sfne.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	reserved	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sfne.s rA,rB
```

Description:

The contents of vector/floating-point register vfrA and the contents of vector/floating-point register vfrB are compared. If the two registers are not equal, then the compare flag is set; otherwise the compare flag is cleared.

32-bit Operation:

```
flag <- vfrA[31:0] != vfrB[31:0]
```

64-bit Operation:

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lf.sub.d **Subtract Floating-Point Double-Precision** **lf.sub.d**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xc	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sub.d rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrB is subtracted from the contents of vector/floating-point register vfrA to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] - vfrB[63:0]
```

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX64 I	Required

lf.sub.s **Subtract Floating-Point Single-Precision** **lf.sub.s**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xb	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lf.sub.s rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrB is subtracted from the contents of vector/floating-point register vfrA to form the result. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

```
vfrD[31:0] <- vfrA[31:0] - vfrB[31:0]
```

64-bit Operation:

Exceptions:

Notes:

Instruction Subset	Implementation
ORFPX32 I	Required

lv.add.b **Vector Byte Elements Add Signed** **lv.add.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x30
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.add.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] + vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] + vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] + vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] + vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] + vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] + vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] + vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] + vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.add.h — Vector Half-Word Elements Add Signed — lv.add.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x31
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.add.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] + vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] + vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] + vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] + vfrB[63:48]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.adds.b **Vector Byte Elements Add Signed Saturated** **lv.adds.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x32
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.adds.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- sat8s(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8s(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8s(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8s(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8s(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8s(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8s(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8s(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.adds.h **Vector Half-Word Elements Add Signed Saturated** **lv.adds.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x33
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.adds.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] + vfrB[15:0])
   vfrD[31:16] <- sat16s(vfrA[31:16] + vfrB[31:16])
   vfrD[47:32] <- sat16s(vfrA[47:32] + vfrB[47:32])
   vfrD[63:48] <- sat16s(vfrA[63:48] + vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.addu.b **Vector Byte Elements Add Unsigned** **lv.addu.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x34
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addu.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrA are added to the unsigned byte elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] + vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] + vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] + vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] + vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] + vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] + vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] + vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] + vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.addu.h — Vector Half-Word Elements Add Unsigned — lv.addu.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x35
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addu.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrA are added to the unsigned half-word elements of vector/floating-point register vfrB to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] + vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] + vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] + vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] + vfrB[63:48]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.addus.b **Vector Byte Elements Add Unsigned Saturated** **lv.addus.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x36
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addus.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrA are added to the unsigned byte elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- sat8u(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8u(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8u(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8u(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8u(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8u(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8u(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8u(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.addus.h **Vector Half-Word Elements Add Unsigned Saturated** **lv.addus.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x37
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.addus.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrA are added to the unsigned half-word elements of vector/floating-point register vfrB to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] + vfrB[15:0])
   vfrD[31:16] <- sat16s(vfrA[31:16] + vfrB[31:16])
   vfrD[47:32] <- sat16s(vfrA[47:32] + vfrB[47:32])
   vfrD[63:48] <- sat16s(vfrA[63:48] + vfrB[63:48])
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_eq.b **Vector Byte Elements All Equal** **lv.all_eq.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x10
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] == vfrB[7:0]
   vfrA[15:8] == vfrB[15:8]
   vfrA[23:16] == vfrB[23:16]
   vfrA[31:24] == vfrB[31:24]
   vfrA[39:32] == vfrB[39:32]
   vfrA[47:40] == vfrB[47:40]
   vfrA[55:48] == vfrB[55:48]
   vfrA[63:56] == vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_eq.h **Vector Half-Word Elements All Equal** **lv.all_eq.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x11
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] == vfrB[15:0]
   vfrA[31:16] == vfrB[31:16]
   vfrA[47:32] == vfrB[47:32]
   vfrA[63:48] == vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_ge.b **Vector Byte Elements All Greater or Equal Than** **lv.all_ge.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x12
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] >= vfrB[7:0]
   vfrA[15:8] >= vfrB[15:8]
   vfrA[23:16] >= vfrB[23:16]
   vfrA[31:24] >= vfrB[31:24]
   vfrA[39:32] >= vfrB[39:32]
   vfrA[47:40] >= vfrB[47:40]
   vfrA[55:48] >= vfrB[55:48]
   vfrA[63:56] >= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_ge.h **Vector Half-Word Elements All Greater or Equal Than** **lv.all_ge.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x13
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] >= vfrB[15:0]
   vfrA[31:16] >= vfrB[31:16]
   vfrA[47:32] >= vfrB[47:32]
   vfrA[63:48] >= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_gt.b **Vector Byte Elements All Greater Than** **lv.all_gt.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x14
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] > vfrB[7:0]
   vfrA[15:8] > vfrB[15:8]
   vfrA[23:16] > vfrB[23:16]
   vfrA[31:24] > vfrB[31:24]
   vfrA[39:32] > vfrB[39:32]
   vfrA[47:40] > vfrB[47:40]
   vfrA[55:48] > vfrB[55:48]
   vfrA[63:56] > vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_gt.h — Vector Half-Word Elements All Greater Than — lv.all_gt.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x15
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are greater than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] > vfrB[15:0]
   vfrA[31:16] > vfrB[31:16]
   vfrA[47:32] > vfrB[47:32]
   vfrA[63:48] > vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_le.b **Vector Byte Elements All Less or Equal Than** **lv.all_le.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x16
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] <= vfrB[7:0]
   vfrA[15:8] <= vfrB[15:8]
   vfrA[23:16] <= vfrB[23:16]
   vfrA[31:24] <= vfrB[31:24]
   vfrA[39:32] <= vfrB[39:32]
   vfrA[47:40] <= vfrB[47:40]
   vfrA[55:48] <= vfrB[55:48]
   vfrA[63:56] <= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_le.h **Vector Half-Word Elements All Less or Equal Than** **lv.all_le.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x17
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less or equal than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] ,= vfrB[15:0]
   vfrA[31:16] <= vfrB[31:16]
   vfrA[47:32] <= vfrB[47:32]
   vfrA[63:48] <= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_lt.b Vector Byte Elements All Less Than lv.all_lt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x18
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] < vfrB[7:0]
   vfrA[15:8] < vfrB[15:8]
   vfrA[23:16] < vfrB[23:16]
   vfrA[31:24] < vfrB[31:24]
   vfrA[39:32] < vfrB[39:32]
   vfrA[47:40] < vfrB[47:40]
   vfrA[55:48] < vfrB[55:48]
   vfrA[63:56] < vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_lt.h **Vector Half-Word Elements All Less Than** **lv.all_lt.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x19
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all elements of vfrA are less than elements of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] < vfrB[15:0]
   vfrA[31:16] < vfrB[31:16]
   vfrA[47:32] < vfrB[47:32]
   vfrA[63:48] < vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_ne.b Vector Byte Elements All Not Equal lv.all_ne.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x1a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] != vfrB[7:0]
   vfrA[15:8] != vfrB[15:8]
   vfrA[23:16] != vfrB[23:16]
   vfrA[31:24] != vfrB[31:24]
   vfrA[39:32] != vfrB[39:32]
   vfrA[47:40] != vfrB[47:40]
   vfrA[55:48] != vfrB[55:48]
   vfrA[63:56] != vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.all_ne.h **Vector Half-Word Elements All Not Equal** **lv.all_ne.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x1b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.all_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if all corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] != vfrB[15:0]
   vfrA[31:16] != vfrB[31:16]
   vfrA[47:32] != vfrB[47:32]
   vfrA[63:48] != vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.and **Vector And** **lv.and**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x38
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.and rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical AND operation. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] AND vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_eq.b **Vector Byte Elements Any Equal** **lv.any_eq.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x20
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] == vfrB[7:0] ||
   vfrA[15:8] == vfrB[15:8] ||
   vfrA[23:16] == vfrB[23:16] ||
   vfrA[31:24] == vfrB[31:24] ||
   vfrA[39:32] == vfrB[39:32] ||
   vfrA[47:40] == vfrB[47:40] ||
   vfrA[55:48] == vfrB[55:48] ||
   vfrA[63:56] == vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_eq.h — Vector Half-Word Elements Any Equal — lv.any_eq.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x21
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] == vfrB[15:0] ||
   vfrA[31:16] == vfrB[31:16] ||
   vfrA[47:32] == vfrB[47:32] ||
   vfrA[63:48] == vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_ge.b **Vector Byte Elements Any Greater or Equal Than** **lv.any_ge.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x22
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] >= vfrB[7:0] ||
   vfrA[15:8] >= vfrB[15:8] ||
   vfrA[23:16] >= vfrB[23:16] ||
   vfrA[31:24] >= vfrB[31:24] ||
   vfrA[39:32] >= vfrB[39:32] ||
   vfrA[47:40] >= vfrB[47:40] ||
   vfrA[55:48] >= vfrB[55:48] ||
   vfrA[63:56] >= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_ge.h **Vector Half-Word Elements Any Greater or Equal Than** **lv.any_ge.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x23
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] >= vfrB[15:0] ||
   vfrA[31:16] >= vfrB[31:16] ||
   vfrA[47:32] >= vfrB[47:32] ||
   vfrA[63:48] >= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_gt.b   Vector Byte Elements Any Greater Than   lv.any_gt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x24
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] > vfrB[7:0] ||
   vfrA[15:8] > vfrB[15:8] ||
   vfrA[23:16] > vfrB[23:16] ||
   vfrA[31:24] > vfrB[31:24] ||
   vfrA[39:32] > vfrB[39:32] ||
   vfrA[47:40] > vfrB[47:40] ||
   vfrA[55:48] > vfrB[55:48] ||
   vfrA[63:56] > vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_gt.h **Vector Half-Word Elements Any Greater Than** **lv.any_gt.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x25
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is greater than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] > vfrB[15:0] ||
   vfrA[31:16] > vfrB[31:16] ||
   vfrA[47:32] > vfrB[47:32] ||
   vfrA[63:48] > vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_le.b **Vector Byte Elements Any Less or Equal Than** **lv.any_le.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x26
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] <= vfrB[7:0] ||
   vfrA[15:8] <= vfrB[15:8] ||
   vfrA[23:16] <= vfrB[23:16] ||
   vfrA[31:24] <= vfrB[31:24] ||
   vfrA[39:32] <= vfrB[39:32] ||
   vfrA[47:40] <= vfrB[47:40] ||
   vfrA[55:48] <= vfrB[55:48] ||
   vfrA[63:56] <= vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_le.h **Vector Half-Word Elements Any Less or Equal Than** **lv.any_le.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x27
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less or equal than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] ,= vfrB[15:0] ||
   vfrA[31:16] <= vfrB[31:16] ||
   vfrA[47:32] <= vfrB[47:32] ||
   vfrA[63:48] <= vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_lt.b Vector Byte Elements Any Less Than lv.any_lt.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x28
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] < vfrB[7:0] ||
   vfrA[15:8] < vfrB[15:8] ||
   vfrA[23:16] < vfrB[23:16] ||
   vfrA[31:24] < vfrB[31:24] ||
   vfrA[39:32] < vfrB[39:32] ||
   vfrA[47:40] < vfrB[47:40] ||
   vfrA[55:48] < vfrB[55:48] ||
   vfrA[63:56] < vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_lt.h **Vector Half-Word Elements Any Less Than** **lv.any_lt.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x29
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any element of vfrA is less than corresponding element of vfrB;otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] < vfrB[15:0] ||
   vfrA[31:16] < vfrB[31:16] ||
   vfrA[47:32] < vfrB[47:32] ||
   vfrA[63:48] < vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_ne.b — Vector Byte Elements Any Not Equal — lv.any_ne.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x2a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[7:0] != vfrB[7:0] ||
   vfrA[15:8] != vfrB[15:8] ||
   vfrA[23:16] != vfrB[23:16] ||
   vfrA[31:24] != vfrB[31:24] ||
   vfrA[39:32] != vfrB[39:32] ||
   vfrA[47:40] != vfrB[47:40] ||
   vfrA[55:48] != vfrB[55:48] ||
   vfrA[63:56] != vfrB[63:56]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.any_ne.h **Vector Half-Word Elements Any Not Equal** **lv.any_ne.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x2b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.any_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Compare flag is set if any two corresponding elements are not equal; otherwise compare flag is cleared.
Compare flag is replicated into all bit positions of vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
flag <- vfrA[15:0] != vfrB[15:0] ||
   vfrA[31:16] != vfrB[31:16] ||
   vfrA[47:32] != vfrB[47:32] ||
   vfrA[63:48] != vfrB[63:48]vfrD[63:0] <- repl(flag)
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.avg.b **Vector Byte Elements Average** **lv.avg.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x39
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.avg.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are added to the byte elements of vector/floating-point register vfrB and the sum is shifted right by one to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- (vfrA[7:0] + vfrB[7:0]) » 1
   vfrD[15:8] <- (vfrA[15:8] + vfrB[15:8]) » 1
   vfrD[23:16] <- (vfrA[23:16] + vfrB[23:16]) » 1
   vfrD[31:24] <- (vfrA[31:24] + vfrB[31:24]) » 1
   vfrD[39:32] <- (vfrA[39:32] + vfrB[39:32]) » 1
   vfrD[47:40] <- (vfrA[47:40] + vfrB[47:40]) » 1
   vfrD[55:48] <- (vfrA[55:48] + vfrB[55:48]) » 1
   vfrD[63:56] <- (vfrA[63:56] + vfrB[63:56]) » 1
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.avg.h — Vector Half-Word Elements Average — lv.avg.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x3a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.avg.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are added to the half-word elements of vector/floating-point register vfrB and the sum is shifted right by one to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- (vfrA[15:0] + vfrB[15:0]) » 1
   vfrD[31:16] <- (vfrA[31:16] + vfrB[31:16]) » 1
   vfrD[47:32] <- (vfrA[47:32] + vfrB[47:32]) » 1
   vfrD[63:48] <- (vfrA[63:48] + vfrB[63:48]) » 1
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_eq.b **Vector Byte Elements Compare Equal** **lv.cmp_eq.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x40
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_eq.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are equal; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- repl(vfrA[7:0] == vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] == vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] == vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] == vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] == vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] == vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] == vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] == vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_eq.h **Vector Half-Word Elements Compare Equal** **lv.cmp_eq.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x41
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_eq.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are equal; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- repl(vfrA[7:0] == vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] == vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] == vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] == vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_ge.b **Vector Byte Elements Compare Greater Than or Equal** **lv.cmp_ge.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x42
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ge.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- repl(vfrA[7:0] >= vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] >= vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] >= vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] >= vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] >= vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] >= vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] >= vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] >= vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_ge.h **Vector Half-Word Elements Compare Greater Than or Equal** **lv.cmp_ge.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x43
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ge.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- repl(vfrA[7:0] >= vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] >= vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] >= vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] >= vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_gt.b **Vector Byte Elements Compare Greater Than** **lv.cmp_gt.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x44
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_gt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- repl(vfrA[7:0] > vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] > vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] > vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] > vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] > vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] > vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] > vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] > vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_gt.h **Vector Half-Word Elements Compare Greater Than** **lv.cmp_gt.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x45
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_gt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is greater than element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- repl(vfrA[7:0] > vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] > vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] > vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] > vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_le.b **Vector Byte Elements Compare Less Than or Equal** **lv.cmp_le.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x46
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_le.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] <= vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] <= vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] <= vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] <= vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] <= vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_le.h **Vector Half-Word Elements Compare Less Than or Equal** **lv.cmp_le.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x47
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_le.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than or equal to element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] <= vfrB[55:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_lt.b **Vector Byte Elements Compare Less Than** **lv.cmp_lt.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x48
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_lt.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[15:8] <- repl(vfrA[15:8] <= vfrB[15:8]
   vfrD[23:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[31:24] <- repl(vfrA[31:24] <= vfrB[31:24]
   vfrD[39:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[47:40] <- repl(vfrA[47:40] <= vfrB[47:40]
   vfrD[55:48] <- repl(vfrA[55:48] <= vfrB[55:48]
   vfrD[63:56] <- repl(vfrA[63:56] <= vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_lt.h **Vector Half-Word Elements Compare Less Than** **lv.cmp_lt.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x49
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_lt.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if element in vfrA is less than element in vfrB; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- repl(vfrA[7:0] <= vfrB[7:0]
   vfrD[31:16] <- repl(vfrA[23:16] <= vfrB[23:16]
   vfrD[47:32] <- repl(vfrA[39:32] <= vfrB[39:32]
   vfrD[63:48] <- repl(vfrA[55:48] <= vfrB[55:48]
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_ne.b **Vector Byte Elements Compare Not Equal** **lv.cmp_ne.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x4a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ne.b rD,rA,rB
```

Description:

All byte elements of vector/floating-point register vfrA are compared to byte elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are not equal; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- repl(vfrA[7:0] != vfrB[7:0])
   vfrD[15:8] <- repl(vfrA[15:8] != vfrB[15:8])
   vfrD[23:16] <- repl(vfrA[23:16] != vfrB[23:16])
   vfrD[31:24] <- repl(vfrA[31:24] != vfrB[31:24])
   vfrD[39:32] <- repl(vfrA[39:32] != vfrB[39:32])
   vfrD[47:40] <- repl(vfrA[47:40] != vfrB[47:40])
   vfrD[55:48] <- repl(vfrA[55:48] != vfrB[55:48])
   vfrD[63:56] <- repl(vfrA[63:56] != vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.cmp_ne.h **Vector Half-Word Elements Compare Not Equal** **lv.cmp_ne.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x4b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.cmp_ne.h rD,rA,rB
```

Description:

All half-word elements of vector/floating-point register vfrA are compared to half-word elements of vector/floating-point register vfrB. Bits of the element in vector/floating-point register vfrD are set if two corresponding compared elements are not equal; otherwise element bits are cleared.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- repl(vfrA[7:0] != vfrB[7:0])
   vfrD[31:16] <- repl(vfrA[23:16] != vfrB[23:16])
   vfrD[47:32] <- repl(vfrA[39:32] != vfrB[39:32])
   vfrD[63:48] <- repl(vfrA[55:48] != vfrB[55:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.madds.h **Vector Half-Word Elements Multiply Add Signed Saturated** **lv.madds.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x54
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.madds.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form intermediate results. They are added to the signed half-word VMAC elements to form the final results that are placed again in VMAC registers. Intermediate result is placed into vector/floating-point register vfrD. If any of the final results exceeds min/max value, it is saturated.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- sat32s(vfrA[15:0] * vfrB[15:0] + VMACLO[31:0])
   vfrD[31:16] <- sat32s(vfrA[31:16] * vfrB[31:16] + VMACLO[63:32])
   vfrD[47:32] <- sat32s(vfrA[47:32] * vfrB[47:32] + VMACHI[31:0])
   vfrD[63:48] <- sat32s(vfrA[63:48] * vfrB[63:48] + VMACHI[63:32])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.max.b **Vector Byte Elements Maximum** **lv.max.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x55
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.max.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB and larger elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] > vfrB[7:0] ?  vfrA[7:0] :  vrfB[7:0]
   vfrD[15:8] <- vfrA[15:8] > vfrB[15:8] ?  vfrA[15:8] :  vrfB[15:8]
   vfrD[23:16] <- vfrA[23:16] > vfrB[23:16] ?  vfrA[23:16] :  vrfB[23:16]
   vfrD[31:24] <- vfrA[31:24] > vfrB[31:24] ?  vfrA[31:24] :  vrfB[31:24]
   vfrD[39:32] <- vfrA[39:32] > vfrB[39:32] ?  vfrA[39:32] :  vrfB[39:32]
   vfrD[47:40] <- vfrA[47:40] > vfrB[47:40] ?  vfrA[47:40] :  vrfB[47:40]
   vfrD[55:48] <- vfrA[55:48] > vfrB[55:48] ?  vfrA[55:48] :  vrfB[55:48]
   vfrD[63:56] <- vfrA[63:56] > vfrB[63:56] ?  vfrA[63:56] :  vrfB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.max.h **Vector Half-Word Elements Maximum** **lv.max.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x56
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.max.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB and larger elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] > vfrB[15:0] ?  vfrA[15:0] :  vrfB[15:0]
   vfrD[31:16] <- vfrA[31:16] > vfrB[31:16] ?  vfrA[31:16] :  vrfB[31:16]
   vfrD[47:32] <- vfrA[47:32] > vfrB[47:32] ?  vfrA[47:32] :  vrfB[47:32]
   vfrD[63:48] <- vfrA[63:48] > vfrB[63:48] ?  vfrA[63:48] :  vrfB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.merge.b **Vector Byte Elements Merge** **lv.merge.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x57
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.merge.b rD,rA,rB
```

Description:

Byte elements of the lower half of the vector/floating-point register vfrA are combined with the byte elements of the lower half of vector/floating-point register vfrB in such a way that lowest element is from the vfrB, second element from the vfrA, third again from the vfrB etc. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8]
   vfrD[23:16] <- vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24]
   vfrD[39:32] <- vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40]
   vfrD[55:48] <- vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.merge.h Vector Half-Word Elements Merge lv.merge.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x58
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.merge.h rD,rA,rB
```

Description:

Half-word elements of the lower half of the vector/floating-point register vfrA are combined with the byte elements of the lower half of vector/floating-point register vfrB in such a way that lowest element is from the vfrB, second element from the vfrA, third again from the vfrB etc. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16]
   vfrD[47:32] <- vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.min.b **Vector Byte Elements Minimum** **lv.min.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x59
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.min.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrA are compared to the byte elements of vector/floating-point register vfrB and smaller elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] < vfrB[7:0] ?  vfrA[7:0] :  vrfB[7:0]
   vfrD[15:8] <- vfrA[15:8] < vfrB[15:8] ?  vfrA[15:8] :  vrfB[15:8]
   vfrD[23:16] <- vfrA[23:16] < vfrB[23:16] ?  vfrA[23:16] :  vrfB[23:16]
   vfrD[31:24] <- vfrA[31:24] < vfrB[31:24] ?  vfrA[31:24] :  vrfB[31:24]
   vfrD[39:32] <- vfrA[39:32] < vfrB[39:32] ?  vfrA[39:32] :  vrfB[39:32]
   vfrD[47:40] <- vfrA[47:40] < vfrB[47:40] ?  vfrA[47:40] :  vrfB[47:40]
   vfrD[55:48] <- vfrA[55:48] < vfrB[55:48] ?  vfrA[55:48] :  vrfB[55:48]
   vfrD[63:56] <- vfrA[63:56] < vfrB[63:56] ?  vfrA[63:56] :  vrfB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.min.h Vector Half-Word Elements Minimum lv.min.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.min.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrA are compared to the half-word elements of vector/floating-point register vfrB and smaller elements are selected to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] < vfrB[15:0] ?  vfrA[15:0] :  vrfB[15:0]
   vfrD[31:16] <- vfrA[31:16] < vfrB[31:16] ?  vfrA[31:16] :  vrfB[31:16]
   vfrD[47:32] <- vfrA[47:32] < vfrB[47:32] ?  vfrA[47:32] :  vrfB[47:32]
   vfrD[63:48] <- vfrA[63:48] < vfrB[63:48] ?  vfrA[63:48] :  vrfB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.msubs.h **Vector Half-Word Elements Multiply Subtract Signed Saturated** **lv.msubs.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.msubs.h rD,rA,rB
```

Description:

The signed half-word elements of vector/floating-point register vfrA are multiplied by the signed half-word elements of vector/floating-point register vfrB to form intermediate results. They are subtracted from the signed half-word VMAC elements to form the final results that are placed again in VMAC registers. Intermediate result is placed into vector/floating-point register vfrD. If any of the final results exceeds min/max value, it is saturated.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- sat32s(VMACLO[31:0] - vfrA[15:0] * vfrB[15:0])
   vfrD[31:16] <- sat32s(VMACLO[63:32] - vfrA[31:16] * vfrB[31:16])
   vfrD[47:32] <- sat32s(VMACHI[31:0] - vfrA[47:32] * vfrB[47:32])
   vfrD[63:48] <- sat32s(VMACHI[63:32] - vfrA[63:48] * vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.nand **Vector Not And** **lv.nand**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.nand rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical NAND operation. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] NAND vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.nor **Vector Not Or** **lv.nor**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5e
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.nor rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical NOR operation. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] NOR vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.or **Vector Or** **lv.or**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x5f
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.or rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical OR operation. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] OR vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.pack.b **Vector Byte Elements Pack** **lv.pack.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x60
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.pack.b rD,rA,rB
```

Description:

Lower half of the byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the byte truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[3:0] <- vfrB[3:0]
   vfrD[7:4] <- vfrB[11:8]
   vfrD[11:8] <- vfrB[19:16]
   vfrD[15:12] <- vfrB[27:24]
   vfrD[19:16] <- vfrB[35:32]
   vfrD[23:20] <- vfrB[43:40]
   vfrD[27:24] <- vfrB[51:48]
   vfrD[31:28] <- vfrB[59:56]
   vfrD[35:32] <- vfrA[3:0]
   vfrD[39:36] <- vfrA[11:8]
   vfrD[43:40] <- vfrA[19:16]
   vfrD[47:44] <- vfrA[27:24]
   vfrD[51:48] <- vfrA[35:32]
   vfrD[55:52] <- vfrA[43:40]
   vfrD[59:56] <- vfrA[51:48]
   vfrD[63:60] <- vfrA[59:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.pack.h **Vector Half-word Elements Pack** **lv.pack.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x61
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.pack.h rD,rA,rB
```

Description:

Lower half of the half-word elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the half-word truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrB[15:0]
   vfrD[15:8] <- vfrB[31:16]
   vfrD[23:16] <- vfrB[47:32]
   vfrD[31:24] <- vfrB[63:48]
   vfrD[39:32] <- vfrA[15:0]
   vfrD[47:40] <- vfrA[31:16]
   vfrD[55:48] <- vfrA[47:32]
   vfrD[63:56] <- vfrA[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.packs.b Vector Byte Elements Pack Signed Saturated lv.packs.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x62
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packs.b rD,rA,rB
```

Description:

Lower half of the signed byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the signed byte truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds signed 4-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[3:0] <- sat4s(vfrB[7:0]
   vfrD[7:4] <- sat4s(vfrB[15:8]
   vfrD[11:8] <- sat4s(vfrB[23:16]
   vfrD[15:12] <- sat4s(vfrB[31:24]
   vfrD[19:16] <- sat4s(vfrB[39:32]
   vfrD[23:20] <- sat4s(vfrB[47:40]
   vfrD[27:24] <- sat4s(vfrB[55:48]
   vfrD[31:28] <- sat4s(vfrB[63:56]
   vfrD[35:32] <- sat4s(vfrA[7:0]
   vfrD[39:36] <- sat4s(vfrA[15:8]
   vfrD[43:40] <- sat4s(vfrA[23:16]
   vfrD[47:44] <- sat4s(vfrA[31:24]
   vfrD[51:48] <- sat4s(vfrA[39:32]
   vfrD[55:52] <- sat4s(vfrA[47:40]
   vfrD[59:56] <- sat4s(vfrA[55:48]
   vfrD[63:60] <- sat4s(vfrA[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.packs.h **Vector Half-word Elements Pack Signed Saturated** **lv.packs.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x63
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packs.h rD,rA,rB
```

Description:

Lower half of the signed halfpword elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the signed half-word truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds signed 8-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- sat8s(vfrB[15:0])
   vfrD[15:8] <- sat8s(vfrB[31:16])
   vfrD[23:16] <- sat8s(vfrB[47:32])
   vfrD[31:24] <- sat8s(vfrB[63:48])
   vfrD[39:32] <- sat8s(vfrA[15:0])
   vfrD[47:40] <- sat8s(vfrA[31:16])
   vfrD[55:48] <- sat8s(vfrA[47:32])
   vfrD[63:56] <- sat8s(vfrA[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.packus.b **Vector Byte Elements Pack Unsigned Saturated** **lv.packus.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x64
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packus.b rD,rA,rB
```

Description:

Lower half of the unsigned byte elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the unsigned byte truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds unsigned 4-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[3:0] <- sat4u(vfrB[7:0]
   vfrD[7:4] <- sat4u(vfrB[15:8]
   vfrD[11:8] <- sat4u(vfrB[23:16]
   vfrD[15:12] <- sat4u(vfrB[31:24]
   vfrD[19:16] <- sat4u(vfrB[39:32]
   vfrD[23:20] <- sat4u(vfrB[47:40]
   vfrD[27:24] <- sat4u(vfrB[55:48]
   vfrD[31:28] <- sat4u(vfrB[63:56]
   vfrD[35:32] <- sat4u(vfrA[7:0]
   vfrD[39:36] <- sat4u(vfrA[15:8]
   vfrD[43:40] <- sat4u(vfrA[23:16]
   vfrD[47:44] <- sat4u(vfrA[31:24]
   vfrD[51:48] <- sat4u(vfrA[39:32]
   vfrD[55:52] <- sat4u(vfrA[47:40]
   vfrD[59:56] <- sat4u(vfrA[55:48]
   vfrD[63:60] <- sat4u(vfrA[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.packus.h **Vector Half-word Elements Pack Unsigned Saturated** **lv.packus.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x65
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.packus.h rD,rA,rB
```

Description:

Lower half of the unsigned halfpword elements of the vector/floating-point register vfrA are truncated and combined with the lower half of the unsigned half-word truncated elements of the vector/floating-point register vfrB in such a way that lowest elements are from vfrB and highest element from vfrA. If any truncated element exceeds unsigned 8-bit value, it is saturated. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- sat8u(vfrB[15:0])
   vfrD[15:8] <- sat8u(vfrB[31:16])
   vfrD[23:16] <- sat8u(vfrB[47:32])
   vfrD[31:24] <- sat8u(vfrB[63:48])
   vfrD[39:32] <- sat8u(vfrA[15:0])
   vfrD[47:40] <- sat8u(vfrA[31:16])
   vfrD[55:48] <- sat8u(vfrA[47:32])
   vfrD[63:56] <- sat8u(vfrA[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.perm.n — Vector Nibble Elements Permute — lv.perm.n

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x66
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.perm.n rD,rA,rB
```

Description:

The 4-bit elements of vector/floating-point register vfrA are permuted according to corresponding 4-bit values in vector/floating-point register vfrB. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[3:0] <- vfrA[vfrB[3:0]*4+3:vfrB[3:0]*4]
   vfrD[7:4] <- vfrA[vfrB[7:4]*4+3:vfrB[7:4]*4]
   vfrD[11:8] <- vfrA[vfrB[11:8]*4+3:vfrB[11:8]*4]
   vfrD[15:12] <- vfrA[vfrB[15:12]*4+3:vfrB[15:12]*4]
   vfrD[19:16] <- vfrA[vfrB[19:16]*4+3:vfrB[19:16]*4]
   vfrD[23:20] <- vfrA[vfrB[23:20]*4+3:vfrB[23:20]*4]
   vfrD[27:24] <- vfrA[vfrB[27:24]*4+3:vfrB[27:24]*4]
   vfrD[31:28] <- vfrA[vfrB[31:28]*4+3:vfrB[31:28]*4]
   vfrD[35:32] <- vfrA[vfrB[35:32]*4+3:vfrB[35:32]*4]
   vfrD[39:36] <- vfrA[vfrB[39:36]*4+3:vfrB[39:36]*4]
   vfrD[43:40] <- vfrA[vfrB[43:40]*4+3:vfrB[43:40]*4]
   vfrD[47:44] <- vfrA[vfrB[47:44]*4+3:vfrB[47:44]*4]
   vfrD[51:48] <- vfrA[vfrB[51:48]*4+3:vfrB[51:48]*4]
   vfrD[55:52] <- vfrA[vfrB[55:52]*4+3:vfrB[55:52]*4]
   vfrD[59:56] <- vfrA[vfrB[59:56]*4+3:vfrB[59:56]*4]
   vfrD[63:60] <- vfrA[vfrB[63:60]*4+3:vfrB[63:60]*4]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.rl.b **Vector Byte Elements Rotate Left** **lv.rl.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x67
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.rl.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are rotated left by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] rl vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] rl vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] rl vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] rl vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] rl vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] rl vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] rl vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] rl vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.rl.h **Vector Half-Word Elements Rotate Left** **lv.rl.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x68
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.rl.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are rotated left by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] rl vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] rl vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] rl vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] rl vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sll **Vector Shift Left Logical** **lv.sll**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sll rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are shifted left by the number of bits specified in lower 4 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the low-order bits of vfrD. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] « vfrB[2:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sll.b **Vector Byte Elements Shift Left Logical** **lv.sll.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x69
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sll.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted left by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the low-order bits elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] « vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] « vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] « vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] « vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] « vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] « vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] « vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] « vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sll.h **Vector Half-Word Elements Shift Left Logical** **lv.sll.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sll.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted left by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting zeros into the low-order bits elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] « vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] « vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] « vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] « vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sra.b **Vector Byte Elements Shift Right Arithmetic** **lv.sra.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6e
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sra.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB, inserting most significat bit of each element into the high-order bits. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] sra vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] sra vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] sra vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] sra vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] sra vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] sra vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] sra vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] sra vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sra.h **Vector Half-Word Elements Shift Right Arithmetic** **lv.sra.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6f
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sra.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting most significant bit of each element into the low-order bits. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] sra vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] sra vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] sra vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] sra vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.srl **Vector Shift Right Logical** **lv.srl**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x70
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.srl rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 4 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the high-order bits of vfrD. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] » vfrB[2:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.srl.b **Vector Byte Elements Shift Right Logical** **lv.srl.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6c
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.srl.b rD,rA,rB
```

Description:

The contents of byte elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 3 bits in each byte element of vector/floating-point register vfrB, inserting zeros into the high-order bits elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] » vfrB[2:0]
   vfrD[15:8] <- vfrA[15:8] » vfrB[10:8]
   vfrD[23:16] <- vfrA[23:16] » vfrB[18:16]
   vfrD[31:24] <- vfrA[31:24] » vfrB[26:24]
   vfrD[39:32] <- vfrA[39:32] » vfrB[34:32]
   vfrD[47:40] <- vfrA[47:40] » vfrB[42:40]
   vfrD[55:48] <- vfrA[55:48] » vfrB[50:48]
   vfrD[63:56] <- vfrA[63:56] » vfrB[58:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.srl.h **Vector Half-Word Elements Shift Right Logical** **lv.srl.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x6d
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.srl.h rD,rA,rB
```

Description:

The contents of half-word elements of vector/floating-point register vfrA are shifted right by the number of bits specified in lower 4 bits in each half-word element of vector/floating-point register vfrB, inserting zeros into the low-order bits of elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] » vfrB[3:0]
   vfrD[31:16] <- vfrA[31:16] » vfrB[19:16]
   vfrD[47:32] <- vfrA[47:32] » vfrB[35:32]
   vfrD[63:48] <- vfrA[63:48] » vfrB[51:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sub.b **Vector Byte Elements Subtract Signed** **lv.sub.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x71
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sub.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrB are subtracted from the byte elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] - vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] - vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] - vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] - vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] - vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] - vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] - vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] - vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.sub.h Vector Half-Word Elements Subtract Signed lv.sub.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x72
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.sub.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrB are subtracted from the half-word elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] - vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] - vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] - vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] - vfrB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.subs.b **Vector Byte Elements Subtract Signed Saturated** **lv.subs.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x73
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subs.b rD,rA,rB
```

Description:

The byte elements of vector/floating-point register vfrB are subtracted from the byte elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- sat8s(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8s(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8s(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8s(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8s(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8s(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8s(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8s(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.subs.h — Vector Half-Word Elements Subtract Signed Saturated — lv.subs.h

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x74
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subs.h rD,rA,rB
```

Description:

The half-word elements of vector/floating-point register vfrB are subtracted from the half-word elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- sat16s(vfrA[15:0] - vfrB[15:0])
   vfrD[31:16] <- sat16s(vfrA[31:16] - vfrB[31:16])
   vfrD[47:32] <- sat16s(vfrA[47:32] - vfrB[47:32])
   vfrD[63:48] <- sat16s(vfrA[63:48] - vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.subu.b **Vector Byte Elements Subtract Unsigned** **lv.subu.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x75
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subu.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrB are subtracted from the unsigned byte elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- vfrA[7:0] - vfrB[7:0]
   vfrD[15:8] <- vfrA[15:8] - vfrB[15:8]
   vfrD[23:16] <- vfrA[23:16] - vfrB[23:16]
   vfrD[31:24] <- vfrA[31:24] - vfrB[31:24]
   vfrD[39:32] <- vfrA[39:32] - vfrB[39:32]
   vfrD[47:40] <- vfrA[47:40] - vfrB[47:40]
   vfrD[55:48] <- vfrA[55:48] - vfrB[55:48]
   vfrD[63:56] <- vfrA[63:56] - vfrB[63:56]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.subu.h **Vector Half-Word Elements Subtract Unsigned** **lv.subu.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x76
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subu.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrB are subtracted from the unsigned half-word elements of vector/floating-point register vfrA to form the result elements. Result elements are placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- vfrA[15:0] - vfrB[15:0]
   vfrD[31:16] <- vfrA[31:16] - vfrB[31:16]
   vfrD[47:32] <- vfrA[47:32] - vfrB[47:32]
   vfrD[63:48] <- vfrA[63:48] - vfrB[63:48]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.subus.b Vector Byte Elements Subtract Unsigned Saturated lv.subus.b

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x77
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subus.b rD,rA,rB
```

Description:

The unsigned byte elements of vector/floating-point register vfrB are subtracted from the unsigned byte elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- sat8u(vfrA[7:0] + vfrB[7:0])
   vfrD[15:8] <- sat8u(vfrA[15:8] + vfrB[15:8])
   vfrD[23:16] <- sat8u(vfrA[23:16] + vfrB[23:16])
   vfrD[31:24] <- sat8u(vfrA[31:24] + vfrB[31:24])
   vfrD[39:32] <- sat8u(vfrA[39:32] + vfrB[39:32])
   vfrD[47:40] <- sat8u(vfrA[47:40] + vfrB[47:40])
   vfrD[55:48] <- sat8u(vfrA[55:48] + vfrB[55:48])
   vfrD[63:56] <- sat8u(vfrA[63:56] + vfrB[63:56])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.subus.h **Vector Half-Word Elements Subtract Unsigned Saturated** **lv.subus.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x78
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.subus.h rD,rA,rB
```

Description:

The unsigned half-word elements of vector/floating-point register vfrB are subtracted from the unsigned half-word elements of vector/floating-point register vfrA to form the result elements. If the result exceeds min/max value for the destination data type, it is saturated to min/max value and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- sat16u(vfrA[15:0] - vfrB[15:0])
   vfrD[31:16] <- sat16u(vfrA[31:16] - vfrB[31:16])
   vfrD[47:32] <- sat16u(vfrA[47:32] - vfrB[47:32])
   vfrD[63:48] <- sat16u(vfrA[63:48] - vfrB[63:48])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.unpack.b **Vector Byte Elements Unpack** **lv.unpack.b**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x79
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.unpack.b rD,rA,rB
```

Description:

Lower half of 4-bit elements in vector/floating-point register vfrA are sign-extended and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[7:0] <- exts(vfrA[3:0])
   vfrD[15:8] <- exts(vfrA[7:4])
   vfrD[23:16] <- exts(vfrA[11:8])
   vfrD[31:24] <- exts(vfrA[15:12])
   vfrD[39:32] <- exts(vfrA[19:16])
   vfrD[47:40] <- exts(vfrA[23:20])
   vfrD[55:48] <- exts(vfrA[27:24])
   vfrD[63:56] <- exts(vfrA[31:28])
```

Exceptions:

None

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.unpack.h **Vector Half-Word Elements Unpack** **lv.unpack.h**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x7a
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.unpack.h rD,rA,rB
```

Description:

Lower half of 8-bit elements in vector/floating-point register vfrA are sign-extended and placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[15:0] <- exts(vfrA[7:0])
   vfrD[31:16] <- exts(vfrA[15:8])
   vfrD[47:32] <- exts(vfrA[23:16])
   vfrD[63:48] <- exts(vfrA[31:24])
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required

lv.xor **Vector Exclusive Or** **lv.xor**

31 26	25 . . . 21	20 . . . 16	15 . . . 11	10 . 8	7 0
opcode 0xa	D	A	B	reserved	opcode 0x7b
6 bits	5 bits	5 bits	5 bits	3 bits	8 bits

Format:

```
lv.xor rD,rA,rB
```

Description:

The contents of vector/floating-point register vfrA are combined with the contents of vector/floating-point register vfrB in a bit-wise logical XOR operation. The result is placed into vector/floating-point register vfrD.

32-bit Operation:

64-bit Operation:

```
vfrD[63:0] <- vfrA[63:0] XOR vfrB[63:0]
```

Exceptions:

```
None
```

Notes:

Instruction Subset	Implementation
ORVDX64 I	Required